

## X-DA4060-B High Efficiency Power Amplifier

- Four channel 60W high efficiency Class-D amplifier
- Automatic protection
- Fault detection
- Effective ventilation using forced air cooling fan
- CE certification complied



X-DA4060 High Efficiency Power Amplifier provides amplification for audio signal delivered by high power loudspeakers that are connected to X-618 Digital Public Address and Voice Alarm System. X-DA4060 is reliable, efficient and light in weight.

### Features

#### INPUT/OUTPUT

X-DA4060 supports both balance and unbalanced audio inputs. To receive unbalanced audio inputs, simply connect the ground port with the negative input port to the rear panel.

X-DA4060 can receive audio signal from X-DCS2000/EN via Ethernet through the RJ45 standard port.

#### FAULT DETECTION

X-DA4060 can self-protect from overheat, over current, over voltage and under voltage. For example, when the internal temperature reaches its critical limit, the overheat protection circuit will shut down the power amplification module and activate the protection indicator light on the front panel.

X-DA4060 can detect power supply errors automatically during operation. The built-in fuse will provide overcurrent protection to the main power supply.

When a short circuit is detected in the main power circuit, the power will be automatically shut down. The backup power will then be enabled to replace the main one.

When a fault, self-protection or self-testing happens, its audio input fault port on the rear panel will short circuit and a fault signal will then be sent to the control unit in the network.

#### SAFETY

The device adopts lightweight design. The front panel is made of UL94V-0 fire proof ABS material, protecting the machine under extreme conditions. A cooling fan is equipped for heat exhaustion so that the machine can maintain high working efficiency.

#### VOLUME CONTROL

When HN-D32N Noise Detector is installed, X-DA4060 can adjust volume according to the ambient noise automatically to ensure high sound intelligibility.

#### INDICATORS

- Power light
- AC fault light x 2
- Signal light (for each channel)
- Clip light (for each channel)
- Protection light (for each channel)

## INTERFACES

- Main power and backup power port
- Audio inputs (balanced or unbalanced)
- Audio outputs (100V or 70V)
- RJ-45 net cable port

## Certification and Standard

Category	Region	Certification
Safety	Europe	CE Complied
Safety	Europe	CB Certified
Material	USA	UL94V-0 Fire-proof ABS material

## Technical Specifications

Parameter	Value
Nominal output power	4 × 60 W
Main power supply voltage	~ 220 - 240 V, 50/60 Hz
Backup power supply voltage	~ 220 - 240 V, 50/60 Hz
Power consumption	< 320 W
Main power supply protection	T3.15 AL 250 V
Speaker output voltage	100 V / 70 V
Frequency response	70 Hz -18 kHz ( +1 dB ~ -3 dB )
Input sensitivity	1.414 V <sub>RMS</sub>
Input impedance	20 kΩ
SNR	> 90 dB(with A-Weight)
Non-linear distortion	< 0.05 % (at 1/3 rated power, 1 kHz)

Indicator lights	Power indicator light: 1 Main power fault light: 1 Backup power fault light: 1 Signal lights: 4 Peak clipping lights: 4 Equipment protection lights: 4
Number of channels	4
Operating conditions	95 % humidity, 0 °C ~ +40 °C (0 ~ 104 °F) (no condensation)
Storage temperature	-10°C ~ +55°C (14°F ~ 131°F)
Cooling method	Air cooling
Product dimensions (W×H×D)	482 × 88 × 420 mm
Package dimensions (W×H×D)	580 × 235 × 552 mm
Net weight	10.6 kg
Gross weight	13.7 kg

## Packing List

Component	Quantity
X-DA4060 High Efficiency Power Amplifier	1
Network cable	2
Input cable terminal	2
Out put cable terminal	2
AC power cable	1
Power connector kit	2
Fuse (3.15 A)	1
Plastic foot	4
Warranty card	1
Quality certificate	1
Product manual	1
Rack	2