

2.4G RF Wireless Remote Control CCT Dimmable LED Panel Light



1.Product Description

- Using RF-2.4G high frequency wireless control, lower power, far transmit distance, strong anti-interference capability, high communication rate. Stylish appearance, practical function, easily operation; Dimming & Color temperature adjustable, synchronous control.
- Stepless adjusted CCT & Dimmable, Freely switch between warm white and cool white.
- Professional circuit design, each group of LEDs work separately to avoid any problem of lighting output caused by single faulty LED.
- Wireless Control, easy to use, easy to install.

2.Technical Parameter

Model No	PL3030-22-CCT	PL6030-24-CCT	PL6060-42-CCT	PL1230-42-CCT
Size	295*295*10mm	295*595*10mm	595*595*10mm	295*1195*10mm
Input Power	22W	24W	42W	42W
Luminous Flux	1900LM	2300LM	4000 LM	4000 LM
Color Temp	2700-6500K			

3.Remote Controller Specification Parameters



Item	Parameters
Remote Controller	Multi-function/Simplified
Working Voltage	3V(AAA battery*2)
Communication Protocol	RF-2.4G HZ
Control Distance	>20M (Without Obstacle)
Number of controllable lamps	1 controller can control 99 groups of lamps, no limit to the number of lamps in one group

4.Remote Instruction (First Connect the lamp and the driver)

Operating method:

Steps of Setting ID number of lamps:

- ① Turn OFF the lamp by switch for 3 Seconds, then turn on lamp, finish step ②, ③ within 10 Seconds
- ② Press 1 or 2 numbers on the number keys of remote controller, then press "ID" key
- ③ Repeat step ② again in case of mistake, then the lamp will flash 1 time.
- ④ Turn off the lamp by switch within 10 seconds, then finish setting.

Control the lamps:

The function of the keys: as the picture on the right.

Control the single group: press the ID number of the lamp you want to control and then press one functional key (on/off, color temp, brightness).

All-control Model: press "ALL" key to control all groups.



TIMING ON/OFF:



Press the ID number of the lamp you want to set, press "ID" key.

SET: Press the number key 1-99, press "⌚" timing ON key or "⌚" timing OFF key, then finish setting. Timing units is 10 minutes.


Cancel: Press "0" key, then "⌚" timing ON key or "⌚" timing OFF key to cancel timing mode.

COPY THE ID OF CONTROLLER:

Press "  " key of one controller and "  " key of another controller at the same time, keep 6 seconds, the indicator will flash 3 times, then finish setting.

Recovery: Press the "  " key and "  " key of the controller which the ID has been copied for 6 seconds, the indicator will flash 3 times.

NIGHT LIGHT MODE:




Press "  " key when the lamp is turned off by the controller to enter the night light mode.

CIRCLE MODE:



Press the ID of the lamp, then press "     " (left, right, up, down) to enter the circle mode.

SCENE MODE: The system can save two scenes : "A" and "B"

Save:

- ① Adjust the light as your preference.
- ② Press the ID number of the lamp.
- ③ Press "  " key and then press "  " or "  ", the lamp will flash 1 time, then the scene will be saved.

Recall:

- ① Press the ID number of the lamp.
- ② Press "  " or "  ", the lamp will enter the scene you preset.