



Sigen Energy Gateway HomeMax

- Multiple breaker positions reserved for SigenStor or other loads
- Seamless switch to backup mode, worry-free energy usage
- Ready for generator, heat pump or other controllable loads
- Support both whole home backup & partial home backup
- 350 ms reverse power flow protection of grid & generator
- Uninterrupted power supply through PV+ESS/grid/generator



Sigen Energy Gateway HomeMax

Sigen Gateway	HomeMax SP 12K	HomeMax TP	Units
Grid Connection			
Grid connection type	Single phase	Three phase	
Nominal AC voltage	220 / 230 / 240	380 / 400	V
Nominal AC current	100	76	A
Nominal AC power	22 / 23 / 24	50 / 52.6	kW
Nominal AC frequency	50 / 60		Hz
Disruption time of backup switch ¹	0		ms
AC Output to Backup Port			
Nominal AC voltage	220 / 230 / 240	380 / 400	V
Nominal AC current	100	76	A
Nominal AC power	22 / 23 / 24	50 / 52.6	kW
Nominal AC frequency	50 / 60		Hz
Overvoltage category	III		
Inverter Connection / EV Charger Port (optional)			
Max. number of connection	3	2	
Nominal AC voltage	220 / 230 / 240	380 / 400	V
Nominal AC current	55 (INV1), 32 (INV2), 32 (INV3) ²	38	A
Compatible EV charger power	7	11 / 22	kW
Smart Port Connection			
Generator output voltage	220 / 230 / 240	380 / 400	V
Nominal current	63	76	A
Nominal AC power	13.8 / 14.5 / 15.1	50 / 52.6	kW
Generator 2-wire start	Supported		
General Data			
Dimensions (W / H / D)	455 / 660 / 179	510 / 750 / 179	mm
Weight	19	23	kg
Storage temperature range	-40 ~ 70		°C
Operating temperature range	-30 ~ 55		°C
Relative humidity range	0% ~ 95%		
Max. operation altitude	4000		m
Cooling	Natural convection		
Ingress protection rating	IP54		
Communication	Fast Ethernet, RS485, dry contact		
Installation method	Wall mounted		

1. This refers to the load-side disruption time, to achieve this functionality Sigen Energy Gateway needs to be used together with Sigen Energy Controller and Sigen Battery. Test conditions: In the open-circuit state of the power grid, the nominal power of the Sigen Energy Controller is higher than the total power of the backup loads.
2. For Sigen Energy single phase inverter products, 8.0-12.0 kW inverters should be connected to the INV1 port, 3.0-6.0 kW inverters should be connected to the INV2/INV3 port.

Disclaimer: The information in this file is provided on an "as is" basis. To the fullest extent permitted by law, Sigen Energy Technology Co., Ltd. excludes all representations and warranties relating to this file and its contents or which is or may be provided by any affiliates or any other third party, including in relation to any inaccuracies or omissions in this file.