

What's in the Box?

| PART NO. | QTY | DESCRIPTION |
|--------------|-----|--|
| UX-RXPLUS | 1 | WUXGA+USB Receiver. Includes PS5VDC2A |
| UX-TXPLUS | 1 | WUXGA+USB Transmitter. Includes PS5VDC2A |
| Power Supply | 2 | PS5VDC2A |
| CCKVMUSB6F | 1 | Assembled KVM USB Cable, 6ft. |

Technical Specifications

| VIDEO | |
|-----------------------|---|
| Format | RGBHV, RGsB, YUV, Y/C, CVBS |
| Resolution | Up to 1920x1200VGA, SVGA, XGA, SXGA, UXGA, WUXGA |
| Input Interface (TX) | (1) HD-15 Male / USB |
| Output Interface (TX) | (1) HD-15 Female (for local display) |
| Output Interface (RX) | (1) HD-15 Female |
| USB | |
| Signal Type | USB 1.1 |
| Input Interface (TX) | (1) HD-15 Male / VGA |
| Output Interface (TX) | (2) USB Type A (Female) (for local keyboard and mouse) |
| Output Interface (RX) | (2) USB Type A (Female) |
| OTHER | |
| Power | External 100-240 VAC/5VDC2A @10W |
| Dimensions | 5 in W x 1 in H x 3 in D |
| Weight | 1 lb. |
| Approvals | UL, CE, ROHS Compliant |
| Operating Temp. | 32-131°F (0-55 °C) |
| Storage Temp. | -4-185 °F (-20-85 °C) |
| Humidity | Up to 95% |

We have simplified the output of the UX-PLUS by consolidating the VGA and USB input into one cable.



© Copyright 2011 Smart-AVI, All Rights Reserved

NOTICE

The information contained in this document is subject to change without notice. Smart-AVI makes no warranty of any kind with regard to this material, including but not limited to, implied warranties of merchantability and fitness for any particular purpose.

Smart-AVI will not be liable for errors contained herein or for incidental or consequential damages in connection with the furnishing, performance or use of this material.

No part of this document may be photocopied, reproduced or translated into another language without prior written consent from Smart-AVI.

For more information, visit www.smartavi.com.

Rack Mountable Option



Our SmartRack is the perfect solution to allow virtually all SmartAVI devices to be custom mounted in a standard 19" server rack. The SmartRack is fully adjustable and can secure/organize several devices.

Smart-AVI
SMART AUDIO VIDEO INNOVATION

Installation Manual

UX-PLUS USB KVM Extender with support for Local Display



Extend and Split WUXGA Video and USB 1.1 Keyboard and Mouse up to 500 feet over CAT5 Cable

Touchboards

Introduction

The UX-PLUS is a cross-platform WUXGA and USB KVM switch capable of sharing one computer between two consoles, one local and one remote.

Features


- Supports WUXGA video extension for resolutions up to 1920 x 1200
- Local WUXGA output for a local display
- Plug and play, no software required
- Fully compliant with USB 1.1 specifications for Keyboard and Mouse
- Built-in skew compensation
- Uses a single CAT5 UTP cable up to 500 feet
- External power adapter for transmitter and receiver unit
- Fully transparent (does not use any emulation)

Applications

- Security
- PC Networking
- Conference Center Systems
- Point of Sale
- Camera Surveillance
- Video Phone
- Control Room Systems
- Recording Studio
- PC KVM Extension
- MAC Keyboard Mouse Extender

In the medical or industrial field, where it may not be practical (or safe) to have one or more CPUs in the general vicinity, SmartAVI's VNET Switch Series is the perfect solution, allowing for either PC or Mac signals to be extended from computer to the display.

Product - Installation Diagram



Installation

1. Turn off the computer and displays.
2. Connect the VGA/USB cable from the computer into the VGA/USB connector on the UX-PLUS transmitter.
3. Connect the local display to the VGA connector on the UX-PLUS transmitter.
4. Connect the local USB keyboard and mouse to the USB connectors on the UX-PLUS transmitter.
5. Connect the remote display to the VGA connector on the UX-PLUS receiver.
6. Connect the remote USB keyboard and mouse to the USB connectors on the UX-PLUS receiver.
7. Connect the power cord to both the UX-PLUS transmitter and receiver.
8. Power on the computers and the display.

