

STOPWATCH (CHRONOGRAPH)

OPERATION MANUAL

MODE D'EMPLOI

GEBRAUCHSANWEISUNG

INSTRUCCIONES

ISTRUZIONI

ENGLISH

6D.6 FUNCTION + CRONOGRAPH + ALARM + LIGHT

S1=SELECT
S2=SET
S3=MODE
S4=LIGHT

FEATURES

1. 6D Functions (Hour, Minute, Second, Month, Date, & Day)
2. 12 or 24 hour system (Selected by user)
3. American (Month-Date) or European (Date-Month) Calendar (selected by user).
4. 1/100 sec. stopwatch with lap.
5. Daily alarm.
6. Hourly chime
7. Blue light

NORMAL MODE

- A. TIME MODE
hour system
- B. DATE MODE
Hold S1 to obtain this mode

ALARM MODE

Depress S2 to obtain the alarm time display
While S2 is being depressed, depress S1 to turn the alarm signal and the chime signal on or off

STOPWATCH MODE

The stopwatch can count up to 24 hours. The resolution is 1/100 sec for the first 40 Minutes of timing and then in 1 sec increment.
Depress S3 to enter this mode. All flags are on, STW & 1/100 are flashing to indicate stopwatch mode and 1/100 sec correspondingly

NORMAL TIME SETTING

- (Illustrated by using 12 hr. system & American Calendar)
1. Hold S3 over 2 seconds to enter the alarm time setting mode
 2. Depress S3 once to enter the time setting mode.
 3. Second start flashing. All the flags are on and the third flag is flashing to indicate time setting mode. Depress S2 to reset the second to zero. If the second is 30 or more, one minute is added to the minute display and if less than 30, the minute is not changed.
 4. Depress S1. Minute start flashing. Depress S2 to advance it (Fast advance by holding down S2 for more than 2 seconds)
 5. Depress S1. Hour starts flashing. Advance it as above.
 6. Depress S1. Month starts flashing. Advance it as above.
 7. Depress S1. Date starts flashing. Advance it as above
 8. Depress S1. Day starts flashing. Advance it as above.
 9. Depress S3 returns to the normal mode.

The setting mode is returned to the normal mode at any time by depressing S3.

ALARM THE SETTING

1. Hold S3 over 2 seconds to enter alarm setting mode
2. Hour Starts flashing. All flags are on and the second flags is flashing to indicate alarm time setting mode. Depress S2 to advance it (fast advance by holding down S2 for more than 2 seconds)
3. Depress S1. Minute starts flashing. Depress S2 to advance it
4. Depress S3 returns to the normal mode

STOPWATCH OPERATION

1. In the stopwatch mode, depress S1 to start or stop (STP is flashing) the stopwatch
2. Depress S2 while the stopwatch is counting. Lap mode is obtained (LAP is flashing). The time is frozen on the display with the stopwatch still counting. Depress S1 may start or stop this internal counting.
3. Depress S2 while the stopwatch is stopped to reset the stopwatch to zero.
4. Depress S3 to resume the normal mode

The stopwatch mode is returned to the normal mode at any time by depressing S3
The blue light will appear at any time by depressing S4.

