EZ WiFi/LAN for Mac

User's Guide



EZ WiFi/LAN is a powerful program which projects your Mac's screen player to another display wirelessly. It also provides extended display capabilities, so that you can display different content in the secondary display. Up to four video sources can be displayed simultaneously.

Features

- Full Screen Mirror and Extended Monitor wireless display
- Performance and quality settings
- Split Screen support
- Supports Mac OS 10.7 and later

System Requirements (Mac OS)

CPU	Dual Core Intel Core I 1.4GHz or higher (PowerPC not supported)
Graphic card	Intel, nVIDIA or ATI graphic card with 64MB VRAM or above
Operating System	Mac OS X 10.7 and above
Recommended Models	Mac Book series and iMac series after E/2011

Recommended System Settings (Mac OS)

СРИ	Dual Core Intel Core i5 2Ghz above
Memory	DDR 4GB
Graphic card	256MB VRAM or above
Operating System	Mac OS X 10.8
Recommended Models	Mac Book series and iMac series after E/2011

Specifications

Display Aspect Ratio	4:3, 16:9, 16:10	
OS support	Mac OS 10.7 and above	
Interface	WiFi 802.11n	
Display mode	 Mirror Display Extension Display Performance mode Quality mode Split Screen 	

First installation

1. On the EZ Suite display: Make sure that the USB WiFi adapter is inserted and enabled. Select EZ Display > EZ WiFi or select the USB Type A source from the source menu.



The WiFi Welcome screen displays. The display is ready to download the application and display wirelessly.

2. On the Mac, open the WiFi SSID list and select the access point indicated in the Welcome page. Enter the displayed PSK if encryption is enabled.



3. Open a browser and enter the IP address from the WiFi Welcome page into the address bar.

4. The Web interface of the display will open. Click the EZ Display Mac OS button.



5. Download and run EZ WiFi LAN-And-Driver-Installer.pkg.

•	O Downloads		-
-	libdvdcss.pkg 35.3 KB	0	ĺ
1	googlechrome.dmg 8.9 MB	۲	
1	MonitorTest.dmg 2.6 MB	۲	
	Citrix Online Launcher.app 273.8 KB	۲	
PSD	InFocus_RealCam_Front.psd 607.8 KB	۲	1
ZIP	LiveViewerForMacOS-v1.10.0213.zip 5.1 MB	٢	
-	EZ WiFi LAN-And-Driver-Installer.pkg 1.2 MB	٩	
Clear	20 Downloads		11.

6. Click **Continue** to begin the installation.



7. Click the location in which you would like EZ WiFi/LAN installed.



8. Click **OK** to continue the installation.



9. Click **Continue** to resume the installation.

000	Install EZWifiMac-	1.1.78
	The package was signed with a acquired this package recently, want to continue with the instal	certificate that has expired. If you it may not be authentic. Do you lation anyway?
	Show Certificate	Cancel Continue
aminuhana ta	2 alunhun ninuhun nununuhun nunuh nunuh nunuhun nunuh nunuh nunu nunuh nunu nunuh nunu nu	
	L	Go Back Continue

10. Click **Continue** to resume the installation.



11. Enter your Password to continue installation and click **Install Software**.

000	Installer is your passw	trying to install new software. Type
🖯 Introdu	Name:	InFocus
0 Destina	Password:	·····
🖯 Installa		
Summai		Cancel Install Software
minimu		
V		Go Back Continue

12. When EZ WiFi/LAN is installed, the Soundflower sound driver installation will begin. Click **Continue** to begin the installation of the sound driver.



13. Click **Continue** to resume installation.



14. The sound driver will install to the same location as EZ WiFi/LAN. Click Install to continue.

000	💝 Install Soundflower
	Standard Install on "Macintosh HD"
 Introduction Read Me License Destination Select Installation Type Installation Summary 	This will take 430 KB of space on your computer. Click Install to perform a standard installation of this software on the disk "Macintosh HD".
***	Customize Go Back Install

15. Click Continue Installation to resume.

000	💝 Install Soundflower	
Introduct Read Me	When this software finishes installing, you must restart your computer. Are you sure you want to install the software now?	.er.
License	Cancel Continue Installation	of
 Destination select Installation Type 	this software on the disk "Macintosh HD".	
Installation		
Summary		
*	Customize Go Back	Install

16. The Mac system needs to restart before you can use the applications. Click **Restart**.

😺 Install Soundflower
The installation was completed successfully.
The installation was successful.
The software was installed.
Click Restart to finish installing the software.
Go Back Restart

Operation

1. Make sure EZ Suite Display is active and displaying the WiFi Welcome screen.

AP Info			*	((14
AP	IN1112a-765078			
IP	192.168.111.1		Success	;
PSK	87654321	ſ	Ready for display	
Channel:	6			
			11	
Passcode:	3302			

2. Establish the WiFi connection between the display device and your Mac using the SSID and encryption key (PSK) in the Welcome screen.

3. Find EZ WiFi>EZWifiMac in your Applications folder and double-click it. All connected display devices will be displayed.

00		EZWiFi		
			Q	
FAVORITES All My Files AlrDrop Desktop FAPIcations Comments raymondyu SHARED aiodemo15 Comments	App Store Automator Juante Automator Blackmagic Disk Speed Test BlackmagicerDeck Utility BlackmagicerDeck Utility Blackmagic Media Express Blackmagicibridge Utility Caffeine Calculator Calendar Calibration Camtasia 2 Camtasia 2	EZWifiMac Soundflower.pkg SoundflowerVersion.rtf		
anduento2-pc andrea-lt-w7 cascade_m dduncan-lt dhedberg dmontz-vs	Chess Compressor Contacts Dashboard Dictionary DVD Player EZUSB EZUSB EVKFi		Name Kind Size Created Modified Last opened Version	EZWifiMac Application 2.1 MB 3/27/13 1:06 AM Today 1:26 PM Today 1:26 PM 1.1.78

4. Select the Device Name you want to display and click Start.

00	EZWifiMac
Device Name	IP Address
IN1112a	192.168.111.1
	Start
Version: 1.1.78	
Convright @ 2012	actions Micro All Rights Reserved

5. Enter the 4-digit Passcode displayed on the WiFi display and click **OK**.

Device Passcode					
sso	code			_	
_					014
C	Ca	ance		F	

6. Select the Display mode (Mirror or Extension).

00	EZWifiMac	
Source	R.	
Control the pro	jector via web page	Link
Mode		
Graphic	💽 Video	
Display		
• Mirror	CExtension	
Split Screen		
	0 💶 0	Change Layout
		Disconnect

7. If you want to display other people's screens in a split screen mode, click **Change Layout**. Select the desired display configuration to display from more than one Mac, PC, iPad, iPhone or Android device. Up to four different sources can be displayed simultaneously.

Note: Do not change the resolution while EZ Display is active.

To display from an iPhone or iPad, install EZ Display from the App Store. EZ Display operation is described in a different document.