

RIGOL

Performance Verification Guide

DS1000E/D Series Digital Oscilloscope

Mar. 2013

RIGOL Technologies, Inc.

Guaranty and Declaration

Copyright

© 2013 RIGOL Technologies, Inc. All Rights Reserved.

Trademark Information

RIGOL is a registered trademark of RIGOL Technologies, Inc.

Publication Number

PVA07000-1112

Notices

- **RIGOL** products are protected by patent law in and outside of P.R.C.
- **RIGOL** reserves the right to modify or change parts of or all the specifications and pricing policies at company's sole decision.
- Information in this publication replaces all previously corresponding material.
- **RIGOL** shall not be liable for losses caused by either incidental or consequential in connection with the furnishing, use or performance of this manual as well as any information contained.
- Any part of this document is forbidden to be copied or photocopied or rearranged without prior written approval of **RIGOL**.

Product Certification

RIGOL guarantees this product conforms to the national and industrial standards in China as well as the ISO9001:2008 standard and the ISO14001:2004 standard. Other international standard conformance certification is in progress.

Contact Us

If you have any problem or requirement when using our products, please contact RIGOL Technologies, Inc. or your local distributors, or visit: www.rigol.com.

General Safety Summary

Please review the following safety precautions carefully before putting the instrument into operation so as to avoid any personal injuries or damages to the instrument and any product connected to it. To prevent potential hazards, please use the instrument only specified by this manual.

Use Proper Power Cord.

Only the power cord designed for the instrument and authorized by local country could be used.

Ground The Instrument.

The instrument is grounded through the Protective Earth lead of the power cord. To avoid electric shock, it is essential to connect the earth terminal of power cord to the Protective Earth terminal before any inputs or outputs.

Connect the Probe Correctly.

Do not connect the ground lead to high voltage since it has the isobaric electric potential as ground.

Observe All Terminal Ratings.

To avoid fire or shock hazard, observe all ratings and markers on the instrument and check your manual for more information about ratings before connecting.

Use Proper Overvoltage Protection.

Make sure that no overvoltage (such as that caused by a thunderstorm) can reach the product, or else the operator might expose to danger of electrical shock.

Do Not Operate Without Covers.

Do not operate the instrument with covers or panels removed.

Use Proper Fuse.

Please use the specified fuses.

Avoid Circuit or Wire Exposure.

Do not touch exposed junctions and components when the unit is powered.

Do Not Operate With Suspected Failures.

If you suspect damage occurs to the instrument, have it inspected by qualified service personnel before further operations. Any maintenance, adjustment or replacement especially to circuits or accessories must be performed by **RIGOL** authorized personnel.

Keep Well Ventilation.

Inadequate ventilation may cause increasing of temperature or damages to the device. So please keep well ventilated and inspect the intake and fan regularly.

Do Not Operate in Wet Conditions.

In order to avoid short circuiting to the interior of the device or electric shock, please do not operate in a humid environment.

Do Not Operate in an Explosive Atmosphere.

In order to avoid damages to the device or personal injuries, it is important to operate the device away from an explosive atmosphere.

Keep Product Surfaces Clean and Dry.

To avoid the influence of dust and/or moisture in air, please keep the surface of device clean and dry.

Electrostatic Prevention.

Operate in an electrostatic discharge protective area environment to avoid damages induced by static discharges. Always ground both the internal and external conductors of the cable to release static before connecting.

Handling Safety.

Please handle with care during transportation to avoid damages to buttons, knob interfaces and other parts on the panels.

Safety Terms and Symbols

Terms on the Product. These terms may appear on the Product:

- DANGER** indicates an injury or hazard may immediately happen.
WARNING indicates an injury or hazard may be accessible potentially.
CAUTION indicates a potential damage to the instrument or other property might occur.

Symbols on the Product. These symbols may appear on the product:



Hazardous Voltage



Safety Warning



Protective Earth Terminal



Chassis Ground



Test Ground

Contents

Guaranty and Declaration	I
General Safety Summary	II
Safety Terms and Symbols	IV
Document Overview	VI
Chapter 1 Overview	1-1
Test Preparations.....	1-1
Self-calibration.....	1-1
Test Result Record.....	1-2
Chapter 2 Performance Calibration Test	2-1
Impedance Test	2-2
DC Gain Accuracy Test	2-3
Bandwidth Test	2-5
Bandwidth Limit Test	2-7
Time Base Accuracy Test.....	2-10
Zero Point Offset Test	2-11
Appendix Test Record Form	1

Document Overview

This manual guides users to correctly test the performance of **RIGOL** DS2000 series digital oscilloscope.

Main topics in this manual:

Chapter 1 Overview

This chapter introduces the preparations and precautions of the performance verification test.

Chapter 2 Performance Calibration Test

This chapter introduces the limit, test device required as well as test method and procedures of each performance.

Appendix Test Record Form

In the appendix, a test record form is provided for test result so as to determine whether each performance fulfills the requirement.

Format Conventions in this Manual:

Front Panel Key: denoted by "Text Box + Button Name (Bold)", for example, **Utility**.

Menu Softkey: denoted by "Character Shading + Menu Word (Bold)", for example, **Self-Cal**.

Operation Step: denoted by an arrow "→", for example, **Utility** → **Self-Cal**.

Contents Conventions in this Manual:

In this manual, DS1102E is taken as an example to illustrate the performance verification method. The introductions in this manual are applicable to all the models of DS1000E/DS1000D.

Model	DS1102E	DS1052E	DS1102D	DS1052D
Analog Bandwidth	100 MHz	50 MHz	100 MHz	50 MHz
channels	2	2	2	2
Max Real-time Sample Rate	1 GSa/s			

Chapter 1 Overview

Test Preparations


The following preparations should be done before the test:




- 1) Warm-up: warm the oscilloscope up for at least 30 minutes;
- 2) Self-calibration: calibrate the oscilloscope.

Self-calibration

Before performing self-calibration, make sure that the oscilloscope has been warmed up or running for 30 minutes.

- 1) Disconnect the connections of all the channels.
- 2) Press **Utility** → **Self-Cal**, "Press RUN/STOP key to start/Press AUTO key to exit" will be displayed on the screen and Press **RUN/STOP**, the oscilloscope starts to execute the self-calibration program as shown in the figure below:



- 3) The self-calibration takes about 5 minutes. "Calibration finished/Press RUN/STOP key to exit", please restart the oscilloscope after exiting.
- 4) Press **Acquire** → **Acquisition** and use  to select "Average". Then, press **Averages** and use  to set the number of averages to 16.
- 5) Press down the **VERTICAL**  **POSITION** knob of each channel respectively to set the vertical position of the two channels to zero. View the distance between the waveform of each channel and the screen center at 2 mV/div. when the distance is greater than 0.2div, please perform self-calibration again until the calibration succeeds (note: make sure that the instrument passes the self-calibration before performing the performance verification test; otherwise, the test results might not be accurate).

Test Result Record

Record and keep the test result of each test. In the Appendix of this manual, a test result record form which lists all the test items and their corresponding performance limits as well as spaces for users to record the test results, is provided.

Tip:

It is recommended that users photocopy the test record form before each test and record the test results in the copy so that the form can be used repeatedly.

Chapter 2 Performance Calibration Test

This chapter introduces the performance verification test method of DS1000E/DS1000D series digital oscilloscope by taking DS1102E as an example. You can perform the following test in any order. In this manual, the test device used is Fluke 9500B. You can also use other devices that fulfill the specification requirements for the test.

Recommended Devices List:

Device	Specification	Recommended Model
Oscilloscope Calibrator	Output range of DC voltage: 1 M Ω : 1 mV to 200 V 50 M Ω : 1 mV to 200 V The rise time of fast edge signal: ≤ 150 ps	Fluke 9500B
Digital Multimeter	The resistance measurement accuracy is higher than $\pm 0.1\%$ of reading	RIGOL DM3058/3068
Test Cable	BNC (male) to Dual-banana Plug Cable	--
Signal Generator	Frequency Accuracy: ± 1 ppm	RIGOL DG4162
Test Cable	BNC (m)-BNC (m) cable	--

Note:

- 1) Make sure that the oscilloscope passes the self-calibration before performing the performance calibration test.
- 2) Make sure that the oscilloscope has been warmed up for 30 minutes before executing any of the following tests.
- 3) Please reset the instrument to the factory setting before or after executing any of the following tests.

Impedance Test



Specifications:

Input Impedance	1 M Ω \pm 2% (0.98 M Ω to 1.02 M Ω)
-----------------	-------------------------------------------------------------

Test Devices: Fluke 9500B or Digital Multimeter and BNC (male) to Dual-banana Plug Cable. In this manual, the test device is Fluke 9500B.

Test Procedures:

1. Impedance test of CH1 and CH2

- 1) Connect the active head of Fluke 9500B to CH1 of the oscilloscope.
- 2) Configure the oscilloscope:
 - a) Press **CH1** in the vertical control area (VERTICAL) at the front panel to enable CH1.
 - b) Rotate **VERTICAL**  **SCALE** to set the vertical scale of CH1 to 100 mV/div.
- 3) Enable the Fluke 9500B and select the resistance measurement function, read and record the resistance measurement value.
- 4) Rotate **VERTICAL**  **SCALE** to adjust the vertical scale of CH1 to 500 mV/div; then, read and record the resistance measurement value.
- 5) Turn CH1 off. Repeat the above test steps to test CH2 and record the test results.

2. Impedance test of [EXT TRIG] channel

- 1) Disconnect the connections of the two input channels.
- 2) Connect the active head of Fluke 9500B to the external trigger channel **[EXT TRIG]**.
- 3) Enable the Fluke 9500B and select the resistance measurement function, read and record the resistance measurement value.

Test Record Form:

Channel	Vertical Scale	Test Result	Limit	Pass/Fail
CH1	100 mV/div		$\geq 0.98 \text{ M}\Omega$ and $\leq 1.02 \text{ M}\Omega$	
	500 mV/div			
CH2	100 mV/div			
	500 mV/div			
EXT TRIG	--			



DC Gain Accuracy Test

Specifications:

DC Gain Accuracy	$\leq 4\% \times \text{Full Scale (2 mV/div to 5 mV/div)}$ $\leq 3\% \times \text{Full Scale (10 mV/div to 10 V/div)}$
Explanation: Full Scale = 8 div \times vertical scale. Relative error of each scale: $ (V_{\text{avg1}} - V_{\text{avg2}}) - (V_{\text{out1}} - V_{\text{out2}}) / \text{Full Scale} \times 100\% \leq X\%$ (the value of X is 3 when the vertical scale is 10 mV/div to 10 V/div and the value of X is 4 when the vertical scale is 2 mV/div to 5 mV/div); otherwise, the test fails. For example, when the vertical scale is 1 V/div, input DC signals with +3 V _{DC} and -3 V _{DC} voltages respectively, the values of Vavg1 and Vavg2 are +3.06 V and -3.04 V respectively, the relative error is $ (+3.06 \text{ V} - (-3.04 \text{ V}) - (+3 \text{ V} - (-3 \text{ V})) / (1 \text{ V/div} \times 8 \text{ div}) \times 100\% = 1.25\%$ and the test passes.	

Test Device: Fluke 9500B

Test Procedures:

- 1) Connect the active head of Fluke 9500B to CH1 of the oscilloscope.
- 2) Enable Fluke 9500B and set the output impedance to 1 M Ω .
- 3) Output a DC signal with +6 mV_{DC} voltage (V_{out1}) from Fluke 9500B.
- 4) Configure the oscilloscope:
 - a) Press **CH1** in the vertical control area (VERTICAL) at the front panel to enable CH1.
 - b) Rotate **VERTICAL SCALE** to set the vertical scale to 2 mV/div.
 - c) Rotate **HORIZONTAL SCALE** to set the horizontal time base to 10 μ s.
 - d) Rotate **VERTICAL POSITION** to set the vertical position to 0.
 - e) Press **Acquire** \rightarrow **Acquisition** and use  to select "Average". Then, press **Averages** and use  to set the number of averages to 32.
- 5) Enable the average measurement function of the oscilloscope. Read and record Vavg1.
- 6) Adjust Fluke 9500B to output a DC signal with -6 mV_{DC} voltage (V_{out2}).
- 7) Read and record the average value Vavg2 at the moment.
- 8) Calculate the relative error of the vertical scale:
 $|(V_{\text{avg1}} - V_{\text{avg2}}) - (V_{\text{out1}} - V_{\text{out2}})| / \text{Full Scale} \times 100\%$
- 9) Keep other settings of the oscilloscope unchanged:
 - a) Set the vertical scale to 5 mV/div, 10 mV/div, 20 mV/div, 50 mV/div, 100 mV/div, 200 mV/div, 500 mV/div, 1 V/div, 2 V/div, 5 V/div and 10 V/div respectively.
 - b) Adjust the output voltage of Fluke 9500B to ± 3 div respectively.
 - c) Repeats steps 2), 3), 4), 5), 6) and 7) and record the results.
 - d) Calculate the relative error of each scale.
- 10) Turn CH1 off. Repeat the above test steps to test CH2 and record the test results.

Test Record Form:

Channel	Vertical Scale	Test Result			Limit	Pass/Fail
		Vavg1	Vavg2	Calculation Result ^[1]		
CH1	2 mV/div				≤4%	
	5 mV/div					
	10 mV/div				≤3%	
	20 mV/div					
	50 mV/div					
	100 mV/div					
	200 mV/div					
	500 mV/div					
	1 V/div					
	2 V/div					
	5 V/div					
	10 V/div					
	CH2	2 mV/div				
5 mV/div						
10 mV/div					≤3%	
20 mV/div						
50 mV/div						
100 mV/div						
200 mV/div						
500 mV/div						
1 V/div						
2 V/div						
5 V/div						
10 V/div						

Note^[1]: the calculation formula is $|(V_{avg1}-V_{avg2})-(V_{out1}-V_{out2})|/Full\ Scale \times 100\%$; wherein, V_{out1} and V_{out2} are 3 and -3 times of the current vertical scale respectively.







Bandwidth Test

Specification:

Amplitude Loss	-3 dB to 1 dB
Explanation:	
Amplitude loss (dB) = $20 \times \lg^{(V_{rms2}/V_{rms1})}$.	

Test device: Fluke 9500B

Test Procedures:

- 1) Connect the active head of Fluke 9500B to CH1 of the oscilloscope.
- 2) Enable the Fluke 9500B and set the output impedance to 1 MΩ.
- 3) Output a sine signal with 1 MHz frequency and 600 mVpp amplitude from Fluke 9500B.
- 4) Configure the oscilloscope:
 - a) Press **CH1** in the vertical control area (VERTICAL) at the front panel to enable CH1.
 - b) Rotate **HORIZONTAL**  **SCALE** to set the horizontal time base to 500 ns.
 - c) Rotate **VERTICAL**  **SCALE** to set the vertical scale to 100 mV/div.
 - d) Rotate **HORIZONTAL**  **POSITION** and **VERTICAL**  **POSITION** to set the horizontal position and vertical position to 0 respectively.
 - e) Rotate **TRIGGER**  **LEVEL** to set the trigger level to 0 V.
- 5) Enable the root mean square measurement function of the oscilloscope. Read and record V_{rms1} .
- 6) Output a sine signal with 100 MHz frequency (for 50 MHz bandwidth oscilloscopes, the frequency is 50 MHz) and 600 mVpp amplitude from Fluke 9500B.
- 7) Rotate **HORIZONTAL**  **SCALE** of the oscilloscope to set the horizontal time base to 5 ns (for 50 MHz bandwidth oscilloscopes, the time base is 10 ns).
- 8) Read and record the root mean square V_{rms2} .
- 9) Calculate the amplitude loss: amplitude loss (dB) = $20 \times \lg^{(V_{rms2}/V_{rms1})}$.
- 10) Keep the other settings of the oscilloscope unchanged and set the vertical scale to 200 mV/div and 500 mV/div respectively.
- 11) Output sine signals with 1 MHz frequency and 1.2 Vpp/3 Vpp amplitude from Fluke 9500B respectively.
- 12) Repeat step 5).
- 13) Output sine signals with 100 MHz frequency (for 50 MHz bandwidth oscilloscopes, the frequency is 50 MHz) and 1.2 Vpp/3 Vpp amplitude from Fluke 9500B respectively.
- 14) Repeat steps 7), 8) and 9).
- 15) Turn CH1 off. Test CH2 according to the above test steps and record the test results.

Test Record Form:

Channel	Vertical Scale	Test Result		Limit	Pass/Fail
CH1	100 mV/div	Vrms1		≥ -3 dB and ≤ 1 dB	
		Vrms2			
		Amplitude Loss ^[1]			
	200 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			
	500 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			
CH2	100 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			
	200 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			
	500 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			

Note^[1]: amplitude loss (dB) = $20 \times \lg(V_{rms2}/V_{rms1})$.








Bandwidth Limit Test

Specification:

Amplitude Loss	-3 dB to 1 dB
Explanation:	
Amplitude Loss (dB) = $20 \times \lg^{(V_{rmsn}/V_{rms1})}$. Wherein, V_{rmsn} represents V_{rms2} and V_{rms3} .	

Test Device: Fluke 9500B

Test procedures:

- 1) Connect the active head of Fluke 9500B to CH1 of the oscilloscope.
- 2) Set the output impedance of Fluke 9500B to 1 MΩ.
- 3) Configure the oscilloscope:
 - a) Press **CH1** in the vertical control area (VERTICAL) at the front panel to enable CH1.
 - b) Rotate **VERTICAL**  **SCALE** to set the vertical scale to 100 mV/div.
 - c) Rotate **HORIZONTAL**  **SCALE** to set the horizontal time base to 500 ns.
 - d) Rotate **HORIZONTAL**  **POSITION** and **VERTICAL**  **POSITION** to set the horizontal position and vertical position to 0 respectively.
 - e) Rotate **TRIGGER**  **LEVEL** to set the trigger level to 0 V.
- 4) Press **CH1** → **BW limit** to enable the function of the bandwidth limit.
- 5) Output a sine waveform with 1 MHz frequency and 600 mVpp amplitude from Fluke 9500B.
- 6) Enable the root mean square measurement function of the oscilloscope. Read and record V_{rms1} .
- 7) Output a sine waveform with 20 MHz frequency and 600 mVpp amplitude from Fluke 9500B.
- 8) Rotate **HORIZONTAL**  **SCALE** of the oscilloscope to set the horizontal time base to 50 ns.
- 9) Read and record root mean square value V_{rms2} .
- 10) Calculate the amplitude loss and compare it to the specification: Amplitude Loss (dB) = $20 \times \lg^{(V_{rms2}/V_{rms1})}$. Amplitude loss should be in the range of the specification at this point.
- 11) Output a sine waveform with 50 MHz frequency and 600 mVpp amplitude from Fluke 9500B.
- 12) Rotate **HORIZONTAL**  **SCALE** of the oscilloscope to set the horizontal time base to 20 ns.
- 13) Read and record root mean square value V_{rms2} .
- 14) Calculate the amplitude loss and compare it to the specification: Amplitude Loss (dB) = $20 \times \lg^{(V_{rms3}/V_{rms1})}$. Amplitude loss should be lower than -3 dB at this point.
- 15) Keep other settings of the oscilloscope unchanged and set the vertical scale to 200 mV/div.
- 16) Output a sine waveform with 1 MHz frequency and 1.2 Vpp amplitude from Fluke 9500B.
- 17) Repeat step 6).
- 18) Output a sine waveform with 20 MHz frequency and 1.2 Vpp amplitude from Fluke 9500B.
- 19) Repeat step 8), 9) and 10).
- 20) Output a sine waveform with 50 MHz frequency and 1.2 Vpp amplitude from Fluke 9500B.
- 21) Repeat step 12), 13) and 14).
- 22) Keep other settings of the oscilloscope unchanged and set the vertical scale to 500 mV/div.

- 23) Output a sine waveform with 1 MHz frequency and 3 Vpp amplitude from Fluke 9500B.
- 24) Repeat step 6).
- 25) Output a sine waveform with 20 MHz frequency and 3 Vpp amplitude from Fluke 9500B.
- 26) Repeat step 8), 9) and 10).
- 27) Output a sine waveform with 50 MHz frequency and 3 Vpp amplitude from Fluke 9500B.
- 28) Repeat step 12), 13) and 14).
- 29) Turn CH1 off. Test CH2 according to the above test steps and record the test results.

Test Record Form:

Channel	Vertical Scale	Test Result		Limit	Pass /Fail
CH1	100 mV/div	Vrms1		--	
		Vrms2			
		Vrms3			
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$		$\geq -3 \text{ dB and } \leq 1 \text{ dB}$	
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$		$\leq 3 \text{ dB}$	
	200 mV/div	Vrms1		--	
		Vrms2			
		Vrms3			
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$		$\geq -3 \text{ dB and } \leq 1 \text{ dB}$	
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$		$\leq 3 \text{ dB}$	
	500 mV/div	Vrms1		--	
		Vrms2			
		Vrms3			
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$		$\geq -3 \text{ dB and } \leq 1 \text{ dB}$	
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$		$\leq 3 \text{ dB}$	
CH2	100 mV/div	Vrms1		--	
		Vrms2			
		Vrms3			
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$		$\geq -3 \text{ dB and } \leq 1 \text{ dB}$	
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$		$\leq 3 \text{ dB}$	
	200 mV/div	Vrms1		--	
		Vrms2			
		Vrms3			
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$		$\geq -3 \text{ dB and } \leq 1 \text{ dB}$	
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$		$\leq 3 \text{ dB}$	
	500 mV/div	Vrms1		--	
		Vrms2			
		Vrms3			
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$		$\geq -3 \text{ dB and } \leq 1 \text{ dB}$	
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$		$\leq 3 \text{ dB}$	

Note^[1]: amplitude loss (dB) = $20 \times \lg^{(Vrmsn/Vrms1)}$. Here, Vrmsn represents Vrms2 and Vrms3.





Time Base Accuracy Test

Specification:

Time Base Accuracy	$\leq \pm 50$ ppm
--------------------	-------------------

Test Devices: Fluke 9500B or signal generator and BNC (m)-BNC (m) cable.

Test procedures:


- 1) Connect the active head of Fluke 9500B to CH1 of the oscilloscope.
- 2) Output a sine waveform with 1 MHz frequency and 1 Vpp amplitude from Fluke 9500B.
- 3) Configure the oscilloscope:
 - a) Press **CH1** in the vertical control area (VERTICAL) at the front panel to enable CH1.
 - b) Rotate **VERTICAL**  **SCALE** to set the vertical scale to 200 mV/div.
 - c) Rotate **VERTICAL**  **POSITION** to set the vertical position to 0.
 - d) Rotate **HORIZONTAL**  **SCALE** to set the horizontal time base to 20 ns.
 - e) Rotate **HORIZONTAL**  **POSITION** to set the horizontal position to 1 ms.
- 4) Observe the display of the oscilloscope and measure the offset (ΔT) of the midpoint of the signal relative to the center of the screen.
- 5) Calculate the time base accuracy, namely the ratio of ΔT to the horizontal position of the oscilloscope. For example, if the offset of this test is 8 ns, the time base accuracy is 10 ns/1 ms=10 ppm.

Test Record Form:

Channel	Test Result ΔT	Calculation Result	Limit	Pass/Fail
CH1			± 50 ppm	

Zero Point Offset Test

Zero point offset is defined as the offset of the crossing point of the waveform and the trigger level relative to the trigger position as shown in the figure below.



Specification:

Zero Point Offset	500 ps
-------------------	--------

Test Devices: Fluke 9500B

Test Procedures:

- 1) Connect the active head of Fluke 9500B to CH1 of the oscilloscope.
- 2) Output a fast edge signal with 150 ps rise time and 600 mV amplitude from Fluke 9500B.
- 3) Configure the oscilloscope:
 - a) Press **CH1** in the vertical control area (VERTICAL) at the front panel to enable CH1.
 - b) Rotate **VERTICAL** **SCALE** to set the vertical scale to 100 mV/div.
 - c) Rotate **HORIZONTAL** **SCALE** to set the horizontal time base to 2 ns (for 50 MHz bandwidth oscilloscopes, set the horizontal time base to 5 ns).
 - d) Rotate **VERTICAL** **POSITION** and **HORIZONTAL** **POSITION** to set the vertical position and horizontal position to appropriate values respectively.
 - e) Rotate **TRIGGER** **LEVEL** to adjust the trigger level to the middle of the screen.
- 4) Observe the display of the oscilloscope. Press **Cursor** → **Mode** → "Manual" to enable the manual cursor function to measure the zero point offset and record the measurement result.
- 5) Keep other settings unchanged and adjust the amplitude of the fast edge signal to 3 V.
- 6) Set the vertical scale to 500 mV/div. Measure the zero point offset according to the above method and record the test result.
- 7) Turn CH1 off. Repeat the above test steps to measure CH2 and record the test results.

Test Record Form:

Channel	Fast Edge Signal Amplitude	Vertical Scale	Test Result	Limit	Pass/Fail
CH1	600 mV	100 mV/div		≤ 500 ps	
	3 V	500 mV/div			
CH2	600 mV	100 mV/div			
	3 V	500 mV/div			

Appendix Test Record Form

RIGOL DS1000E/D Series Digital Oscilloscope Performance Verification Test Record Form

Model: _____ Tested by: _____ Test Date: _____

Impedance Test:

Channel	Vertical Scale	Test Result	Limit	Pass/Fail
CH1	100 mV/div		$\geq 0.98 \text{ M}\Omega$ and $\leq 1.02 \text{ M}\Omega$	
	500 mV/div			
CH2	100 mV/div			
	500 mV/div			
EXT TRIG	--			

DC Gain Accuracy Test:

Channel	Vertical Scale	Test Result			Limit	Pass/Fail
		Vavg1	Vavg2	Calculation Result ^[1]		
CH1	2 mV/div				≤4%	
	5 mV/div					
	10 mV/div				≤3%	
	20 mV/div					
	50 mV/div					
	100 mV/div					
	200 mV/div					
	500 mV/div					
	1 V/div					
	2 V/div					
	5 V/div					
	10 V/div					
CH2	2 mV/div				≤4%	
	5 mV/div					
	10 mV/div				≤3%	
	20 mV/div					
	50 mV/div					
	100 mV/div					
	200 mV/div					
	500 mV/div					
	1 V/div					
	2 V/div					
	5 V/div					
	10 V/div					

Note^[1]: the calculation formula is $|(V_{avg1}-V_{avg2})-(V_{out1}-V_{out2})|/Full\ Scale \times 100\%$; wherein, V_{out1} and V_{out2} are 3 and -3 times of the current vertical scale respectively.

Bandwidth Test:

Channel	Vertical Scale	Test Result		Limit	Pass/Fail
CH1	100 mV/div	Vrms1		≥ -3 dB and ≤ 1 dB	
		Vrms2			
		Amplitude Loss ^[1]			
	200 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			
	500 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			
CH2	100 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			
	200 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			
	500 mV/div	Vrms1			
		Vrms2			
		Amplitude Loss			

Note^[1]: amplitude loss (dB) = $20 \times \lg(V_{rms2}/V_{rms1})$.

Bandwidth Limit Test:

Channel	Vertical Scale	Test Result	Limit	Pass/Fail		
CH1	100 mV/div	Vrms1		--		
		Vrms2				
		Vrms3				
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$				$\geq -3 \text{ dB and } \leq 1 \text{ dB}$
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$				$\leq 3 \text{ dB}$
	200 mV/div	Vrms1		--		
		Vrms2				
		Vrms3				
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$				$\geq -3 \text{ dB and } \leq 1 \text{ dB}$
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$				$\leq 3 \text{ dB}$
	500 mV/div	Vrms1		--		
		Vrms2				
		Vrms3				
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$				$\geq -3 \text{ dB and } \leq 1 \text{ dB}$
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$				$\leq 3 \text{ dB}$
CH2	100 mV/div	Vrms1		--		
		Vrms2				
		Vrms3				
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$				$\geq -3 \text{ dB and } \leq 1 \text{ dB}$
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$				$\leq 3 \text{ dB}$
	200 mV/div	Vrms1		--		
		Vrms2				
		Vrms3				
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$				$\geq -3 \text{ dB and } \leq 1 \text{ dB}$
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$				$\leq 3 \text{ dB}$
	500 mV/div	Vrms1		--		
		Vrms2				
		Vrms3				
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms2/Vrms1)}$				$\geq -3 \text{ dB and } \leq 1 \text{ dB}$
		Amplitude Loss ^[1] (dB) = $20 \times \lg^{(Vrms3/Vrms1)}$				$\leq 3 \text{ dB}$

Note^[1]: amplitude loss (dB) = $20 \times \lg^{(Vrmsn/Vrms1)}$. Wherein, Vrmsn represents Vrms2 and Vrms3.

Time Base Accuracy Test:

Channel	Test Result ΔT	Calculation Result	Limit	Pass/Fail
CH1			$\pm 50 \text{ ppm}$	

Zero Point Offset Test:

Channel	Fast Edge Signal Amplitude	Vertical Scale	Test Result	Limit	Pass/Fail
CH1	600 mV	100 mV/div		≤ 500 ps	
	3 V	500 mV/div			
CH2	600 mV	100 mV/div			
	3 V	500 mV/div			