



Wiring Accessories

Weatherproof Junction Box

For your safety, this product must be installed in accordance with local Building Regulations. **If in any doubt, or where required by the law, consult a competent person who is registered with an electrical self-certification scheme.** Further information is available online or from your Local Authority.

Please read carefully and use in accordance with these safety wiring instructions. Before commencing any electrical work ensure the supply is switched off at the mains. Either by switching off the consumer unit or by removing the appropriate fuse or turning off MCB (trip). Wiring should be in accordance with the latest edition of the IET regulations (BS 7671).

To prevent fire hazard always use cable of the correct rating & type for the application.

Warning do not exceed the load rating - 57A.

Note - As from 1st April 2004 new colour codes for hard wire installations were introduced.

EARTH = Green/Yellow Slewing

NEUTRAL = Black (pre Apr 04) / Blue (after Apr 04)

LIVE = Red (pre Apr 04) / Brown (after Apr 04)



If installed correctly BG Electrical Weatherproof products provide an IP66 level of protection, this means that the sealed construction provides a very high level of protection against the ingress of both water & dust.

Installation Instructions

Before commencing work always isolate the power at the consumer unit/fuse box.

1. The unit should be mounted on a clean, rigid vertical surface suitable to accept screw type fixings. Surface should be reasonably flat as unevenness could cause product damage or affect operation.

2. Remove Front Cover from Rear Box.


3. For cable entry, decide if conduit is being used & entry positions. For side, top or rear entry the lowermost drain hole position **MUST** be drilled out using a 5mm drill. **ONLY ONE** drain hole position must be drilled.

For bottom entry a drain hole **MUST NOT** be drilled in Rear Box, but a drain hole **MUST** be drilled at lowermost point of conduit run.

For rear entry, drill/cut the appropriate size hole. For extra sealing protection, channels around knock-out and fixing holes are provided to accept a bead of sealant (not supplied) when fixing to mounting surface.

Note – The drilling of the drain hole or removing a knock-out will reduce the IP rating of the product.

4. Mount the Rear Box using No 8 screws in all four, or at least two diagonal positions on fixing centres shown. The fixing holes are slotted to enable some rotation adjustment if required. Fit supplied Bungs over all used fixing screw positions to seal aperture recesses.



5. Make cable entry into Rear Box as required. Only remove the blanking plugs for positions used. Ensure adequate excess lengths of cable for connection to the Terminal Block. Install & seal all cable glands & conduit to manufacturers instructions.

To install, remove the blanking plug from the Rear Box, and fit gland or conduit. Ensure the gland or conduit and cable entry are sealed with non-setting sealant.

6. Position Terminal Block in Rear Box to determine final lengths of cables & cut to suit. Strip outer insulation as required & then trim insulation on individual wires 8-10mm to expose conductor ends.

7. Connect the wires to the relevant terminals of the Terminal Block.

8. Tighten terminal screws securely (Do not over tighten).

9. Any earth connections **MUST** be made & continuity maintained. All bare Earth wires must be sheathed with green/yellow sleeving.

Safety Instructions

Please read carefully before installation.

1. An outdoor location should be chosen ensuring adequate access to a mains supply circuit. The circuit **MUST** be protected by an appropriate fuse, circuit breaker or RCD (Residual Current Device) in accordance with current IET wiring regulations.


2. Where conduit is used for cable runs, water condensation **MUST** be prevented from collecting inside the unit & conduit. Drain holes **MUST** be drilled out (see Installation Instructions)

3. If metal conduit is used, earth continuity across the conduit must be maintained using appropriate connections (not supplied).


4. Where outdoor cable runs occur, ensure cable recommended for outdoor installations is used. In general, rubber insulated cable & plastic M20 cable glands can be used. Alternatively standard flat PVC twin & earth mains cable inside 20mm plastic or metal conduit may be used. Where necessary, SWA (Steel Wire Armoured) cable with metal cable glands should be used. The outdoor use of unprotected flat PVC insulated cable is **NOT** recommended.

Technical

10. After wiring the Terminal Block, refit the Front Cover to Rear Box, securing using the quick fix fasteners. Turn 150° clockwise with a suitable flat bladed screwdriver to tighten, from 0 to I – DO NOT OVER TIGHTEN.



Fastener in open position



Fastener in locked position

11. Once the installation has been completed correctly, replace the fuse/reset MCB (trip), switch the power back on at the consumer unit and test.

Voltage : 450V ac

Rating : 57A

Terminal Block : 5 Way

Terminal Capacity (each way) : Min 2.5mm² - Max 10.0mm²

IP Rating : IP66 (with cover securely fitted)

Batch Code Explanation

yyWxx Manufacturing date code, year of manufacture (yy) and week of manufacture (Wxx)

Care

This BG Electrical Nexus Storm Weatherproof accessory is made from polycarbonate material that is durable with a high impact resistance. During the life of the product any cleaning should be carried out with a damp cloth using a mild detergent & warm water. DO NOT USE solvent based cleaners as these may cause damage.

Address/Hotline

Luceco PLC
Stafford Park 1
Telford TF3 3BD
ENGLAND

(EU) Luceco SE
C/ Bobinadora 1-5
08302 Mataró
SPAIN

If you have further technical assistance you can get in touch with our

Technical Helpline on:

+44 (0)3300 249 279

technical.support@bgelectrical.co.uk

Environmental Protection



This symbol is known as the "Crossed-out Wheelie Bin Symbol". When this symbol is marked on a product or battery, it means that it should not be disposed of with your general household waste. Some chemicals contained within electrical/electronic products or batteries can be harmful to health and the environment. Only dispose of electrical/electronic/battery items in separate collection schemes, which cater for the recovery and recycling of materials contained within. Your co-operation is vital to ensure the success of these schemes and for the protection of the environment.