


Metal Enclosure Installation Guide - CFUE4M



Enclosure complies with 17th Edition Wiring Regulations Amendment 3

This provides a guide to the assembly and installation of the BG Electrical metal enclosure unit.

This product must be installed by a competent person in accordance with the current IET Wiring Regulations (BS 7671) and Building Regulations.

Ensure ALL screws are fully tightened before use

Please ensure electrical supply is disconnected before installation

1. Remove front cover by opening the visor, and undo two retaining screws.
2. Provide cable access via either 20mm or 32mm knockouts on the top and bottom faces, 32mm knockouts on the side faces or a large knockout in the base. only remove the minimum number required. Cable glands can be used to manage cable entry.
3. Secure to wall. Use one key hole slot to hang in position, ensure fitted level, use other fixing holes to firmly secure.
4. Fit required devices to DIN rail, fit required busbar and cables to devices and neutral and earth terminal blocks. Note:- Devices, busbar and cables are not supplied with this enclosure.
5. **Ensure all connections are secure and terminal screws fully tightened. Recommended max torque for Terminal screws, MCBs and RCBOs is 2Nm, Switch and RCD 2.5Nm.**
6. Test in accordance with the current IET wiring regulations.
7. Add cover mounted blanks supplied if required.
8. Refit cover, and secure using two screws.
9. Apply RCD test label if required and circuit identification labels to front cover above devices.

General

Tools – Screwdriver PZ 2 or Flat screwdriver, knife and pliers.

Cleaning – use a soft damp cloth with luke warm water (only clean outside of unit).

Standards – All consumer units have been designed to comply with the requirements of BS EN 62208, BS 7671 and Part P document.

Guarantee

BG Electrical products are guaranteed against faulty materials and workmanship for a period of 10 years from date of delivery: products will be repaired or (at BG Electrical's discretion) replacements will be supplied or (at BG Electrical's discretion) a credit note will be issued. This guarantee is subject to BG Electrical's conditions of sale and in particular to the following conditions being met:

1. Notification of any defect is given to BG Electrical as soon as reasonably practicable after becoming apparent, and the products then returned to BG Electrical.
2. The products have only been operated under normal operating conditions and have only been subject to normal use.
3. No work (other than normal and proper maintenance) has been carried out to the products without BG Electrical's prior written consent.
4. The products have been assembled, or incorporated into other goods, by a qualified and recognised electrician and only in accordance with any instructions issued by BG Electrical.
5. The defect has not arisen from an item manufactured or supplied by a person other than BG Electrical.

This guarantee does not affect any consumer statutory rights.

All components used in a BG Electrical enclosure, must be supplied by BG Electrical. The use of any other components will negate compliance to BS EN 61439 and the BG Electrical Guarantee. Failure to fit the enclosure in accordance with these instructions will invalidate the guarantee.

Technical Helpline: **-03300 249 279**

Luceco PLC
Stafford Park 1
Telford

Shropshire
TF3 3BD
United Kingdom

T: +44(0) 1952 238100 F: +44(0) 1952 238180
www.bgelectrical.co.uk