WPTMSKTII -A

Authority

application.

of the product.

were introduced

EARTH = Green/Yellow Sleeving

NEUTRAL = Black (pre Apr 04) / Blue (after Apr 04)

LIVE = Red (pre Apr 04) / Brown (after Apr 04)

to enter the socket with the cover open.

Please read carefully before installation.

drilled out (see Installation Instructions)

current IET wiring regulations.



Installation Instructions

Before commencing work always isolate the power at the consumer unit/fuse box.


- 1. The unit should be mounted on a clean, rigid vertical surface suitable to accept screw type fixings. Surface should be reasonably flat as unevenness could cause product damage or affect operation.
- Remove Front assembly from Rear Box.
- For cable entry, decide if conduit is being used & entry positions. For side, top or rear entry the lowermost drain hole position MUST be drilled out using a 5mm drill, ONLY ONE drain hole position must be drilled. For bottom entry a drain hole MUST NOT be drilled in Rear Box, but a drain

hole MUST be drilled at lowermost point of conduit run.

For rear entry, drill/cut the appropriate size hole. For extra sealing protection, channels around knock-out and fixing holes are provided to accept a bead of sealant (not supplied) when fixing to mounting surface.

Note - The drilling of the drain hole or removing a knock-out will reduce the IP rating of the product.

4. Mount the Rear Box using No.8 screws in all four, or at least two diagonal positions on fixing centres shown. The fixing holes are slotted to enable some rotation adjustment if required. Fit supplied Bungs over all



5. Make cable entry into rear box as required. Only remove the blanking plugs for positions used. Ensure adequate excess lengths of cable for connection to the Socket, Install & seal all cable glands & conduit to

Manufacturer's instructions To install, remove the blanking plug from rear box, and fit gland or conduit. Ensure the gland or conduit and cable entry are sealed with a non-setting

- 6. Offer up Front Assembly to Rear Box to determine final lengths of cables & cut to suit. Strip outer insulation as required & then trim insulation on individual wires 10-12mm to expose conductor ends.
- 7. Connect the wires to the correct rear terminals. Connect LIVE wire to BROWN LIVE (L) terminal Connect NEUTRAL wire to BLUE NEUTRAL INIterminal Connect EARTH wire to GREEN/YELLOW (E) terminal

(1) The colours of the wires will be dependent on the type of cable used. (2) It is possible to remove the socket from the Front Assembly to aid wiring by releasing the retaining clips on the rear.

Safety Warning

3. If metal conduit is used, earth continuity across the conduit must be maintained using appropriate connections (not supplied). An earth terminal in the Rear Box is provided as required. 4. Where outdoor cable runs occur, ensure cable recommended for outdoor

Building Regulations. If in any doubt, or where required by the law, consult a competent person who is registered with an electrical self-certification scheme. Further information is available online or from your Local Please read carefully and use in accordance with these safety wiring

instructions. Before commencing any electrical work ensure the supply is switched off at the mains. Either by switching off the consumer unit or by

removing the appropriate fuse or turning off MCB (trip). Wiring should be in accordance with the latest edition of the IET regulations (BS 7671). To prevent fire hazard always use cable of the correct rating & type for the

Warning do not exceed the load rating of this device as stated on the rear

Note - As from 1st April 2004 new colour codes for hard wire installations

If installed correctly BG Electrical Weatherproof products provide an IP66

level of protection, this means that the sealed construction provides a very

high level of protection against the ingress of both water & dust. The cover will seal regular sized plugs, however the cover must be closed and

secured when in use to provide the IP rating protection. Do not allow water

Safety Instructions

1. An outdoor location should be chosen ensuring adequate access to a

circuit breaker or RCD (Residual Current Device) in accordance with

2. Where conduit is used for cable runs, water condensation MUST be

prevented from collecting inside the unit & conduit. Drain holes MUST be

mains supply circuit. The circuit MUST be protected by an appropriate fuse,

For your safety, this product must be installed in accordance with local


installations is used. In general, rubber insulated cable & plastic M20 cable glands can be used. Alternatively standard flat PVC twin & earth mains cable inside 20mm plastic or metal conduit may be used. Where necessary.

SWA (Steel Wire Armoured) cable with metal cable glands should be used. The outdoor use of unprotected flat PVC insulated cable is NOT recommended.


24 Hour Timer User Instructions

Please read carefully and use in accordance with our safety instructions

- 1. Plug the appliance to be controlled into the socket.
- 2. Push the segments on the timer face towards the outer edge
- corresponding to the desired operating time. (One segment=15 minutes) 3. Turn the disk clockwise, following the direction of the arrow, until the marker is pointing at the current time.
- 4. To activate the timer function ensure that the switch next to the disk is



Wiring Diagram



- 8. Tighten terminal screws securely (Do not over tighten).
- Any earth connections MUST be made & continuity maintained. All bare earth wires must be sheathed with green/yellow sleeving. Note – the sockets have two linked earth terminals but only one needs to be used for the installation.
- 10. After wiring Socket, refit Front Assembly to Rear Box, secure using the quick fix fasteners. Turn 150° clockwise with a suitable flat bladed screwdriver to tighten, from 0 to I DO NOT OVER TIGHTEN.





Fastener in open position Fastener in locked position

- 11. Once the installation has been completed correctly, replace the fuse/reset MCB (trip), switch the power back on at the consumer unit and test
- 12. For security to prevent unwanted tampering of the socket, the cover has two lug features with 6mm holes, this will accept a padlock or similar locking security device (not supplied).



Care

This BG Electrical Nexus Storm Weatherproof accessory is made from polycarbonate material that is durable with a high impact resistance. During the life of the product any cleaning should be carried out with a damp cloth using a mild detergent & warm water. DO NOT USE solvent based cleaners as these may cause damage.

Technical

Voltage : 240V ac Frequency : 50Hz Socket Rating : 13A

Terminal Capacity : 3 x 2.5mm², 3 x 4mm², 2 x 6mm² IP Rating : IP66 (when cover securely closed)

Batch Code Explanation

yyWxx Manufacturing date code, year of manufacture (yy) and week of manufacture (Wxx) $\,$

Address/Helpline

Luceco PLC Stafford Park 1 Telford TF3 3BD ENGLAND

(EU) Luceco SE C/ Bobinadora 1-5 08302 Mataró SPAIN

If you have further technical assistance you can get in touch with our

Technical Helpline on: +44 (0)3300 249 279

technical.support@bgelectrical.co.uk

Environmental Protection



This symbol is known as the "Crossed-out Wheelie Bin Symbol". When this symbol is marked on a product or battery, it means that it should not be disposed of with your general household waste. Some chemicals contained within electrical/electronic products or batteries can be harmful to health and the environment. Only dispose of electrical/electronic/battery items in separate collection schemes, which cater for the recovery and recycling of materials contained within. Your co-operation is vital to ensure the success of these schemes and for the protection of the environment.