

Undervoltage release for NZM2/3, 1 early-make auxiliary contact, 2NO, 110-130DC, Push-in terminals



Part no. NZM2/3-XUHIV110-130DC-PI

189784

EL Number 4362657

(Norway)

Product name	Eaton Moeller series NZM release
Part no.	NZM2/3-XUHIV110-130DC-PI
EAN	4015081877799
Product Length/Depth	115 millimetre
Product height	65 millimetre
Product width	75 millimetre
Product weight	0.08 kilogram
Compliances	IEC UL/CSA RoHS conform
Product Tradename	NZM
Product Type	Accessories
Product Sub Type	Release
Type	Accessory Undervoltage release Undervoltage release with early-make auxiliary contact
Special features	For interlocking and load-shedding circuits, as well as for early-make of the undervoltage release in main-switch applications. Instantaneous shut-off of the NZM circuit breaker when the control voltage drops below 35 - 70% Us. For use with emergency-stop devices in connection with an emergency-stop button. When the under-voltage trip is switched off, accidental contact with the circuit breaker's primary contacts is prevented when switched on. Early-make of auxiliary contacts on switching on and off (manual operation): approx. 20 ms (NZM2/3) and 90 ms (NZM4). Undervoltage release modules cannot be installed simultaneously with early-make contact NZM...-XHIV, shunt release NZM...-XA... or relays modules NZM...-X2A...
Fitted with:	Early-make auxiliary contact
Suitable for	Motor safety switch Off-load switch
Used with	NZM3(-4), N(S)3(-4) NZM2(-4), N(S)2(-4)
Voltage type	AC
Rated control supply voltage	110 - 130 V DC
Rated control supply voltage (Us) at AC, 50 Hz - min	0 V
Rated control supply voltage (Us) at AC, 50 Hz - max	0 V
Rated control supply voltage (Us) at AC, 60 Hz - min	0 V
Rated control supply voltage (Us) at AC, 60 Hz - max	0 V
Rated control supply voltage (Us) at DC - min	110 V
Rated control supply voltage (Us) at DC - max	130 V
Electric connection type	Screw connection
Number of contacts (change-over contacts)	0
Number of contacts (normally closed contacts)	0
Number of contacts (normally open contacts)	1
Connection type	With push in terminal
Special features	For interlocking and load-shedding circuits, as well as for early-make of the undervoltage release in main-switch applications. Instantaneous shut-off of the NZM circuit breaker when the control voltage drops below 35 - 70% Us. For use with emergency-stop devices in connection with an emergency-stop button. When the under-voltage trip is switched off, accidental contact with the circuit breaker's primary contacts is prevented when switched on. Early-make of auxiliary contacts on switching on and off (manual operation): approx. 20 ms (NZM2/3) and 90 ms (NZM4). Undervoltage release modules cannot be installed simultaneously with early-make contact NZM...-XHIV, shunt release NZM...-XA... or relays modules NZM...-X2A...

10.2.2 Corrosion resistance		Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures		Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat		Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects		Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation		Meets the product standard's requirements.
10.2.5 Lifting		Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact		Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions		Meets the product standard's requirements.
10.3 Degree of protection of assemblies		Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances		Meets the product standard's requirements.
10.5 Protection against electric shock		Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components		Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections		Is the panel builder's responsibility.
10.8 Connections for external conductors		Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength		Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage		Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material		Is the panel builder's responsibility.
10.10 Temperature rise		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility		Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function		The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Under voltage coil (EC001022)		
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Undervoltage trip (ecl@ss10.0.1-27-37-04-17 [AKF015013])		
Rated control supply voltage Us at AC 50HZ	V	0 - 0
Rated control supply voltage Us at AC 60HZ	V	0 - 0
Rated control supply voltage Us at DC	V	110 - 130
Voltage type for actuating		AC
Type of electric connection		Screw connection
Number of contacts as normally open contact		1
Number of contacts as normally closed contact		0
Number of contacts as change-over contact		0
Delayed		No
Suitable for power circuit breaker		No
Suitable for off-load switch		Yes
Suitable for motor safety switch		Yes
Suitable for overload relay		No