

AL802ULADA

NAC Power Extender

Altronix AL802ULADA is an extremely cost effective voltage regulated remote NAC Power Extender. It may be connected to any 24 volt Fire Alarm Control Panel (FACP). Primary applications include Notification Appliance Circuit (NAC) expansion (supports ADA requirements) and providing auxiliary power to support system accessories.



AL802ULADA

Specifications

Input

| | |
|---------|--|
| Voltage | 120VAC, 60Hz, 4A Two (2) Class A or two (2) Class B inputs Two (2) NC dry contact trigger inputs |
|---------|--|

Input Ratings (*INP1 and INP2*):

| |
|--------------------------------|
| 8-30VDC 6.5mA max from FACP |
| 12V 6.5mA, 24V 6.5mA from FACP |

Output

| | |
|-----------|--|
| Voltage | 24VDC power-limited outputs |
| Current | 8A max. total alarm current 2.5A max. current per output |
| Auxiliary | 1A. |
| Other | Thermal and short circuit protection with auto reset Filtered and regulated outputs |

Programmable Supervised Indicating Circuit Outputs:

| |
|--|
| Four (4) Class B, or Two (2) Class A, or One (1) Class A and Two (2) Class B |
|--|

Back-up Battery (*not included*)

| | |
|----------|------------------------------|
| Type | Sealed lead acid or gel type |
| Failover | Upon AC loss, instantaneous |

Supervision

| | |
|------------|-------------------|
| AC Failure | Form "C" contacts |
| Battery | Form "C" contacts |

Indicators (LED)

| | |
|-----------------------------|--------------------------|
| AC Power (Green) | Input voltage is present |
| DC Output (Red) | Powered |
| Logic Board (Red and Green) | Output status |

Agency Listings

| | |
|------|--|
| UL | UL864 (Control Units and Accessories for Fire Systems) |
| MEA | NYC Department of Buildings Approved |
| FM | Factory Mutual Approved |
| CSFM | California State Fire Marshal Approved |

Special Features

- 2-wire horn/strobe Sync mode allows audible notification appliances (horns) and visual notification appliances (strobes) to be silenced/deactivated at the same time
- Sync protocols include Potter/Amseco, Gentex®, System Sensor®, and CooperWheelock®
- Temporal Code 3, Steady Mode, Input to Output Follower Mode (maintains synchronization of notification appliances circuit)
- Compatible with 12VDC or 24VDC fire panels
- Output loop supervision steered to Input 1 or Input 2
- Signal circuit trouble memory (helps identify intermittent loop problems)
- Common trouble input and output for external trouble signals tie-in
- Ground fault detection

Physical and Environmental

Dimensions (H x W x D)

| | |
|------------|--|
| Enclosure: | 15.5" x 12" x 4.5" (393.7mm x 304.8mm x 114.3mm) |
| Shipping: | 16.5" x 13.5" x 6" (419.1mm x 342.9mm x 152.5mm) |

Enclosure accommodates up to two (2) 12VDC/12AH batteries.

Weight (approx.)

| | |
|-----------|--------------------|
| Product: | 9.6 lb. (4.35 kg) |
| Shipping: | 12.3 lb. (5.58 kg) |

Temperature

| | |
|------------|---------------------------------|
| Operating: | 0°C to 49°C (32°F to 120°F) |
| Storage: | - 20°C to 70°C (- 4°F to 158°F) |

| | |
|-------------------|--------------|
| Relative Humidity | 85% +/- 5% |
| BTU/Hr. (approx.) | 41.3 BTU/Hr. |

Lifetime Warranty