

CONTROL CIRCUIT AND LOAD PROTECTION DEVICES

TECHNICAL DATA

Rockwell Automation has Short Circuit Current Ratings on the list of products below per the specific UL Standard and Category Code.

BULLETIN 1489
BULLETIN 1492-CB
BULLETIN 1492-FB
BULLETIN 1492-GH
BULLETIN 1492-GS
BULLETIN 1492-MC
BULLETIN 1492-SP

These ratings are included in the UL acceptance file of the device and summarized on the UL Certification site per the Category Code for the specific product.

SHORT CIRCUIT CURRENT RATINGS

Per the requirements of the 2005 National Electric Code (NEC) and UL508A (effective April 25, 2006), many electrical panels must be rated for their Short Circuit Withstand Rating. Analyzing the SCCR of individual components, and the associated branch and feeder overcurrent devices is a method of determining the SCCR of an electrical assembly.

UL Standard 508A permits these devices to have a SCCR without any additional testing.

Device	SCCR
Circuit Breaker	5 kA
Circuit Breaker With GFCI	5 kA
Fuse Holder	10 kA
Supplementary Protector	200 A

The Allen-Bradley products far exceed those ratings (see page 2).



UL489 CIRCUIT BREAKERS – CAT. CODE DIVQ

UL 508 MANUAL MOTOR STARTERS – CAT. CODE NLRV

UL 1077 SUPPLEMENTARY PROTECTORS – CAT. CODE QVNU2

UL512 FUSE HOLDERS – CAT. CODE IZLT

STANDARD PRODUCT

Rockwell Automation has tested a number of the 1492-PD Power Terminal blocks to determine their SCCR related to the new testing requirements. These are the standard Power Terminal Blocks that have been used in Industrial Control Panels.

The new ratings for these blocks permit their continued use in panels where the higher SCCR ratings are required.

**HIGH FAULT SCCR RATINGS
– UP TO 200,000 A
CERTIFIED TO UL REQUIREMENTS
STANDARD PRODUCTS**

Bulletin Number	Notes	UL508A Category Code	UL File Number	Poles	Current Rating	Max Voltage	SCCR	Application code/notes
1489	Circuit Breaker	DIVQ	E197878	1 pole 2, 3 pole	0.5 - 25 ^(*) A 30 - 40 A 0.5 - 25 ^(*) A 30 - 40 A	277 VAC 240 VAC 480Y/277 VAC 240 VAC	10 kA	---
1492-CB	When used as UL508 Manual Motor Controller Supplementary Protector	NLRV QVNU2	E14841 E65138	1 pole 2, 3 pole 1, 2, 3 pole 1 + N pole 3 + N pole	0.5 - 52A 0.5 - 50 A	277 VAC 480Y/277 VAC 125 VAC 240 VAC 480Y/277 VAC 480Y/277 VAC	5 kA 10 kA 5 kA 3 kA 5 kA	U2 U2 U2 U2 U1
1492-FB	Fuse holder	IZLT	E34648	1, 2, 3 pole	0.1 - 30 A 35 - 60 A 0.1 - 30 A	1492-FB	200 kA (*) (*) Interrupt rating of fuse Type J (*) Interrupt rating of fuse (*)	Type CC & J (*) Interrupt rating of fuse Type J (*) Interrupt rating of fuse Type M (*) Interrupt rating of fuse
1492-GH	Supplementary Protector	QVNU2	E65138	1 pole	0.2 - 15 A	250 VAC	1 kA	U1
1492-GS	Supplementary Protector	QVNU2	E65138	1 pole 2, 3 pole	0.2 - 16 A 20 - 25 A 0.2 - 5 A 6 - 25 A 0.2 - 16 A 20 - 25 A 0.2 - 5 A 6 - 25 A	277 VAC 480Y/277 VAC 800 A 800 A	5 kA 3 kA 400 A 800 A 5 kA 3 kA 400 A 500 A	C1 C1 U1 U1 C1 C1 U1 U1
1492-MC	Circuit Breaker Circuit Breaker with Ground Fault GFCI and GFEP	DIVQ	E197878	1, 2 pole 2 pole 3 pole 1 pole 2 pole 1 pole 2 pole	10 - 60 A 70 - 100 A 15 - 30 A 40 - 100 A 15 - 30 A 40 - 100 A 15 - 100 A 277 VAC 240 VAC 15 - 30 A 40 - 100 A 120 VAC 277 VAC 240 VAC 480Y/277 VAC 15 - 50 A 15 - 50 A	120/240 VAC 240 VAC 240 VAC 120 VAC 277 VAC 240 VAC 480Y/277 VAC 120VAC 120/240 VAC	10 kA 10 kA 10 kA 85 kA 14 kA 85 kA 14 kA 10 kA 10 kA	1492-MCAAnnn 1492-MCBAnnn 1492-MCAA2Hnn 1492-MCBA2Hnn 1492-MCAA3nn 1492-MCBA3nn 1492-MCCA1nn 1492-MCCA2nn 1492-MCGA1nn 1492-MCEA1nn 1492-MCGA2nn 1492-MCEA2nn
1492-SP	Supplementary Protector	QVNU2	E65138	1 pole 1 + N pole 2, 3 pole 3 + N pole	0.5 - 35 A 40 - 63 A 0.5 - 40 A 0.5 - 35 A 40 - 63 A 0.5 - 40 A	277 VAC 480Y/277 VAC	10 kA 5 kA 5 kA 10 kA 5 kA 5 kA	U2 - B or C trip U2 - B or C trip U2 - D trip U2 - B or C trip U2 - B or C trip U2 - D trip

(a) Indicates 25 A @ 480Y/277 available November 2006

C1 Indicates that the short-circuit test was conducted with series overcurrent protection that is no greater than 400% of Supplementary Protector or 15 A whichever is greater.
Indicates that a recalibration and dielectric test was not conducted as part of the short-circuit test.

U1 Indicates that the short-circuit test was conducted without series overcurrent protection. Indicates that a recalibration and dielectric test was not conducted as part of the short-circuit test.
U2 Indicates that the short-circuit test was conducted without series overcurrent protection. Indicates that a recalibration and dielectric test was conducted as part of the short-circuit test.

www.rockwellautomation.com

Power, Control and Information Solutions Headquarters

Americas: Rockwell Automation, 1201 South Second Street, Milwaukee, WI 53204-2496 USA, Tel: (1) 414.382.2000, Fax: (1) 414.382.4444

Europe/Middle East/Africa: Rockwell Automation, Vorstlaan/Boulevard du Souverain 36, 1170 Brussels, Belgium, Tel: (32) 2 663 0600, Fax: (32) 2 663 0640

Asia Pacific: Rockwell Automation, Level 14, Core F, Cyberport 3, 100 Cyberport Road, Hong Kong, Tel: (852) 2887 4788, Fax: (852) 2508 1846