



Southwire™

TOOLS & EQUIPMENT

RECEPTACLE TESTERS

RECEPTACLE TESTERS

Quickly identifies the most common wiring faults in standard 3-wire outlets.

40010S-A
40020S-A

EASY TO USE
SIMPLY PLUG INTO
A LIVE OUTLET

EASY TO READ LED
INDICATORS AND WIRING
LEGEND QUICKLY
IDENTIFY FAULT





RECEPTACLE TESTERS

- Identifies wiring errors in standard 3-wire receptacles
- For use on 120V AC outlets
- GFCI Test (40020S-A only) - verifies operation of GFCI protected outlets
- UL Listed

RECEPTACLE TESTERS

40010S-A 40020S-A

INDICATOR LIGHT GUIDE

LED INDICATOR	FAULT	REASON FOR WIRING FAULT
○ ● ○	Open Ground	Ground terminal is not connected
○ ○ ●	Open Neutral	Neutral terminal is not connected
○ ○ ○	Open Hot	Hot terminal is not connected
● ○ ●	Reversed Hot Ground	Hot & Ground connections are interchanged
● ● ○	Reversed Hot Neutral	Hot & Neutral connections are interchanged
○ ● ●	Correct	Receptacle is wired correctly



SPECIFICATIONS

MODEL #	STOCK #	UPC #	HEIGHT	WIDTH	DEPTH
40010S-A	58292540	0-3288691002-9	3.77" (96mm)	1.7" (44mm)	1.1" (29mm)
40020S-A	58292640	0-3288691003-6	3.77" (96mm)	1.7" (44mm)	1.3" (33mm)
DESCRIPTION	Receptacle Testers		SHIPPING	Box	

BUILT FOR DURABILITY.
BUILT FOR RELIABILITY.
BUILT FOR WORK.™

1-855-SWTOOLS | 1-855-798-6657 | SOUTHWIRETOOLS.COM