

## CONTACT US @ 855-355-2724 E-Mail: <u>Sales@brahelectric.com</u> www.Brahelectric.com



MAGNETIC CONTACTOR Picture is for reference only, Actual Kit may vary slightly

## Voltage Selection Chart B3RT1016-XXXX

B3RT1016	120VAC
B3RT1016-1AB01	24VAC
B3RT1016-1AK61	120VAC
B3RT1016-1AP61	240VAC
B3RT1016-1AV61	480VAC

## PART NUMBER-B3RT1016-1AK61:

BRAH Electric, aftermarket direct replacement contactors for Siemens 3RT1016-1AK61, Sirius line, type 3RT, 3P, 3PH, 9A, 600V, 3HP @ 230V, 5HP @ 460V, 7.5HP @ 575V, complete with 120V AC coil, 1 N/O auxiliary contact, AC magnetic contactor, suitable for use with 3RT series motor control systems

## **PRODUCT SPECIFICATIONS**

Manufacturer	BRAH Electric
Sub-Category	Contactor
Phase	3
Poles	3
Voltage Max	600
Amperage Max	9
Coil Voltage Min	120
Coil Voltage Max	120
Min HP.Rating	3(HP) @230V
Max HP.Rating	7.5(HP) @575V

Warranty: All Products sold by BRAH Electric are guaranteed to be free of defect for a period of two years, under the condition that the product has been installed and operated properly. All items proven defective within the one year period will be replaced by BRAH Electric. In the event that we cannot provide a direct replacement, your monies will be refunded in full. We are not responsible for any consequential losses or damages outside of the defective product as well as any replacements or repairs performed by another party without our written authorization from BRAH Electric.

