

PRODUCT DATA SHEET

CONTACT US @ 855-355-2724 E-Mail:<u>Sales@brahelectric.com</u> www.Brahelectric.com

PART NUMBER – B3UA52-00-2B: BRAH Electric, aftermarket direct replacement solid state overload relays for Siemens 3UA52-00-2B, World Series, type 3UA, rated for 12.50-20.00 amps, suitable for 3TF32, 3TF33, 3TF42, 3TF43, 3TB42, 3TB43 contactors

PRODUCT SPECIFICATIONS

MOTOR STARTER OVERLOAD RELA PART NO. B3UA52-00-2B	Y TYPE	VALUE (UNITS)	NOTES	COMMENTS
	PHASE	3		
	POLES	3		
	AMPERAGE MIN	12.50 (A)		
	AMPERAGE MAX	20.00 (A)		
	VOLTAGE RATING	600V AC		
	TRIP CURRENT	125% OF DIAL SETTING		
	SUITABLE FOR USE WITH	3TF32, 3TF33, 3TF42, 3TF43, 3TB42, 3TB43		
	RELAY STYLE	SOLID STATE		

ADDITIONAL INFORMATION:

* Overload relays are configured with adjustable amperage range settings. Many of the models overlap in amperage range, make sure to verify the required range specification for your application.

* Auxiliary contacts are arranged with screw type terminals. Includes 1 NO & 1 NC auxiliary contact

WARRANTY:

All Products sold by BRAH Electric are guaranteed to be free of defect for a period of one year, under the condition that the product has been installed and operated properly. All items proven defective within the one year period will be replaced by BRAH Electric. In the event that we cannot provide a direct replacement, your monies will be refunded in full. We are not responsible for any consequential losses or damages outside of the defective product as well as any replacements or repairs performed by another party without our written authorization from BRAH Electric.

