

CONTACT US @ 855-355-2724 E-Mail: <u>Sales@brahelectric.com</u> www.Brahelectric.com

## **PRODUCT DATA SHEET**



**PART NUMBER – BLC2D0910-M6**: BRAH Electric, aftermarket direct replacement reversing contactors for Telemecanique LC2D0910-M6, TeSys D Series, type LC2D, 3P, 3PH, 25A, 600V, 0.5-2HP @ 240V, 0.5-5HP @ 480V, 7.5HP @ 600V, both complete with 220V 60Hz AC coil, 1 N/O auxiliary contact, AC magnetic contactor, suitable for use with LC2-D series motor control systems

## **PRODUCT SPECIFICATIONS**

MAGNETIC CONTACTOR	ΤΥΡΕ	VALUE (UNITS)	NOTES	COMMENTS
PART NO. BLC2D0910-M6	PHASE	3		
	POLES	3		
	VOLTAGE	600 (VAC)		
	AMPERAGE	25 (A)		
	COIL VOLTAGE MIN	220 (V)		
	COIL VOLTAGE MAX	220 (V)		
	MIN HP. RATING	0.5-2 (HP)	@ 240V	
	MAX HP RATING	7.5 (HP)	@ 600V	

Warranty: All Products sold by BRAH Electric are guaranteed to be free of defect for a period of one year, under the condition that the product has been installed and operated properly. All items proven defective within the one year period will be replaced by BRAH Electric. In the event that we cannot provide a direct replacement, your monies will be refunded in full. We are not responsible for any consequential losses or damages outside of the defective product as well as any replacements or repairs performed by another party without our written authorization from BRAH Electric

	REVISIONS	
		OVED
MOUNTING FIXTURES MOUNTING HOLES	LOAD SIDE WIRE TERMINALS	
		9]
4.12 [104.6]	0.51 [13.0] 1.80 [45.8]	
	AHELECTRIC.COM , 855-355-2724	1
	TILLECTRIC.CONT, 000-000-2124	
*NOTE: BRAH ELECTRIC CONTACTOR BLC2D0910-M6 IS AN AFTERMARKET DIRECT	UNLESS OTHERWISE NOTED ALL DIMENSIONS ARE IN INCHES METRIC UNITS ARE DISPLAYED BENEATH IN [MM.]	
REPLACMENT FOR LC2D0910-M6,LC2-D SERIES. SUITABLE FOR USE WITH LC2-D SERIES MOTOR CONTROL	AL THIS OF TION MATERIAL MOLDED PLASTIC CASE FINISH N/A SIZE DWG NO	REV.
SYSTEMS WOTOK CONTROL WRITTEN PERMISSION OF BRAH ELE IS PROHIBITED.	CTRIC DO NOT SCALE DRAWING A DLC 2DU9 10-1V10 SCALE:1:4 WEIGHT: 3.2 LBS SHEET 1 C	A A