

CONTACT US @ 855-355-2724 E-Mail: <u>Sales@brahelectric.com</u> www.Brahelectric.com

PRODUCT DATA SHEET



BLC2D1210-Q6

BLC2D1210-R7

BLC2D1210-T6

BLC2D1210-U6

BLC2D1210-U7

380 VAC

440 VAC

480 VAC

240 VAC

240 VAC

PART NUMBER – BLC2D1210-T6: BRAH Electric, aftermarket direct replacement contactors for Telemecanique LC2D1210-T6, TeSys D Series, direct substitute contactor, type LC2D, 3P, 3PH, 25A, 600V, 3HP @ 240V, 7.5HP @ 480V, 10HP @ 600V, complete with 480V AC coil, 1 N/O auxiliary contact, AC magnetic contactor suitable for use with LC2D series motor control systems

MAGNETIC CONTACTOR		ΤΥΡΕ	VALUE (UNITS)	NOTES	COMMENT
PART NO. BLC2D1210-T6		PHASE	3		
Voltage Selection Chart		POLES	3		
BLC2D12XX		VOLTAGE			
BLC2D12	110/120 VAC		600 (VAC)		
BLC2D1210	110/120 VAC	AMPERAGE	25 (A)		
BLC2D1210-B6	24 VAC				
BLC2D1210-B7	24 VAC	COIL VOLTAGE MAX	480 (V)		
BLC2D1210-G6	110/120 VAC	MIN HP. RATING	3 (HP)	@ 240V	
BLC2D1210-G7	110/120 VAC	MAX HP. RATING	10 (HP)	@ 600V	
BLC2D1210-M6	220 VAC] 			
BLC2D1210-M7	220 VAC				

PRODUCT SPECIFICATIONS

Warranty: All Products sold by BRAH Electric are guaranteed to be free of defect for a period of one year, under the condition that the product has been installed and operated properly. All items proven defective within the one year period will be replaced by BRAH Electric. In the event that we cannot provide a direct replacement, your monies will be refunded in full. We are not responsible for any consequential losses or damages outside of the defective product as well as any replacements or repairs performed by another party without our written authorization from BRAH Electric

-	REVISIONS ZONE REV. DESCRIPTION DATE APPROVED
MOUNTING FIXTURES LO MOUNTING HOLES	LOAD SIDE WIRE TERMINALS CATION OF FUNCTION MARKER STOPS FOR ATTACHING FRONT MOUNTED ACCESORIES
	$\begin{array}{c} 86 \\ 2.7 \\ \hline \\ 2.80 \\ 71.2 \\ \hline \\ 0.22 \\ \hline \\ 5.6 \\ \hline \\ \\ 5.6 \\ \hline \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ $
4.12 [104.6]	0.51 13.0 1.80 [45.8]
*NOTE: BRAH ELECTRIC CONTACTOR BLC2D1210-T6 IS AN AFTERMARKET DIRECT REPLACMENT FOR LC2D1210-T6,LC2-D SERIES. SUITABLE FOR USE WITH LC2-D SERIES MOTOR CONTROL SYSTEMS	AL THIS DF ION THE MATERIAL MOLDED PLASTIC CASE FINISH N/A SIZE DWG. NO. BL C2D1210-T6 REV.