

HN-MA260

I Mixer Amplifier

260W Highly flexible mixer amplifiers are designed for a wide variety of voice and background music applications such as retail shops, restaurants and bars, service centers, houses of worship, warehouses etc.



FEATURES AND BENEFIT



TWO MICROPHONE INPUTS



BUILT-IN MEDIA PLAYER

- USB/ SD Card reader (FLAC, WAV, MP3)
- FM Tuner
- Bluetooth ver 5.0
- Aux Line-in



SUPER EFFICIENT CLASS D AMPLIFIER TECHNOLOGY

- Superior output
- Low power consumption

TECHNICAL SPECIFICATIONS

| ELECTRICAL | |
|----------------------------------|--|
| Mains power supply | 180~250 Volts AC 50 Hz |
| Power consumption | 450 VA |
| PERFORMANCE | |
| Amplifier topology | Class D >90% efficiency |
| Frequency response (Mic) | 70 Hz to 20 KHz |
| Frequency response (Line) | 60 Hz to 20 KHz |
| THD + N @ 1 KHz | 0.1% |
| Bass & Treble control | +/- 10 dB |
| Mic / Line input | Phoenix connector for 2 mics RCA stereo Input for AUX Line input |
| Sensitivity | 1mV(mic) 300mV (Line) |
| Impedance | >1 kOhm (mic) 5 kOhm (Line) |
| Dynamic range | 93dB |
| S/N (flat at max volume) | 70dB (mic) 80dB (line) |
| Power Output | 260 watts 100 Volt speaker output - Phoenix connector |
| Damping factor @ 8 Ohm | 300 |
| Protection | Output Short-circuit Thermal shut-down |
| Dimension (mm) | 432 x 330 x 89 |
| Dimension (mm) | 95.2 H x 431.8 W x 304.8 D |
| Operating Temperature & Humidity | -10°C to 50°C @ 90% relative humidity (non condensing) |
| Cooling | Forced Air cooling with Fan |
| Weight | 4.75 kgs |
| Certifications | CE Complied |

THE
FUTURE
IS
WHAT
WE
MAKE IT

Honeywell