


DS1233 5V EconoReset

www.maxim-ic.com


FEATURES

- Automatically restarts microprocessor after power failure
- Monitors pushbutton for external override
- Internal circuitry debounces pushbutton switch
- Maintains reset for 350ms after V_{CC} returns to an in-tolerance condition or pushbutton released
- Accurate 5%, 10%, or 15% microprocessor
 5V power supply monitoring
- Reduces need for discrete components
- Precision temperature-compensated voltage reference and voltage sensor
- Low-cost TO-92 package or surface-mount SOT-223 package
- Internal $5k\Omega$ pull-up resistor
- Operating temperature of -40°C to +85°C

PIN ASSIGNMENT







PIN DESCRIPTION

 $\begin{array}{ll} \text{PIN 1} & \quad & \quad & \quad & \quad & \quad \\ \text{PIN 2} & \quad & \quad & \quad & \quad \\ \text{PIN 3} & \quad & \quad & \quad & \quad & \quad \\ \end{array}$

PIN 4 GROUND (SOT-223 ONLY)

DESCRIPTION

The DS1233 EconoReset monitors two vital conditions for a microprocessor: power supply and external override. A precision temperature-compensated reference and comparator circuit are used to monitor the status of the power supply (V_{CC}). When an out-of-tolerance condition is detected, an internal power-fail signal is generated which forces reset to the active state. When V_{CC} returns to an in-tolerance condition, the reset signal is kept in the active state for approximately 350ms to allow the power supply and processor to stabilize. The second function of the DS1233 is pushbutton reset control. The DS1233 debounces a pushbutton closure and will generate a 350ms reset pulse upon release.

OPERATION — POWER MONITOR

The DS1233 provides the functions of detecting out-of-tolerance power supply conditions and warning a processor-based system of impending power failure. When V_{CC} is detected as out-of-tolerance, as defined by the tolerance of the part selected, the \overline{RST} signal is asserted. On power-up, \overline{RST} is kept active for approximately 350ms after the power supply has reached the selected tolerance. This allows the power supply and microprocessor to stabilize before \overline{RST} is released.

1 of 5 122001

ABSOLUTE MAXIMUM RATINGS*

 $\begin{array}{lll} \mbox{Voltage on V_{CC} Pin Relative to Ground} & -0.5 \mbox{V to } +7.0 \mbox{V} \\ \mbox{Voltage on I/O Relative to Ground} & -0.5 \mbox{V to V_{CC}} +0.5 \mbox{V} \\ \mbox{Operating Temperature Range} & -40 \mbox{°C to } +85 \mbox{°C} \\ \mbox{Storage Temperature Range} & -55 \mbox{°C to } +125 \mbox{°C} \\ \mbox{Soldering Temperature} & 260 \mbox{°C for } 10 \mbox{ seconds} \\ \end{array}$

* This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operation sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods of time may affect reliability.

RECOMMENDED DC OPERATING CONDITIONS

(-40°C to +85°C)

PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Supply Voltage	V_{CC}	1.2	5.0	5.5	V	1

DC ELECTRICAL CHARACTERISTICS

 $(-40^{\circ}\text{C to } +85^{\circ}\text{C}; V_{DD} = 5\text{V} \pm 10\%)$

PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Low Level @ RST	$V_{ m OL}$			0.4	V	1
Output Current @ 0.4V	I_{OL}	+8			mA	
Operating Current	I_{CC}			50	μΑ	
V _{CC} Trip Point 5%	V _{CCTP0}	4.50	4.625	4.75	V	1
V _{CC} Trip Point 10%	V _{CCTP1}	4.25	4.375	4.49	V	1
V _{CC} Trip Point 15%	V_{CCTP2}	4.0	4.125	4.24	V	1
Output Capacitance	C _{OUT}			10	pF	
Pushbutton Detect	PB_{DV}	1.8		3.3	V	1
Pushbutton Release	PB_{RD}		0.3	0.8	V	1, 2
Internal Pull-Up Resistor	R_P	3.75	5	6.25	kΩ	

AC ELECTRICAL CHARACTERISTICS

 $(-40^{\circ}\text{C to } +85^{\circ}\text{C}; V_{CC} = 5\text{V} \pm 10\%)$

PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
RESET Active Time	t_{RST}	250	350	450	ms	
V _{CC} Detect to RST	$t_{ m RPD}$			100	ns	
V _{CC} Slew Rate (4.75V - 4.00V)	t_{F}	300			μs	
V _{CC} Slew Rate (4.00V - 4.75V)	t_R	0			ns	
Pushbutton Debounce	PB_{DB}	250	350	450	ms	
V _{CC} Detect to RST	$t_{ m RPU}$	250	350	450	ms	

NOTES:

- 1) All voltages are referenced to ground.
- 2) With a 100pF to $0.01\mu F$ capacitor connected from \overline{RST} to ground.

ECONORESET SELECTION GUIDE

		V _{CC} TRIP POINT			PUSHBUTTON DETECT			
		MIN	TYP	MAX	MIN	TYP	MAX	
5V	DS1233-15	4.0	4.125	4.24	1.8	-	3.3	
	DS1233-10	4.25	4.375	4.49	1.8	-	3.3	
	DS1233-5	4.5	4.625	4.75	1.8	-	3.3	
	DS1233D-15	4.0	4.125	4.24	N/A		N/A	
	DS1233D-10	4.25	4.375	4.49	N/A		N/A	
	DS1233D-5	4.5	4.625	4.75	N/A		N/A	
	DS1833-15	4.0	4.125	4.24	N/A		N/A	
	DS1833-10	4.25	4.375	4.49	N/A		N/A	
	DS1833-5	4.5	4.625	4.75	N/A		N/A	
3.3V	DS1233A-15	2.64	2.72	2.80	0.8	-	2.0	
	DS1233A-10	2.8	2.88	2.97	0.8	-	2.0	