

DC POWER SUPPLIES & DECADE BOXES

Models AX502 & AX503



Optional lead set includes two color-coded leads, one ground lead (stripped), two alligator clips and two grip probes.

Catalog #2117.78



SPECIFICATIONS

MODELS	AX502	AX503
Number of Outputs	2	3
VOLTAGE		
Output 1 & 2	0 to 30Vdc	0 to 30Vdc
Output 3 (No display)	—	2.7 to 5.5Vdc
Display Resolution	100mV	100mV
Basic Accuracy	±0.5% of Reading ± 1ct	±0.5% of Reading ± 1ct
Residual Ripple	±1mVrms	±1mVrms
LINE REGULATION		
±10% Line Voltage	±0.03% of Reading ± 2mV	
LOAD REGULATION		
0 to 2.5A	±0.02% of Reading ± 5mV	
0 to 5A	—	±0.2% Reading ±10mV
CURRENT		
Output 1 & 2	0 to 2.5A	0 to 2.5A
Output 3	—	5A max (no adjustment)
Resolution	10mA	10mA
Basic Accuracy	±0.5% of Reading ± 1ct	±0.5% of Reading ± 1ct
Limit Indicator	LED, Outputs 1 and 2	LED, Outputs 1, 2 and 3
Short-circuit Protection	Electronic current limitation with voltage shutdown	
Overheating Protection	Thermal protection	
OUTPUT COUPLING		
Tracking	Output 1: Master/Output 2: Slave Proportional Slave Tracking (0 to 100% of Master)	
Series Mode	0 to 60Vdc/0 to 2.5A	
Parallel Mode	0 to 30Vdc/0 to 5A	

FEATURES

- Dual 0 to 30Vdc/0 to 2.5A outputs
- 5.5V/5A output (Model AX503)
- Series and parallel operation permit 0 to 60V or 0 to 5A output
- Low noise (<1mV ripple) and stable linear technology for clean output
- High efficiency toroidal transformers: no fan and low electromagnetic emissions
- Active protection against overloads, short circuits and overheating
- Unique variable tracking mode for master/slave operation: slave or master track proportionally to the original setting
- Simultaneous display of voltage and current
- Highly visible green (V) and red (A) LED displays
- Compact design for bench tops
- Designed to EN 61010-1 safety standards

Models BR07 & BC05



SPECIFICATIONS

DECADE	1	2	3	4	5	6	7
BR07	1 to 10 Ω ; Max current: 700mA	10 to 100 Ω ; Max current: 200mA	100 Ω to 1k Ω ; Max current: 70mA	1 to 10k Ω ; Max current: 20mA	10 to 100k Ω ; Max current: 7mA	100k Ω to 1M Ω ; Max current: 1mA	1 to 10M Ω ; Max current: 0.1mA
BC05	0.1 to 1nF	1 to 10nF	10 to 100nF	100nF to 1 μ F	1 to 10 μ F	—	—
MODELS			BR07				
Accuracy	1%			3% (low residual capacitance)			
Residual Capacitance	—			25pF (approx.)			
Max Operating Voltage	—			300Vdc, 230Vac (50Hz)			

FEATURES

- Capacitance and resistance decade boxes
- Rotary switch selector
- Stop position to prevent accidental switching from 10 to 0
- Male ground (earth) terminal with safety jack
- Outputs on Ø 4mm safety terminals
- Ground jumper lead EN 61010-2-03, 150V CAT II, 50V CAT III, Pollution Degree 2
- Resistance ranges are 1 Ω to 11.1111M Ω for BR07 and 0.1nF to 11.111 μ F for BC05

CATALOG NO.	DESCRIPTION
2130.06	DC Power Supply Model AX502 (Dual outputs, 0 to 2.5A; 0 to 30Vdc)
2130.07	DC Power Supply Model AX503 (Triple outputs, two 0 to 2.5A; 0 to 30Vdc; 5A; 2.7 to 5.5Vdc)
2131.25	Resistance Decade Box Model BR07 (x1 Ω , x10 Ω , x100 Ω , x1k Ω , x10k Ω , x100k Ω , x1M Ω , 1%)
2131.26	Capacitance Decade Box Model BC05 (x0, 1nF, x1nF, x10nF, x100nF, x1kF, 3%)
Accessories (Optional)	
2117.78	Lead – Set of 3, (2 Color-coded Safety Leads, 1 Ground Lead, 2 Color-coded Alligator Clips and 2 Color-coded Grip Probes) for Power Supply Models AX501-AX503
2131.35	Lead – Replacement, 6 ft. Safety Lead, 4mm Female to Female for use with Decade Boxes