

ESD Safe Electric Screwdrivers

Standard Screwdrivers



TL-3000 ESD



TL-6500 ESD

ASG TL-ESD Series

- Brush type motor offers proven performance
- External torque adjustment
- Automatically stops when pre-set torque is reached
- Reduced vibration and noise
- Tamper proof torque locking nuts available
- ESD (electrostatic discharge) housing
- 4 mm drive type is a HIOS® drive (wing style)
- Inline body style

Model Number	ASG Number	Operation	Torque Range		Speed (RPM)		Length		Weight	Drive Type	Power Supply
			lbf.in	N.m	HI	LOW	mm	in.			
TL-3000-ESD	65603	Lever	0.25 - 4.0	0.03 - 0.45	1000	700	210	8.3	0.68	1/4" Hex	PS-55
TL-3000-ESD	65604	Lever	0.25 - 4.0	0.03 - 0.45	1000	700	210	8.3	0.68	4 mm	PS-55
TL-6500-ESD	65606	Lever	1.8 to 17.7	0.2 to 2.0	700	450	200	7.9	0.7	1/4" Hex	PS-55
TL-6500-ESD	65608	Lever	1.8 to 17.7	0.2 to 2.0	700	450	200	7.9	0.7	5 mm	PS-55

ASG Direct Plug-In ESD Series



AC-1120



ED-3001PSESD

- Direct plug-in 110 VAC power
- ESD (electrostatic discharge) housing
- Selectable lever/push-to-start or push-to-start only for AC Series
- Patented disk brake to prevent sparking on ED-3001PSESD model
- Intended for a duty cycle of 0.5 seconds on, 3.5 seconds off
- Inline body style

Model Number	ASG Number	Operation	Torque Range		Speed (RPM)		Length		Weight	Drive Type
			lbf.in	N.m	HI	LOW	mm	in.		
ED-3001PSESD	65530	Push-to-Start	1.8 - 10.6	0.2 - 1.2	1000	—	237	9.3	2.4	1/4" Hex
AC-1110	65540	Lever/Push-to-Start	1.8 - 8.9	0.2 - 1.0	1000	—	254	10.0	2.3	1/4" Hex
AC-1120	65541	Lever/Push-to-Start	2.7 - 17.7	0.3 - 2.0	1000	—	254	10.0	2.3	1/4" Hex
AC-1120HS	65542	Lever/Push-to-Start	3.5 - 17.7	0.4 - 2.0	2200	—	254	10.0	2.3	1/4" Hex
AC-1130	65543	Lever/Push-to-Start	3.5 - 26.0	0.4 - 3.0	1000	—	254	10.0	2.3	1/4" Hex
AC-1155	65544	Lever/Push-to-Start	8.9 - 48.7	1.0 - 5.5	400	—	267	10.5	4	1/4" Hex