



Agilent
E36XXA Series
Non-Programmable DC Power Supplies

Data Sheet



Reliable Power, Repeatable Results

- **Linear power supply**
- **Single, dual or triple output**
- **10-turn voltage and current control**
- **Low noise and excellent regulation**



Affordable, full-featured benchtop power supplies provide excellent performance and flexibility

A whole family of low-cost power supplies to meet your needs

The E3600 Series of low-cost benchtop power supplies give you the performance of system power supplies at a decent price. All E3600 family members provide clean power with excellent regulation and a fast transient response. The E3600 Series single-output non-programmable models are described on this page. Refer to page 3 for information on dual-output and triple-output non-programmable models.

Single-output models

All E3600 Series single-output non-programmable power supplies feature separate digital-panel meters for monitoring voltage and current simultaneously, giving you precise reading and control capability. All models also feature 10-turn potentiometers for accurate adjustment of voltage and current output settings.

With 0.01 percent load and line regulation, these instruments keep the output steady when power line and load changes occur.

The low normal mode noise specification of less than 200 μ Vrms ensures clean power for precision circuitry.

In all single-output models, either the positive or negative terminal can be connected to ground, providing a positive or negative voltage output. Outputs can also be floated up to 240 V from ground.

These instruments also feature adjustable current limits, letting you set the safest current limit without having to short the output.

E3610A, E3611A, and E3612A single-output, dual range models

These popular 30-watt bench supplies are designed for general laboratory use. The constant-voltage, constant-current output allows operation as either a voltage or current source. The changeover occurs automatically, based on the load. Each of these models has two ranges, allowing more current at a lower voltage. For higher output voltages, supplies can be connected in series. These models also feature overload protection. A continuously acting constant current circuit protects the power supply against all overloads including a direct short placed across the terminals in a constant voltage operation.

E3614A, E3615A, E3616A and E3617A models feature overvoltage protection, remote sensing and remote programming

These flexible 60-watt, single-range power supplies can be used as either voltage or current sources. When the output terminal voltage increases to a preset shut-down level, an overvoltage protection circuit disables the output to protect the device under test (DUT) for damage. The overvoltage protection feature can be easily monitored and adjusted from the front panel.

Using the remote sensing capability, these instruments automatically compensate for voltage drop in the load leads, so you obtain an accurate voltage at the DUT.

Using the remote analog voltage programming capability, these instruments can remotely vary the voltage, so you are able to control the regulation output voltage or current.

You can combine multiple units in auto-parallel, auto-series and auto-tracking configurations for greater output voltage or current capacity. Front and rear output terminals allow for a flexible configuration. The output voltage and current can be controlled with external 0– to 10– volt analog voltage or variable resistance.

Multiple-output non-programmable models

With multiple supplies in a compact unit, the E3620A and E3630A provide excellent performance while saving space on your bench. Both instruments feature a tight 0.01 percent line and load regulation and a low normal mode noise specification of less than 0.35 mV to ensure clean power for precision circuitry. With a common mode current specification of less than 1 μ A, both multiple-output power supplies minimize the power line current injection.

Like the single-output models in the E3600 Series, the E3620A and E3630A feature separate digital panel meters so you can monitor the voltage and current simultaneously. They also protect your DUT against overload and short-circuit damage.

Smooth turn-on and turn-off transitions keep power spikes out of your circuits. Auto-tracking permits equal or proportional voltage sharing, and allows control of output voltage from one master unit. The master and slave supplies have the same output polarity with respect to a common bus or ground. This operation is useful where simultaneous turn-up, turn-down or proportional control of all power supplies is required.

E3620A dual-output power supply

The 50-watt E3620A dual-output power supply provides two 0 V to 25 Vdc outputs with the maximum current of 1 A to satisfy most bench requirements. The outputs are completely independent and isolated.

E3630A triple-output power supply with auto-tracking feature

The 35-watt E3630A triple-output power supply provides three DC outputs: 0 to 6 V with a maximum current of 1 to 2.5 A and 0 to 20 V and 0 to -20 V with a maximum current of 0.5 A. An auto-tracking feature lets you use one voltage control to adjust the +20 V and -20 V outputs simultaneously. The outputs track each other to within 1 percent, making it easy to adjust the power supply for circuits requiring balanced voltages.

Specifications

	E3610A	E3611A	E3612A	E3614A	E3615A	E3616A	E3617A	E3620A	E3630A
Features	Dual range, 10 turn pots, Constant Voltage (CV), Constant Current (CC) modes.			Adjustable overvoltage protection, voltage & resistance programming, remote sense, rear outputs, ten turn pots, CV, CC modes. Multiple supplies can be connected for tracking or higher power.				Isolated dual outputs, 10 turn pots CV, CL	Tracking, CV, CL (± 20 V) CV, CF (+6 V)
Number of outputs	1							2	3
Number of Output Ranges	2	2	2	1	1	1	1	1	1
DC Output Rating	8 V, 3 A 15 V, 2 A	20 V, 1.5 A 35 V, 0.85 A	60 V, 0.5 A 120 V, 0.25 A	8 V, 6 A	20 V, 3 A	35 V, 1.7 A	60 V, 1 A	25 V, 1 A 25 V, 1 A	+6 V, 2.5 A +20 V, 0.5 A -20 V, 0.5 A
Load and Line Regulation	< 0.01% + 2 mV								
Ripple and Noise (20 Hz to 20 MHz)									
Normal mode voltage	< 200 μ Vrms, < 2 mVpp			< 200 μ Vrms, < 1 mVpp				< 350 μ Vrms, < 1.5 mVpp	
Normal mode current	< 200 μ Arms, < 1 mVpp			< 0.02% + 3 mA	< 0.02% + 1.5 mA	< 0.02% + 1 mA	< 0.02% + 0.5 mA	-	
Common mode current	Not specified							< 1 μ Arms	
Transient Response Time	< 50 μ sec following a change in output current from full load to half load for output to recover within:								
	10 mV			15 mV					
Meter Accuracy	$\pm 0.5\%$ + 2 counts at 25 $^{\circ}$ C ± 5 $^{\circ}$ C								
Meter Resolution									
Voltage	10 mV	100 mV	100 mV	10 mV	10 mV (0–20 V), 100 mV (>20 V)				10 mV
Current	10 mA	10 mA	1 mA	10 mA	10 mA	1 mA	1 mA	1 mA	10 mA
Isolation	240 Vdc								

Supplemental Characteristics

	E3610A	E3611A	E3612A	E3614A	E3615A	E3616A	E3617A	E3620A	E3630A	
Control Mode	CV/CC						CV/CL		CV/CL (± 20 V) CV/CF (+6 V)	
Temperature Coefficient per °C										
Voltage	< 0.02% + 1 mV			< 0.02% + 500 μ V			< 0.02% + 1 mV			
Current	< 0.02% + 2 mA			< 0.02% + 3 mA	< 0.02% + 1.5 mA	< 0.02% + 1 mA	< 0.02% + 0.5 mA	-		
Output Drift										
Voltage	Less than 0.1% + 5 mV total drift for 8 hours after initial warm-up of 30 minutes									
Current	Less than 0.1% + 10 mA total drift for 8 hours after initial warm-up of 30 minutes							N/A		
Temperature Range										
	0 to 40 °C for full rated output. Derate output current 1% per °C between 40 °C to 55 °C						Derate output current 50% between 40 °C to 55 °C			
Cooling	Convection cooling									
Isolation	± 240 Vdc									
AC Input	100 Vac $\pm 10\%$, 47–63 Hz (opt. 0E9) 115 Vac $\pm 10\%$, 47–63 Hz (std) 230 Vac $\pm 10\%$, 47–63 Hz (0E3)									
Weight	3.8 kg (8.4lbs) net, 4.2 kg (9.3 lbs) shipping			5.5 kg (12.1 lbs) net, 6.75 kg (14.9 lbs) shipping			5.0 kg (11.0 lbs) net, 6.25 kg (13.8 lbs) shipping		3.8 kg (8.4 lbs) net, 5.1 kg (11.3 lbs) shipping	
Size	88.1 mm H x 212.3 mm W x 318.4 mm D 3.5" H x 8.4" W x 12.5" D			88.1 mm H x 212.3 mm W x 373.4 mm D 3.5" H x 8.4" W x 14.7" D			88.1 mm H x 212.3 mm W x 392.4 mm D 3.5" H x 8.4" W x 15.4" D		Same as E3610A	
Warranty	One year for E3600 Series power supplies Three months for standard shipped accessories									
Product Regulation	Certified to CSA 22.2 No. 231; conforms to IEC 1010-1; carries CE mark; complies with CISPR-11, Group 1, Class A									

Ordering Information

E3600 Series Power Supplies

E3610A 30-Watt Power Supply
E3611A 30-Watt Power Supply
E3612A 30-Watt Power Supply
E3614A 48-Watt Power Supply
E3615A 60-Watt Power Supply
E3616A 60-Watt Power Supply
E3617A 60-Watt Power Supply
E3620A Dual-output Power Supply
E3630A Triple-output Power Supply

Standard Shipped Accessories

User's guide, Product Reference CD,
power cord

Power Options

Opt. 0E3 230 Vac $\pm 10\%$
Opt. 0EM 115 Vac $\pm 10\%$
Opt. 0E9 100 Vac $\pm 10\%$

Other Options

Opt. 1CM Rackmount kit* (Only
applicable for E3614A, E3615A,
E3616A, E3617A and E3620A)
Opt. 0L2 Extra manual
Opt. UK6 Commercial calibration with
test result data
E3600A-100 Test lead kit

Extra Manual Sets

E3610A/11A/12A Manual
(P/N 5959-5304)
E3614A/15A/16A/17A Manual
(P/N 5959-5310)
E3620A Manual
(P/N E3620-90001)
E3630A Manual
(P/N 5959-5329)

Rackmount Kits*

E3614A/15A/16A/17A/20A

To rackmount two instruments side-
by-side

- Lock-link Kit (P/N 5061-9694)
- Flange Kit (P/N 5063-9212)

To rackmount one or two instruments
in a sliding support shelf

- Support Shelf (P/N 5063-9255)
- Slide Kit (P/N 1494-0015)
required for support shelf

For a single instrument, also order
filler panel (P/N 5002-3999)

* Rackmounting with 1CM or lock-
link/flange kit requires

- Agilent or customer support rails
- Agilent Support Rails-E3663AC.



Agilent Email Updates

www.agilent.com/find/emailupdates
Get the latest information on the products and applications you select.



Agilent Direct

www.agilent.com/find/agilentdirect
Quickly choose and use your test equipment solutions with confidence.



www.agilent.com/find/open
Agilent Open simplifies the process of connecting and programming test systems to help engineers design, validate and manufacture electronic products. Agilent offers open connectivity for a broad range of system-ready instruments, open industry software, PC-standard I/O and global support, which are combined to more easily integrate test system development.

Remove all doubt

Our repair and calibration services will get your equipment back to you, performing like new, when promised. You will get full value out of your Agilent equipment throughout its lifetime. Your equipment will be serviced by Agilent-trained technicians using the latest factory calibration procedures, automated repair diagnostics and genuine parts. You will always have the utmost confidence in your measurements.

Agilent offers a wide range of additional expert test and measurement services for your equipment, including initial start-up assistance onsite education and training, as well as design, system integration, and project management.

For more information on repair and calibration services, go to

www.agilent.com/find/removealldoubt

Product specifications and descriptions in this document subject to change without notice.

www.agilent.com

For more information on Agilent Technologies' products, applications or services, please contact your local Agilent office. The complete list is available at:

www.agilent.com/find/contactus

Phone or Fax Americas

Canada	(877) 894-4414
Latin America	305 269 7500
United States	(800) 829-4444

Asia Pacific

Australia	1 800 629 485
China	800 810 0189
Hong Kong	800 938 693
India	1 800 112 929
Japan	0120 (421) 345
Korea	080 769 0800
Malaysia	1 800 888 848
Singapore	1 800 375 8100
Taiwan	0800 047 866
Thailand	1 800 226 008

Europe & Middle East

Austria	01 36027 71571
Belgium	32 (0) 2 404 93 40
Denmark	45 70 13 15 15
Finland	358 (0) 10 855 2100
France	0825 010 700* *0.125€/minute
Germany	07031 464 6333
Ireland	1890 924 204
Israel	972-3-9288-504/544
Italy	39 02 92 60 8484
Netherlands	31 (0) 20 547 2111
Spain	34 (91) 631 3300
Sweden	0200-88 22 55
Switzerland	0800 80 53 53
United Kingdom	44 (0) 118 9276201

Other European Countries:

www.agilent.com/find/contactus

Revised: October 6, 2008

© Agilent Technologies, Inc. 2009
Printed in USA, October 20, 2009
5968-9727EN



An Interworld Highway, LLC Company



Agilent Technologies