

## Common Emissivity Values

| Material             | Emissivity  | Material                   | Emissivity  |
|----------------------|-------------|----------------------------|-------------|
| Aluminum (oxidized)  | 0.25        | Marble                     | 0.9         |
| Aluminum (polished)  | 0.1         | Matte black paint          | 0.95        |
| Asbestos             | 0.95        | Nickel (pure)              | 0.1         |
| Brass (oxidized)     | 0.6         | Nickel plate (oxidized)    | 0.95        |
| Brass (polished)     | 0.1         | Paper                      | 0.9         |
| Carbon               | 0.75        | Plaster                    | 0.9         |
| Carborundum          | 0.85        | Plastics                   | 0.8 to 0.95 |
| Cardboard            | 0.9         | Quartz                     | 0.9         |
| Cast Iron (polished) | 0.2         | Red Brick                  | 0.75 to 0.9 |
| Cast Iron (rusted)   | 0.95        | Rubber (rough)             | 0.98        |
| Chromium (polished)  | 0.1         | Rubber (smooth)            | 0.9         |
| Concrete             | 0.7         | Silica                     | 0.4         |
| Copper (oxidized)    | 0.8         | Silver (polished)          | 0.1         |
| Copper (polished)    | 0.05        | Stainless Steel (other)    | 0.2 to 0.6  |
| Gold (polished)      | 0.1         | Stainless Steel (polished) | 0.1         |
| Iron plate           | 0.7 to 0.85 | Steel (ground sheet)       | 0.6         |
| Lead (oxidized)      | 0.3         | Steel (Mild)               | 0.3 to 0.5  |
| Lead (pure)          | 0.1         | Steel plate                | 0.9         |
|                      |             | Timber                     | 0.8 to 0.9  |
|                      |             | Water                      | 0.98        |
|                      |             | Zinc (oxidized)            | 0.1         |

## F. MAINTENANCE

1. Clean the surface of the instrument and optical lens with a damp cloth.
2. Replace the 9 Volt battery when the low battery indicator appears on the LCD.

## G. TROUBLE SHOOTING

### Symptom

Temperature seems inaccurate.

### Probable Cause

- Dirty optical lens.
- Low battery.
- Instrument held too far away from target increasing desired target area.
- Target surface has poor emissivity qualities.
- Laser sight out of alignment.

371/373 does not turn on.

- Dead or low battery.
- Defective POWER ON switch.
- Broken batter connector.

Laser does not turn on.

- Low battery.
- Broken connector to Laser.



**Infrared Thermometers 375,376,377**  
from Test Products International, Inc.



### Test Products International, Inc.

9615 SW Allen Blvd., Ste. 104  
Beaverton, OR USA 97005  
503-520-9197 • Fax: 503-520-1225  
tpisales@tpi-thevalueleader.com

### Test Products International, Ltd.

342 Bronte Road South, Unit 9  
Milton, Ontario L9T5B7  
Canada  
905-693-8558 • Fax: 905-693-0888

L373M • 4/24/00 copyright © 2000 Test Products International, Inc.

# The Value Leader™

Visit [www.tpi-thevalueleader.com](http://www.tpi-thevalueleader.com)

## A. INTRODUCTION

1. Congratulations: Thank you for purchasing TPI products. The 370 Series are easy to use and built to last. All are backed by a 3 year limited warranty. Please remember to complete and return your product warranty registration card.
2. Product Description: The 370 Series are non-contact temperature testers with laser sighting to confirm you target. They are easy to use and fit comfortably in your hand. All have built in K-type thermocouple inputs for optional contact temperature measurement

## B. SAFETY CONSIDERATIONS

1. Never point the laser beam at someone's eyes.
2. Never look directly at the laser beam.
3. Use caution when measuring a shiny surface so the laser does not reflect back into your or someone else's eyes.
4. Do not touch the lens to any foreign object.
5. Do not expose the unit to damp environments for extended periods of time.

## C. TECHNICAL DATA

|                                     |  |
|-------------------------------------|--|
| Temperature Range                   |  |
| 375:                                | 0° to 950°F (-18° to 510°C)                                |
| 376:                                | -58° to 950°F (-50° to 510°C)                              |
| 377:                                | 0° to 1832°F (-18° to 1000°C)                              |
| Accuracy @ 23°C and 0.95 emissivity | ± 2% of reading or ± 3.5°F (which is greater)              |
| Emissivity                          | 0.3 to 0.95 adjustable                                     |
| Laser Sighting                      | Output <1mW, Wavelength 645-660nm, Class II Laser          |
| °F or °C Selectable                 | Yes  |
| Distance to Spot Ratio              | 8 : 1  |
| Display Hold                        | Yes, last reading held for 7 seconds after trigger release |
| Response Time                       | 1 second   |
| Spectral Response                   | 7 - 14 um  |
| Operating Temperature               | 32° to 120°F (0° to 150°C)                                 |
| Battery Type                        | 9 Volt   |
| Display Resolution                  | 0.1°F (°C) or 1°F (°C)                                     |
| Type K Range                        | -40° to 2192°F (-40° to 1200°C)                            |
| Type K Accuracy                     | ± 0.5% of reading ±3°F (2°C)                               |

## D. MEASUREMENT TECHNIQUES

### Controls and Functions


1. **TRIGGER:** Squeeze the trigger to turn the instrument on. Release the trigger and the last reading is held on the display for approximately 7 seconds.
2. **SEL:** Toggles on and off the laser, backlight and K-type thermocouple measurement functions of instrument.
3. **LOCK:** This locks the power on and is indicated by the word LOCK on the LCD. You can release the trigger and the instrument remains on. Pushing the LOCK button once more deactivates the lock feature and the unit will turn off after 10 seconds.
4. **°F/°C:** This button allows you to view the reading in Fahrenheit of Celsius. The thermometer will power on in the unit of measurement last set when the thermometer automatically powered off.
5. **⌵:** This button allows the user to adjust the emissivity setting of the instrument (refer to chart on page ).
6. **REC:** This button activates the record function to store minimum and maximum temperatures.

**CAUTION: LASER RADIATION - DO NOT STARE INTO BEAM. OUTPUT <1mW WAVELENGTH 645 - 660nm. CLASS II LASER PRODUCT.**


### Measuring Temperature:

1. Turn the thermometer on by either squeezing the trigger or squeezing the trigger and pushing the LOCK button.
2. Line up the laser with the target and hold the front of the thermometer eight inches from the target (spot size will be one inch at this distance).
3. Read the temperature on the LCD.

### Turning the laser ON and OFF:

1. Squeeze the trigger on the instrument (do not push the LOCK button) and hold it in.
2. Push the SEL button until the laser icon  is either on the LCD or not on the LCD (when the icon is on the LCD, the laser is activated).

### Turning the Back Light ON and OFF

1. Squeeze the trigger on the instrument (do not push the LOCK button) and hold it in.
2. Push the SEL button until the Back Light icon  is either on the LCD or not on the LCD (when the icon is on the LCD, the Back Light is activated).

### Adjusting Emissivity

1. Squeeze the trigger on the instrument and hold it in or push the LOCK button to lock the instrument ON..
2. Push the ⌵ button and the "⌵." will start flashing on the LCD.
3. Push the LOCK button to increase the emissivity or the C/F button to decrease the emissivity.
4. Push the ⌵ button to save the setting.

### Recording Minimum and Maximum Temperatures

1. Squeeze the trigger on the instrument and hold it in or push the LOCK button to lock the instrument ON.
2. Push the REC button to activate the Record function. You will see REC on the LCD.
3. Push the REC button to toggle between the recorded Max and Min temperatures during the measurement period.
4. Pushing in the REC button and holding it in for 3 seconds deactivates the REC mode (or turn the unit off).

### Changing from °C to °F (or °F to °C)

1. Squeeze the trigger on the instrument and hold it in or push the LOCK button to lock the instrument ON.
2. Push the °C/°F push button to select the desired measurement unit.

### Measuring Temperature with K-type Thermocouple

1. Squeeze the trigger on the instrument and push the LOCK button (make sure the display says LOCK).
  2. Press the SEL push button.
  3. Make sure there is a K next to the word LOCK on the display.
  4. Plug the temperature probe into the socket on the lower section of the thermometers handle.
  5. Insert the probe tip into the air, liquid or surface to be measured.
  6. Read the temperature on the LCD of the thermometer.
- NOTE: You can select the mode of measurement (°F/°C) or the REC function for K-type temperature measurement.

### Setting Emissivity using K-Type Contact Probe When Emissivity is not Known

1. Squeeze the trigger on the instrument and push the LOCK button (make sure the display says LOCK).
2. Press the SEL push button.
3. Make sure there is a K next to the word LOCK on the display.
4. Plug the contact temperature probe into the socket on the lower section of the thermometers handle.
5. Touch the end of the probe to the surface to be measured and record the temperature when the reading stabilizes.
6. Remove the temperature probe from the instrument.
7. Push the LOCK button and let the instrument turn off (Do not push in the trigger).
8. After the unit turns off, squeeze the trigger and point the instrument at the location the contact probe took the measurement.
9. Press the ⌵ button and push the LOCK or °C/°F until the reading on the display matches the recorded reading in step 5 above.
10. Press the SEL button to save the setting.
11. Emissivity is now set for the surface being measured.