

## EK-500LUA RC Command List

| key position | key legend  | data code(hex) |
|--------------|-------------|----------------|
| 1            | Input       | 40             |
| 2            | Power ON    | 17             |
| 3            | VGA         | 1B             |
| 4            | VIDEO       | 25             |
| 5            | HDMI        | 1F             |
| 6            | MENU        | 00             |
| 7            | AUTO        | 0F             |
| 8            | UP          | 18             |
| 9            | LEFT        | 19             |
| 10           | OK          | 07             |
| 11           | RIGHT       | 08             |
| 12           | DOWN        | 09             |
| 13           | KEystone    | 03             |
| 14           | IMAGE       | 41             |
| 15           | FREEZE      | 13             |
| 16           | PATTERN     | 14             |
| 17           | SCREEN      | 1C             |
| 18           | LIGHT       | 01             |
| 19           | MUTE        | 0D             |
| 20           | INFORMATION | 02             |
| 21           | D.Zoom +    | 1D             |
| 22           | VOLUME +    | 06             |
| 23           | BLANK       | 15             |
| 24           | D.Zoom -    | 0E             |
| 25           | VOLUME -    | 23             |
| 26           | TIMER       | 42             |

ID Custom Code    0x0135

