

**Ideal for: HVAC, Hospitals, Laboratories,
Computer Rooms, Paper Mills, General Use,
Wood & Furniture Industry, Industrial,
Printing, Nurseries, Film Processing,
Greenhouses, Tobacco Industry**

FEATURES:

- Simultaneous Display of Temperature and Humidity
- °F/°C Switch
- Auto Power Off:
Approximately after 20 minutes
- MIN/MAX Memory
- RESET Switch
- HOLD Switch
- Pocket-sized • Belt or Pocket Clip

SPECIFICATIONS:

- Range: 14° to 122°F (-10° to 45°C)
- Humidity Range: 5 to 95% RH
- Accuracy: $\pm 3\%$ from 10 to 90%RH
at 77°F (25°C); $\pm 5\%$ from 5 to 10%RH
and from 90 to 95%RH
- Resolution: 0.1°F/0.1°C
- Sensor: Electronic Capacitance
Polymer Film Sensor
- Power Source: 1 "CR2032" battery (included)
- Battery Life: 150 hours
- Dimensions: 6.9" x 1.7" x 0.6"
(175 x 42 x 16 mm)
- Weight: 1.6 oz (45 g)
- Color: Dark Gray

GENERAL®

PTH8708

USER'S MANUAL

GENERAL®

Specialty Tools & Instruments

GENERAL TOOLS & INSTRUMENTS™

75 Seaview Drive
Secaucus, NJ 07094-1806
PHONE (212) 431-6100
FAX (212) 431-6499
TOLL FREE (800) 697-8665

e-mail: sales@generaltools.com
www.generaltools.com

PTH8708 User's Manual

Specifications subject to change
without notice

©2015 GENERAL TOOLS & INSTRUMENTS

*NOTICE - WE ARE NOT
RESPONSIBLE FOR
TYPOGRAPHICAL ERRORS.*
MAN#PTH8708 05/08



**DIGITAL
TEMPERATURE/
HUMIDITY
PEN**

NORMAL MEASUREMENT:

1. Turn meter on by pressing “ON/OFF” button.
2. Press “C/F” key to convert reading to desired range. Both temperature and relative humidity measurement will display simultaneously.

MIN/MAX FUNCTION:

1. Press and hold “MIN/MAX” button until (MIN) appears on display. Display is now showing minimum humidity and temperature reading in memory.
2. Press and hold “MIN/MAX” button again until (MAX) appears on display. Display is now showing maximum humidity and temperature readings in memory.
3. To return to current temperature and humidity readings, press and hold “MIN/MAX” button until (MIN) or (MAX) disappears from display.
4. To clear current “MIN” and “MAX” reading from memory, press and hold “RESET” button until entire display flashes.

DATE HOLD FUNCTION:

1. Press “HOLD” button until (HLD) appears in display. The current reading is now being held and will not change until “HOLD” function is cancelled.
2. Press “RESET” button to cancel the “HOLD” function. The Hold function

can be used for temperature, humidity, dew-point and wet bulb.

AUTO POWER OFF:

1. Unit will turn itself off after 20 minutes. (Sleep mode)
2. To override Auto Power Off function (Non-Sleep Mode) press “ON/OFF” and “MIN/MAX” button simultaneously. After the full display appears release “ON/OFF” button, the display will show “n” in left side. When “n” appears, then release “MIN/MAX” button. Unit will now be in Non-sleep Mode.

CHANGING THE BATTERY:

1. Use a coin to turn off the battery cover.
2. Put the battery whose “+” faces out into the battery compartment, place the battery cover back and lock it.

NOTE: Remember low batteries will tend to give inaccurate readings, so make sure you have good batteries.

Please do not immerse probe into liquids as this will cause permanent damage to the sensor.