



American Hakko Products, Inc.

# PRODUCT BULLETIN

**Bulletin No:** PB267

**Issue Date:** 1-10-2008

**Effective date:** 1-10-2008

**Product Description:**

Hakko FR-803B

**Part No:**

FR803B-11

**Specification:**

Model	FR-803B
Power Consumption	120V – 440W



**Station**

Power Consumption	120V – 40W (4W in Standby Mode)
Airflow	5 L/min to more than 20 L/min
Control Temperature (as measured at sensor)	100 ~ 500°C (200 ~ 930°F)
Modes	Manual or Auto
Memory	Up to 50 3-stage profiles
Dimensions (W x H x D)	160 x 145 x 230 mm (6.3 x 5.7 x 9.1 in.)
Weight	5 kg (11.02 lb.)

**Handpiece**

Power Consumption	120V – 400W
Total Length (w/o cord)	200 mm (7.9 in.)
Weight (w/o cord)	200 g (0.44 lb.)

**Comments:**

This product replaces the Hakko FR-803. The Hakko FR-803B has most the same specifications as the Hakko FR-803 with the exception of the maximum set temperature, which was raised from 450°C to 500°C (840°F to 930°F). The Hakko FR-803B also has increased memory capacity, which can now store up to 50 separate 3-stage rework profiles (the Hakko FR-803 had a maximum of 3).

For more information on this product, please visit our web site at [www.HakkoUSA.com](http://www.HakkoUSA.com)

Hakko FR-803B SMD Rework Station

From...

For additional information:

- End-User Customers – Call Customer Support at 1-800-88-HAKKO (42556)
- Authorized Distributors – Call Distributor Support at 661-294-0090

American Hakko Products, Inc.  
 28920 Avenue Williams.  
 Valencia, CA 91355  
 Tel: (661) 294-0090  
 Fax: (661) 294-0096  
[www.HakkoUSA.com](http://www.HakkoUSA.com)  
 AHP14 Rev 2007-12