

120V AC CIRCUIT BREAKER FINDER

W/FLASHLIGHT, NCVT & GFCI RECEPTACLE TESTER



61-535 120V AC CIRCUIT BREAKER FINDER

- cULus Certified (UL 1436, CSA C22.2 No. 160), CAT II 150V
- Quickly and easily identifies circuit breakers/fuses without disrupting power on energized 120V AC circuits
- Clear Visual and Audible indicators (audible signal can be muted)
- NCVT in receiver tip indicates presence of AC voltage between 80-300V AC
- Flashlight in receiver operates independently of the tester functions and can be used to illuminate work area
- Transmitter tests outlet wiring configurations (indicated via Green/Red LEDs) and tests GFCIs
- Receiver powers off automatically after 5 minutes of non-use to conserve battery life

Narrower Tip
improves breaker identification accuracy

LED Flashlight
operates independently and illuminates work area

Transmitter
sends a signal over the conductors when connected to an energized circuit. It also identifies the presence of power and indicates correct/incorrect wiring conditions via illuminated green and red LED's. A GFCI test light illuminates when the GFCI Test button is pressed, indicating the activation of the GFCI test. The GFCIs will trip if they are functioning properly



NOTE: Receptacle MUST be properly grounded for the GFCI test to work properly.

NOTE: The transmitter works on LIVE/Energized circuits only



Receiver
powers off automatically after five minutes of non-use to conserve battery life

Lanyard Mount



NCVT
in receiver tip indicates presence of AC voltage between 80-300 volts (visual flashing red LEDs & audible indicators)



Receiver
reads the transmitter's signal and identifies the breaker/finder energizing the circuit by illuminating a flashing green LED and emitting beeps once it determines the breaker/fuse with the strongest signal.

LED Flashlight

Audible Defeat
for noise sensitive areas

ON/OFF
toggles between circuit breaker finding and NCVT functions (default is circuit breaker finding)



SCAN
to learn more



THE ELECTRICIAN'S
CHAMPION™



120V AC CIRCUIT BREAKER FINDER


W/FLASHLIGHT, NCVT & GFCI RECEPTACLE TESTER

61-535
Transmitter

61-535
Receiver



SCAN
to learn more



CIRCUIT BREAKER FINDER SELECTION GUIDE



**REPLACED BY
THE ENHANCED
AND
ERGONOMIC
61-535**



TRANSMITTER FEATURES	61-535	61-534	61-532
CAT Rating (Safety)	CAT II 150V	CAT II 300V	CAT II 300V
Listing	UL 1436, CSA C22.2 No. 160	UL 1436, CSA C22.2 No. 160	UL 1436, CSA C22.2 No. 160
Line Voltage	Line Powered (120V AC)	Line Powered (120V AC)	Line Powered (120V AC)
Supply Frequency	60Hz	47-63Hz	47-63Hz
Weight	28.35g (approx.)	50g (approx.)	50g (approx.)
Flashlight	✓	—	—
NCVT	✓	—	—
Power Consumption	1.5W max. @ 120V AC	200mW max. @ 120V AC	200mW max. @ 120V AC
Correct/Wiring Fault/Polarity Indications	✓	✓	—
GFCI Trip/Test	✓	✓	—
GFCI Trip Test Indicator	✓	—	—
RECEIVER FEATURES	61-535	61-534	61-532
Visual and Audible Indicators	✓	✓	✓
Low Battery Indication	✓	✓	✓
Auto Power Off (after no activity)	(after 5 minutes)	(after 10 minutes)	(after 10 minutes)
Battery Type	9V	9V	9V
Weight	85g (w/o battery)	85g (w/o battery)	85g (w/o battery)
Warranty	2-Year*	2-Year*	2-Year*
ACCESSORIES	61-535	61-534	61-532
Light Socket, 3 to 2-Prong Adapters, Alligator Clips	TL-532A	TL-532A	TL-532A

* Visit www.idealind.com for warranty details.

Specifications are subject to change without notice.

P-6070 (02-23)
©2023 IDEAL INDUSTRIES, INC.

IDEAL CUSTOMER SERVICE:
orderdesk@idealindustries.com
1-800-824-3325
www.idealind.com

THE ELECTRICIAN'S
CHAMPION™

