



### FEATURES

- 4.3" TFT LCD Display
- Supports Setting Value, Measurement Value and Output Waveform Display
- Load Function (CC, CV, CR Mode)
- Setting Resolution: 1mV/0.1mA ; Read Back Resolution: 0.1mV/0.1mA
- Low Ripple Noise:  $\leq 350\mu\text{Vrms}/\leq 2\text{mArms}$
- Transient Response Time:  $\leq 50\mu\text{s}$
- Tracking Series and Parallel Function without Additional External Wiring
- Utilizing Hardware to Realize Over Voltage Protection/Over Current Protection/Over Temperature Protection
- Delay Function/Output Monitoring Function/Output Recorder Function
- Intelligent Temperature Control Fan Effectively Reduces Noise
- Sequential Output Function and Built-in 8 Template Waveforms
- The Output Recorder Function Records The Output Voltage & Current Parameters with A Minimum Recording Interval of 1 Second
- Provides 10 Sets of Memory for Each Sequence/Delay/Recorder/Panel Setting Condition
- GPP-3323 Supports A USB(Type A)Output Terminal
- Standard: RS-232, USB, Ext I/O ; Optional (Manufacturer Installed Only) : LAN, GPIB+LAN
- Compatible with Commands of GPD-X303S Series



With the maximum output power of 217W, the GPP-Series, the multi-channel programmable DC power supply, includes four models: GPP-1326 (0~32V/0~6A) for single-channel output and GPP-2323 for dual-channel output (CH1:0~32V/0~3A, CH2:0~32V/0~3A), GPP-3323 for three-channel output (CH1: 0~32V/0~3A, CH2:0~32V/ 0~3A, CH3: 1.8V, 2.5V, 3.3V, 5.0V/5A) and GPP-4323 for four-channel output (CH1:0~32V/0~3A, CH2:0~32V/0~3A, CH3:0~5V/0~1A, CH4: 0~15V/0~1A). This series not only provides high program resolution (1mV/0.1mA) and read back resolution (0.1mV/0.1mA), but also features optimal low-ripple noise characteristics  $\leq 350\mu\text{Vrms}/\leq 2\text{mArms}$  and output transient recovery capability  $\leq 50\mu\text{s}$ . Independent output on-off switch is provided for each channel.

For series and parallel applications of CH1 and CH2, the tracking function of the GPP-Series utilizes the internal circuit to automatically switch the output to serial or parallel output without additional external wiring, providing users with convenience not only in operating procedures but also a more stable output. The tracking function design of other brands requires additional external wiring connections for the output in series or parallel. However, excessively long, thin or inconsistent external wiring may cause inaccurate voltage or current output.

The GPP-Series offers a variety of display modes, including single or multi-channel setting values, measurement values, and waveform displays. The Monitor function of the GPP-Series allows users to set monitoring conditions according to requirements, sound alarms or stop output during the measurement process, and stop measurement and protect the customer's DUT. The GPP-Series provides output recorder function, which records the voltage/current of the output process to the internal memory, and the result can be stored as a (\*.REC) or (\*.CSV) file, which can then be transferred to the USB flash drive. The stored \*.CSV can be exported to the Excel to conduct the future analysis.

The CH1/CH2 of the GPP-Series are designed with the load function. A single power supply can set one channel as the power output, and one channel for the load function to consume the power of the DUT so as to meet the basic charging and discharging test requirements for battery. Channel 1 and channel 2 not only provide 32V/3A power output, but also feature built-in maximum 32V constant voltage load (CV), maximum 3.2A constant current load (CC) and maximum 1k $\Omega$  constant resistance load (CR) function.

The GPP-Series provides the sequential output function on Channel 1 and Channel 2. This function not only allows users to edit the power output waveform, but also allows users to set the sequential constant voltage (CV) or constant current (CC) load waveform, i.e. a serial power output or a simulation test of a dynamic load. In order to simplify the setting of waveform editing, the GPP-Series has 8 built-in Template waveforms in the sequence output function for users to directly apply for output, including Sine, Pulse, Ramp, Stair Up, Stair Dn, Stair UpDn, Exp Rise, Exp Fall waveforms.

The sound protection functions include OVP/OCP/OPP/OTP, in which the protection mechanism for OVP/OCP/OTP is implemented by hardware circuit that has the advantage of faster response time compared with competitors who adopt software to achieve protections. The OVP/OCP functions allow users to set the protection action point (except CH3 of GPP-3323) according to the conditions of the DUT. The OPP is only activated during the operation of the load function. The Delay Function sets the length of time during channel 1 or channel 2 power output on or during power output off.

In addition, the Trigger In/Trigger Out functions synchronize external devices. The GPP-3323 channel 3 adds a 3A USB (Type A) output terminal for USB charging test. The intelligent temperature-controlled fan can adjust the speed according to the temperature of the power transistor so as to reduce unnecessary noise. The output value setting and the Sequence/Delay/Recorder functions provide 10 sets of internal memory for use, and can be loaded/stored using a USB flash drive. In addition to the standard RS-232 and USB remote interfaces, the GPP-Series also has an optional LAN or LAN+ GPIB interface to facilitate different requirements. The commands of the GPP series conform to SCPI requirements and are compatible with the commands of the GPD-X303S series.



Front Panel



Rear Panel

### APPLICATIONS

- School and Research Institute
- Energy Storage Device Industry
- Semiconductor Industry
- Consumer Electronics Industry



## SPECIFICATIONS

		GPP-4323				GPP-3323			GPP-2323		GPP-1326
OUTPUT MODE	Number of Channel	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2	CH1
	Voltage	0~32V	0~32V	0~5V	0~15V	0~32V	0~32V	1.8/2.5/3.3/5.0V	0~32V	0~32V	0~32V
	Current	0~3A	0~3A	0~1A	0~1A	0~3A	0~3A	5A	0~3A	0~3A	0~6A
	Tracking Series Voltage	0~64V				0~64V			0~64V		-
Tracking Parallel Current	0~6A				0~6A			0~6A		-	
CONSTANT VOLTAGE OPERATION	Line Regulation	≤ 0.01%+3mV									
	Load Regulation	≤ 0.01%+3mV(rating current ≤ 3A); ≤ 0.02%+5mV(rating current > 3A)									
	Ripple & Noise(5Hz~1MHz)	≤ 350μVrms	≤ 1mVrms	≤ 350μVrms	≤ 2mVrms	≤ 350μVrms	≤ 500μVrms	≤ 50μs	≤ 50μs	≤ 50μs	≤ 100μs
CONSTANT CURRENT OPERATION	Line Regulation	≤ 0.2%+3mA									
	Load Regulation	≤ 0.2%+3mA									
	Ripple & Noise	≤ 2mArms				≤ 2mArms			≤ 2mArms		≤ 4mArms
PROGRAMMING RESOLUTION	Voltage	1mV				1mV	-	1mV	1mV		
	Current	0.1mA				0.1mA	-	0.1mA	0.2mA		
TRACKING OPERATION (CH1,CH2)	Tracking Error	≤ 0.1%+10mV of Master(0~32V, No Load, with Load add Load regulation ≤ 100mV)									
	Parallel Regulation	Line : ≤ 0.01%+3mV Load : ≤ 0.01%+3mV(rating current ≤ 3A); ≤ 0.02%+5mV(rating current > 3A)									
CH3 OPERATION FOR (GPP-3323)	Output Voltage	1.8V/2.5V/3.3V/5.0V, ±5%									
	Output Current	5A									
METER	Line Regulation	≤ 3mV				≤ 5mV			2mVrms(5Hz~1MHz)		100μs
	Load Regulation	≤ 5mV				2mVrms(5Hz~1MHz)			100μs		1.8V/2.5V/3.3V/5.0V, ±0.35V, 3A
	Ripple & Noise	2mVrms(5Hz~1MHz)				100μs			1.8V/2.5V/3.3V/5.0V, ±0.35V, 3A		
	Transient Recovery Time	100μs				1.8V/2.5V/3.3V/5.0V, ±0.35V, 3A					
DC LOAD CHARACTERISTIC	USB Port Output	1.8V/2.5V/3.3V/5.0V, ±0.35V, 3A									
	Voltage Resolution	0.1mV				0.1mV	-	0.1mV	0.1mV		
	Current Resolution	0.1mA				0.1mA	-	0.1mA	0.2mA		
	Setting Accuracy	≤ ±(0.03%+10mV) ≤ ±(0.30%+10mA)				≤ ±(0.03%+10mV) ≤ ±(0.30%+10mA)	-	≤ ±(0.03%+10mV) ≤ ±(0.30%+10mA)	≤ ±(0.03%+10mV) ≤ ±(0.30%+10mA)		
INSULATION	Readback Accuracy	≤ ±(0.03%+10mV) ≤ ±(0.30%+10mA)				≤ ±(0.03%+10mV) ≤ ±(0.30%+10mA)	-	≤ ±(0.03%+10mV) ≤ ±(0.30%+10mA)	≤ ±(0.03%+10mV) ≤ ±(0.30%+10mA)		
	Channel	2				2	-	2	1		
	Display Power	0~50.00W				0~50.00W	-	0~50.00W	0~100.00W		
	Display Voltage	1~33.00V				1~33.00V	-	1~33.00V	1~33.00V		
	Display Current	0~3.200A				0~3.200A	-	0~3.200A	0~6.200A		
	CV Mode Setting Range	1.500V~33.00V				1.500V~33.00V	-	1.500V~33.00V	1.500V~33.00V		
	Resolution	10mV				10mV	-	10mV	10mV		
	Set Accuracy	≤ 0.1%+30mV				≤ 0.1%+30mV	-	≤ 0.1%+30mV	≤ 0.1%+30mV		
	Read Accuracy	≤ 0.1%+30mV				≤ 0.1%+30mV	-	≤ 0.1%+30mV	≤ 0.1%+30mV		
	CC Mode Setting Range	0~3.200A				0~3.200A	-	0~3.200A	0~6.200A		
	Resolution	1mA				1mA	-	1mA	1mA		
	Set Accuracy	≤ 0.3%+10mA				≤ 0.3%+10mA	-	≤ 0.3%+10mA	≤ 0.3%+10mA		
Read Accuracy	≤ 0.3%+10mA				≤ 0.3%+10mA	-	≤ 0.3%+10mA	≤ 0.3%+10mA			
CR Mode Setting Range	1~1kΩ				1~1kΩ	-	1~1kΩ	1~1kΩ			
Resolution	1Ω				1Ω	-	1Ω	1Ω			
Set Accuracy	≤ 0.3%+1Ω(Voltage ≥ 0.1V, and current ≥ 0.1A)				≤ 0.3%+1Ω(Voltage ≥ 0.1V, and current ≥ 0.1A)	-	≤ 0.3%+1Ω(Voltage ≥ 0.1V, and current ≥ 0.1A)	≤ 0.3%+1Ω(Voltage ≥ 0.1V, and current ≥ 0.1A)			
Read Accuracy	≥ 0.1V, and current ≥ 0.1A				≥ 0.1V, and current ≥ 0.1A	-	≥ 0.1V, and current ≥ 0.1A	≥ 0.1V, and current ≥ 0.1A			
ENVIRONMENT CONDITION	Chassis and Terminal	20MΩ or above (DC 500V)									
	Chassis and AC Cord	30MΩ or above (DC 500V)									
EXTERNAL CONTROL	Operation Temp	0~40°C									
	Storage Temp	-10~70°C									
	Operating Humidity	≤ 80% RH									
INTERFACE	Storage Humidity	≤ 70% RH									
	Yes										
POWER SOURCE	Std: RS-232/USB(CDC), Opt(Manufacturer installed only): LAN/ GPIB+LAN										
DIMENSION & WEIGHT	AC100V/120V/220V/230V±10%, 50/60Hz										
	213 (W) x 145 (H) x 312 (D) mm ; Approx. 7.5kg										

Specifications subject to change without notice. GPP-SeriesGD1DH

### ORDERING INFORMATION

**GPP-1326** (32V/6A) Single-Output Programmable DC Power Supply  
**GPP-2323** (32V/3A\*2) Dual-Output Programmable DC Power Supply  
**GPP-3323** (32V/3A\*2; 1.8V or 2.5V or 3.3V or 5V/5A\*1) Three-Output Programmable DC Power Supply  
**GPP-4323** (32V/3A\*2; 5V/1A; 15V/1A) Four-Output Programmable DC Power Supply

### ACCESSORIES

User Manual x 1 , Power cord x 1  
**GPP-1326** Test Lead GTL-104A x 1, GTL-105A x 1    **GPP-2323** Test Lead GTL-104A x 2  
**GPP-4323** Test Lead GTL-104A x 2, GTL-105A x 2    **GPP-3323** Test Lead GTL-104A x 3  
 European Test Leads:  
**GPP-1326** GTL-203A x 1, GTL-204A x 1, GTL-201A x 1    **GPP-2323** GTL-204A x 2, GTL-201A x 1  
**GPP-4323** GTL-203A x 2, GTL-204A x 2, GTL-201A x 1    **GPP-3323** GTL-204A x 3, GTL-201A x 1

### OPTIONAL ACCESSORIES

**GTL-246** USB Cable  
**OPTIONS (Manufacturer Installed Only)**  
 LAN Interface; GPIB+LAN Interface

## GOOD WILL INSTRUMENT CO., LTD.

No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan  
 T +886-2-2268-0389 F +886-2-2268-0639  
 E-mail: marketing@goodwill.com.tw



[www.gwinstek.com](http://www.gwinstek.com)



[www.facebook.com/GWInstek](https://www.facebook.com/GWInstek)

# GW INSTEK

Simply Reliable