

MT-90A Wireless Interlinking Transmitter Amplifier

Key Features

- Modular design for easy installation and maintenance.
- 16 selectable channels available by push of a button.
- Numeric LED clearly indicates working channel.
- High/Low power output selectable.
- LED indicators for RF and audio signal strength.
- Supplies +48V phantom power for true condenser microphone.
- Compatible with ACT-717, ACT-727, ACT-747 & MR-90a receivers.

Related



ACT-717	Single-Channel True Diversity Receiver
ACT-727	Dual-Channel True Diversity Receiver
ACT-747	Quad-Channel True Diversity Receiver
MR-90a	Professional Portable ENG Receiver

Accessories

FB-71	Rack Mount Kit
FB-72	Rack Mount Kit

Technical Specifications

Frequency Range	UHF 620~934MHz
Bandwidth	24MHz
Oscillation Mode	PLL Synthesized
Channel Grid	25kHz
Frequency Stability	± 0.005%, -10~60
Modulation	FM
Output Power	<100mW (low), <500mW (high)
Spurious	<4nW
Frequency Response	80Hz~15kHz
T.H.D.	<0.5% (at 1kHz, Max. deviation)
Audio Input	XLR/6.3mmØ Combo jack
Input Sensitivity	Mic or Line level
Input Sensitivity Control	Adjustable control for input gain
Phantom Power Switch	ON / OFF
Panel Display	AF Meter, AF Limit, RF Hi/Low Power indicators, numeric channel.
Antenna Connector	TNCx1 (50Ω impedance)
Dimensions	210(W)× 44(H)× 206(D) mm / 8.3(W)× 1.7(H)× 8.1(D)"
Weight	Approx. 1.1kg / 2.4lbs



205 Westwood Ave, Long Branch, NJ 07740
Phone: 866-94 BOARDS (26273) / (732)-222-1511
Fax: (732)-222-7088 | E-mail: sales@touchboards.com



MIPRO Electronics Co., Ltd
Headquarters: 814 Pei-kang Road, Chiayi, 60096, Taiwan
Tel: +886.5.238.0809 | Fax: +886.5.238.0803
www.mipro.com.tw | mipro@mipro.com.tw