

# Validate Network Connectivity In Less Than 10 Seconds

## Key features include:

- Quick and simple to use
- Understand if a network connectivity issue is in the PC or the network and locate the problem if it is in the network
- Zero touch reporting automatically sends every test to Link-Live Cloud Service saving time and ensuring accuracy in reporting
- Priced to fit every IT budget as a personal tool everyone can have allowing teams to solve problems faster without the need for a shared device



LinkSprinter is a pocket-sized Ethernet tester that provides complete end-to-end network connectivity testing and automated cloud-based reporting all with the touch of a button. LinkSprinter is used by PC help desk, front line technicians, network engineers and many others, to validate network connectivity, cable, and that power is correctly being applied to PoE powered devices.

Simply connect an Ethernet cable and the LinkSprinter goes to work checking the connection path from wall jack to internet, and in less than 10 seconds, you'll know that status of the connection path through color coded LEDs.



LinkSprinter Awards

## Big Things Come In Small Packages

Don't let LinkSprinter's small stature fool you as it's packed with capability and provides several custom configuration options that can be set per tester or within Link-Live Cloud Service.

LinkSprinter runs a series of standardized tests to ensure consistency in workflow and documentation across team members regardless of skill level.

- **Power Over Ethernet (PoE)**

Check to make sure you can power a phone, security camera or Access Point through a specific port. The LinkSprinter Network Tester can even run without batteries on PoE.

- **Link to the Switch**

Perform a switch test, which indicates switch name, model, slot, port and VLAN you are connected to using CDP/LLDP/EDP. Know your available speed and duplex settings.

- **DHCP Connection**

Confirm that the DHCP server is running and responsive. Request an IP address, get your subnet information, and identify the default gateway and DNS server.

- **Gateway Connection**

Verify the gateway/router address and reachability by pinging the device.

- **Internet Connection**

Confirm cloud connectivity or internal service reachability. Verify DNS server lookup and application port connectivity.

## Quick Answers to Common Tasks

- **Moves, Adds, Changes**

Validate proper connectivity including IP subnet and VLAN so you're ready when devices arrive.

- **PoE Validation**

Ensure switch port provisioning and cabling before installing cameras, phones, or wireless access point.

- **PC Help Desk**

Is the problem in the PC or the Network? If it's the network, find out where so you can escalate with facts.

- **Gateway Connection**

Verify the gateway/router address and reachability by pinging the device.

- **Remote Site Network Connectivity Validation**

Leave one on site as an office assistant can run a test while the NOC sees the detailed result appear on the Link-Live Cloud Service dashboard.

## Link-Live Cloud Service

Once the LinkSprinter is connected to the Link-Live Cloud service, basic network connectivity test results are automatically uploaded to the dashboard for project management and reporting. This internet-hosted service is available from anywhere at any time using any device with a browser and internet connection. It is especially useful for managers of remote teams that need visibility to test results instantly. In addition, teams that utilize companions to the LinkSprinter, such as the LinkRunner AT, AirCheck G2, or OneTouch AT have a single dashboard system to manage results from network connectivity tests.

Link-Live™ Results (52)						
Search for folders, labels, or anything...						
Test	PoE	Link	Switch	DHCP	Gateway	WWW
James' Unit - 00C017-B60... 6:28 PM 9/13/2016 Colonies / Americas network-certification	<b>Volts:</b> 10 <b>Unloaded:</b> 8 <b>Loaded:</b> 2	10/100 HDx/FDx <b>RX Pair:</b> 3,6 <b>Polarity:</b> Normal	switch-sj1 <b>Model:</b> MSI on Windo... <b>Port:</b> Local Area Conn...	<b>IP:</b> 192.168.0.45	<b>IP:</b> 192.168.0.1 <b>PING (ms):</b> 1,1,1	<b>TCP:</b> www.google.com <b>Ip:</b> 0.0.0.0 <b>Time (ms):</b> 1,1,1 43
Test Unit 1 6:28 PM 9/13/2016 Americas initial-verification 41	PoE not found	10/100 HDx/FDx <b>RX Pair:</b> 3,6 <b>Polarity:</b> Normal	switch-ntct-cos-123 <b>Model:</b> MSI on Windo... <b>Port:</b> Local Area Conn...	<b>IP:</b> 192.168.0.33	<b>IP:</b> 192.168.0.1 <b>PING (ms):</b> 1,1,1	<b>TCP:</b> www.google.com <b>Ip:</b> 0.0.0.0 <b>Time (ms):</b> 1,1,1 43
Test Unit 0 6:28 PM 9/13/2016 Americas network-debugging 41	PoE not found	10/100 HDx/FDx <b>RX Pair:</b> 3,6 <b>Polarity:</b> Normal	switch-tdan6 <b>Model:</b> MSI on Windo... <b>Port:</b> Local Area Conn...	<b>IP:</b> 127.154.22.87	<b>IP:</b> 192.168.0.1 <b>PING (ms):</b> 1,1,1	<b>TCP:</b> www.google.com <b>Ip:</b> 0.0.0.0 <b>Time (ms):</b> 1,1,1 43
Michaels OneTouch d 4:27 PM 9/8/2016 xxxxxxxx 42	<b>Volts:</b> 47 <b>Unloaded:</b> 47	10/100/1000 HDx/FDx <b>RX Pair:</b> 3,6 <b>Polarity:</b> normal	Core-Switch02.dhr.com <b>Model:</b> ciscoWS-C296... <b>IP/MAC:</b> 172.31.163.10 <b>Port:</b> GigabitEthernet1...	<b>IP:</b> 192.168.1.2 <b>Server:</b> 193.211.132.1... <b>Subnet:</b> 255.255.254...	<b>IP:</b> 172.16.1.1 <b>PING (ms):</b> 2,1,2 <b>PublicIp:</b> 207.141.116...	<b>TCP:</b> www.google.com <b>Ip:</b> 172.16.200.100 <b>Time (ms):</b> 45,47,39
Michaels OneTouch d 4:27 PM 9/8/2016 xxxxxxxx 41	<b>Volts:</b> 47 <b>Unloaded:</b> 47	10/100/1000 HDx/FDx <b>RX Pair:</b> 3,6 <b>Polarity:</b> normal	Core-Switch02.dhr.com <b>Model:</b> ciscoWS-C296... <b>IP/MAC:</b> 172.31.163.10 <b>Port:</b> GigabitEthernet1...	<b>IP:</b> 192.168.1.2 <b>Server:</b> 193.211.132.1... <b>Subnet:</b> 255.255.254...	<b>IP:</b> 172.16.1.1 <b>PING (ms):</b> 2,1,2 <b>PublicIp:</b> 207.141.116...	<b>TCP:</b> www.google.com <b>Ip:</b> 172.16.200.100 <b>Time (ms):</b> 84,89,73

### Link-Live dashboard

## Technical Specifications

<b>Operating Temperature and Relative Humidity</b>	32°F to 122°F (0°C to 50°C), Relative Humidity 5% to 90% Non-condensing
<b>Storage Temperature</b>	-4°F to 140°F (-20°C to 60°C)
<b>Shock and Vibration</b>	Random 2g, 5 Hz – 500 Hz (class 2), 1m drop
<b>Safety</b>	CAN/CSA-C22.2 No. 61010-1-12, UL Std. No. 61010-1 (3rd Edition), IEC61010- 1:2010, Pollution degree 2
<b>Altitude</b>	Operating: 13,123 ft. (4,000 m) Storage: 39,370 ft. (12,000 m)
<b>EMC</b>	EN 61326-1:2006
<b>Certifications and Compliance</b>	Conforms to relevant European Union directives  Conforms to relevant Australian standards  Listed by the Canadian Standards Association  Conforms to relevant FCC standards
<b>Dimensions</b>	4.36" x 1.6" x 1.28" (11.07 cm x 4.06 cm x 3.25 cm)
<b>Weight with batteries</b>	Model 300: 0.255 lb (0.116 kg)
<b>Battery</b>	2 AA Alkaline
<b>Specification Compliance</b>	IEEE 802.11b/g
<b>Frequency Channels</b>	802.11 Channels 1 thru 11 default is 11
<b>Operating Frequency</b>	2.412 ~ 2.484 GHz, ISM Band
<b>Regulatory Domain</b>	EN 301 489-1/17
<b>Browser</b>	Internet Explorer 9.0, Firefox 3.6, Chrome 5.0, Safari 5.1 (minimum revision)

## Ordering Guide

Item Name	Description
LSPRNTR-300	Includes 1 LinkSprinter and wrist strap
LSPRNTR-300-5PK	Includes 5 LinkSprinter's at a reduced price
LSPRNTR-300-10PK	Includes 10 LinkSprinter's for the price of 9
LSPRNTR-HOLSTER	Belt attachable holster carries one LinkSprinter and includes short patch cable and business card holder
LINKSOLUTIONS-KIT	Includes 1 LinkRunner AT 2000 with standard components, 2 LinkSprinter's and 2 LinkSprinter Holsters

For a complete listing of LinkSprinter models and accessories, visit:  
**<http://enterprise.netscout.com/linkssprinter>**