



# Micro-Ohm Meters

## TESTING APPLICATIONS



Accurately measure very low contact resistances of breakers, switches, busbars, motors, generators, or any application where low resistance current is required.

## SAFETY and DESIGN FEATURES

- Microprocessor controlled
- 4-wire Kelvin measurement
- Easy to read digital screen display
- IEC safety compliant
- Separate Cable/Accessory carrying case

## MRM Series, 10-200 Amp

- Lightweight and ruggedly constructed
- Reliable and accurate measurements in the laboratory or in the field
- Printable test results via external printer or built-in printer



MODEL	MRM-10	MRM-10E	MRM-100	MRM-200
TEST CURRENT	1 mA - 10 A	1 mA - 10 A	10 A - 105 A	5 A - 200 A (True DC)
RESISTANCE RANGES	0-2000 $\mu\Omega$ @ 10 A 0-20 m $\Omega$ @ 10 A 0-200 m $\Omega$ @ 1 A 0-2000 m $\Omega$ @ 100 mA 0-20 $\Omega$ @ 10 mA 0-200 $\Omega$ @ 1 mA	0-2000 $\mu\Omega$ @ 10 A 0-20 m $\Omega$ @ 10 A 0-200 m $\Omega$ @ 1 A 0-2000 m $\Omega$ @ 100 mA 0-20 $\Omega$ @ 10 mA 0-200 $\Omega$ @ 1 mA	1 $\mu\Omega$ to 240 m $\Omega$	0.1 $\mu\Omega$ to 2 m $\Omega$ , with 0.1 $\mu\Omega$ resolution 2 m $\Omega$ to 200 m $\Omega$ , with 10 $\mu\Omega$ resolution 200 m $\Omega$ to 1 $\Omega$ , with 1 m $\Omega$ resolution
RESOLUTION	1 $\mu\Omega$ @ 10 A	0.1 $\mu\Omega$ @ 10A	1 $\mu\Omega$ to 199 $\mu\Omega$ : 0.1 $\mu\Omega$ 200 $\mu\Omega$ to 1999 $\mu\Omega$ : 1.0 $\mu\Omega$ 2.00 m $\Omega$ to 19.99 m $\Omega$ : 0.01 m $\Omega$ 20.0 m $\Omega$ to 240.0 m $\Omega$ : 0.1 m $\Omega$	up to 0.1 $\mu\Omega$
INPUT	100-240 V, 50/60 Hz	100-240 V, 50/60 Hz	120 VAC, 60 Hz or 230 VAC, 50/60 Hz, 5 A	100-240 V, 50/60 Hz
BASIC ACCURACY	$\pm$ (0.2% of reading $\pm$ 2 digits)	$\pm$ (0.1% of reading + 0.005% of full scale)	$\pm$ (1% of reading $\pm$ 0.4 $\mu\Omega$ at 100 A) or ( $\pm$ 4 $\mu\Omega$ at 10 A)	$\pm$ 0.5% of measured value
PROTECTION	n/a	n/a	Thermal	Overcurrent, short-circuit and thermal
OPERATING TEMPERATURE	-5°C to 50°C	-5°C to 50°C	-5°C to 50°C	-5°C to 50°C
STORAGE TEMPERATURE	-25°C to 65°C	-25°C to 65°C	-20°C to 57°C	-10°C to 60°C
HUMIDITY	<90%, non-condensing	<90%, non-condensing	<90%, non-condensing	<90%, non-condensing
ADVANCED FEATURES	Powered by rechargeable battery Measured value display hold function	Powered by rechargeable battery Measured value display hold function	Full Keypad—Allows easy entry of test descriptions and parameters Integrated printer	Programmable set-up test time 5-120 seconds Software w/automatic report generator, including operator's comments Built-in memory with capacity to store 50 registers with 80 readings each
DIMENSIONS				
Length	15" (378 mm)	15" (378 mm)	16.5" (419 mm)	20" (502 mm)
Width	12" (308 mm)	12" (308 mm)	15.25" (387 mm) W	15.5" (394 mm)
Height	7" (175 mm)	7" (175 mm)	11.25" (286 mm)	7.5" (190 mm)
WEIGHT	19 lbs (8.7 kgs)	17 lbs (7.6 kgs)	28 lbs (13 kgs)	45 lbs (20.5 kgs)
ACCESSORIES Included	2 Combined test leads (current and potential) 1 Charger Power cord 1 RS232 cable User guide 1 Synthetic bag for cables and instrument	2 Combined test leads (current and potential) 1 Charger Power cord 1 RS232 cable User guide 1 Synthetic bag for cables and instrument	1 Input Power cable 6' (2 m) 2 Output/Sense cables 30' (9 m) 1 Canvas bag for cables User guide	2 Combined test leads (current and potential), clamp type "C" (sargent), 49 ft (15 m) 2 Combined test leads (current and potential), alligator clip, 16 ft (5 m) 1 Ground cable 1 Power cord 1 USB Communication cable 1 Carrying case for the test leads 1 Software license User guide

High Voltage • High Current • High Power Test Systems and Components

ISO 9001  
CERTIFIED



**World Headquarters**  
Phenix Technologies, Inc.  
75 Speicher Drive  
Accident, MD 21520 USA  
Ph: +1.301.746.8118  
Fx: +1.301.895.5570  
Info@phenixtech.com

**Branch Offices**

**Phenix Systems AG**  
Riehenstrasse 62A, 4058 Basel, Switzerland  
Ph: +41.61.383.2770 • Fx: +41.61.383.2771  
Info@phenixsystems.com

**Phenix Asia**  
Zhong Cheng Rd, Sec 1, No 177, 2F, Taipei 11148 Taiwan  
Ph: +886.2.2835.9738 • Fx: +886.2.2835.9879  
Info@phenixasia.com



www.phenixtech.com