




More information on the website  
[radwag.com/en/info,w1,PES](http://radwag.com/en/info,w1,PES)

# PUE H315 Indicator



## Functions

-  Plus/Minus Control
-  Percent Weighing
-  Totalizing
-  Parts counting
-  Internal battery
-  Peak hold
-  Newton unit measurement
-  GLP Procedures
-  Animal weighing
-  ALIBI Memory

## Datasheet

Metrological parameters	
Maximum quantity of verification units	6000 e
OIML Class	III
Maximum quantity of divisions from converter	838 860 ×10
Maximum increase of signal	39 mV
Minimum volatge per verification unit	0,4 μV
Maximum voltage per verification unit	3,25 μV
Minimum load cell impedance	50 Ω

<b>Metrological parameters</b>	
Maximum load cell impedance	1200 Ω
Load cell excitation voltage	5V DC
Connection of load cells	4 or 6 wires + shield
<b>Physical parameters</b>	
Display	LCD (backlit)
Device dimensions	208×145×80 mm
Packaging dimensions	300×250×130 mm
Net weight	1,9 kg
Gross weight	2,3 kg
Protection class	IP 66 / IP 67 / IP 69
Number of buttons	5
Multiple range	1 or 2 ranges
Additional LCD display	WD-4/1 (option)
<b>Communication interface</b>	
USB Interface	1
RS232 Interface	1
Optional interfaces	RS232 or RS485 or 4IN/4OUT or Ethernet or analog output 4-20 mA
<b>Electrical parameters</b>	
Power supply	100-240 V AC 50/60 Hz
Optional power supply	internal rechargeable battery
Operation time on batteries	max 7h
<b>Environmental conditions</b>	
Operating temperature	-10 ÷ +40 °C
Storage temperature	-10 ÷ +50 °C
Relative humidity	10% ÷ 80% RH no condensation
<b>Construction</b>	
Keypad	microswitch
Housing	stainless steel



## Compatible with

Waterproof stainless steel platforms  
 Mild steel powder coated weighing platforms  
 RS 232 cables (scale - EPSON printer)  
 RS 232, RS 485 cables  
 Mild steel powder coated weighing platforms  
 Displays  
 RS 232 cables (scale - Ethernet)

Receipt Printer  
 USB adapter  
 USB cable (scale - printer)  
 Stands, wall mounting kits and mounting brackets  
 RS 232 – USB Converter  
 RS 232 – RS 485 Converter

## Software

RAD-KEY

RW Tool

## Device dimensions

