

# Titan<sup>neo</sup> Input Panel



The Input Panel provides a Lo-z XLR Microphone Input (1/4" Phone or XLR) with Mic Volume Control, Dual RCA Line Input with volume control and Dual RCA Line Output, Treble & Bass Controls, Master Volume Control. Voice Priority Circuit and Battery Level Indicator

## Specifications

Audio Input	XLR-TRS Balanced Mic
Audio Output	Line Level, Dual RCA
Controls	Master Volume, Treble, Bass Mic Vol., Line Input Vol., Voice Priority Switch
Voice Priority Control	On/Off
Attack time	<.1mS
Release time	3 seconds
Attenuation	<-26dB

## Features

Simultaneous mixing with the microphone inputs  
 Plug-In microphone Lo-z, XLR or phone plug connection  
 Treble and bass controls  
 Dual line input (RCA) with volume control  
 Dual line output (RCA)  
 Voice Priority Switch  
 4 LED battery level indicator  
 AC Operable without batteries being fully charged

## Charging Functions

Charging	LEDs Light in Sequence
Fully Charged	Only top green LED will light

## Battery Level Indication

Top LED (Green) lights:	80–100% charged
Second LED (Green) lights:	50–80% charged
Third LED (Yellow) lights:	20–50% charged
Bottom LED (Red) lights:	0–20% charged

Internal battery requires 8 – 10 hours to fully charge

# Touchboards

205 Westwood Ave, Long Branch, NJ 07740  
 Phone: 866-94 BOARDS (26273) / (732)-222-1511  
 Fax: (732)-222-7088 | E-mail: sales@touchboards.com

TeachLogic, Inc. 1688 Ord Way Oceanside, CA 92056

☎ 800-588-0018

**TeachLogic**  
 FOR SOUND LEARNING