



205 Westwood Ave, Long Branch, NJ 07740 Phone: 866-94 BOARDS (26273) / (732)-222-1511 Fax: (732)-222-7088 | E-mail: sales@touchboards.com

WiFi Configuration

I. WiFi Modes

NovoConnect supports two WiFi modes

(1) Hotspot Mode

- The NovoConnect device acts as a "wireless router"
- o Users connects their devices to this "wireless router"
- o Users do not have access to the Internet



User's Device

- (2) Client Mode
 - The NovoConnect device connects to an existing wireless network (like a school or a company's WiFi network)
 - \circ \quad Users connects their devices to the same wireless network
 - o Users have access to the Internet via this existing wireless network.



There are two ways to configure the WiFi settings

- 1. On-screen configuration
- 2. Configuration via PC/Mac software (Desktop Streamer)

The following two sections describe these two approaches in details.



II. On-Screen Configuration

- Step 1. Connect a mouse to the NovoConnect device.
- Step 2. After it boots up, use the mouse to click button "WiFi", shown below.



Step 3. To connect the NovoConnect device to an existing wireless network, select "Client Mode" and then click button "Configure". It will bring up the following WiFi configuration screen.

Select the desired WiFi network and enter the proper security key (if prompted). The wireless connection should be established in 5^{20} seconds.

Settings	ON ()
NETGEAR96 Connected	© i
phishnet Saved, secured with WPA/WPA2	s i
ess_connect Saved, secured with WPA2	<u></u>
hpsetup Saved	Ŧ
ATT712 Secured with WPA/WPA2	₹.
CP Secured with WPA2 (WPS available)	₹.
NorthMarq San Deigo WiFi Secured with WPA/WPA2	₹.
west_sd_wireless Secured with WPA2 (WPS available)	₹.

Step 4. Then, click the "Go-Back" button, , to return to the home screen for normal operation.



III. Configuration via PC/Mac Software

Step 1. Follow the on-screen instructions to download and install PC/Mac software "Desktop Streamer," as highlighted in the following figure. (You can skip this step if you have already done so.)



Step 2. Click button "Advanced..." (highlighted in the following figure) to access its advanced settings menu.

NovoConnect	ð	:≡ <mark>×</mark>				
Emily, You are connected!	Di	С sconnect				
192.168.43.1						
PIN: OFF		QR Code				
Projection Mode Vide	Video Playback					
Screen Refresh Rate Higl	า					
Visual Quality Higl	n					
Remote Mouse Disa	abled					
About Vers	Version 1.1.14184					
© Delta Electronics, Inc. All rights reserved						
	Adva	nced				



Step 3. In section "WiFi Network" (highlighted in the following figure), input the information as appropriate and then click "Apply." The NovoConnect device immediately tries to connect to the WiFi network you specify.

If it fails, it will go back to the default WiFi Hotspot mode where you can re-start this configuration process.

NovoCor	nnect		ð	:≡ <mark>*</mark>
Emily, You are conn 192.168.43. PIN:	ected! 1	OFF	Dis	Connect
Device's Sett	inas			_
WiFi Network SSID KEY	 Hots Netgear grand98 	pot 💿 -112 875	Client	Apply
Display	WXGA (1280x80	00) 🔻	Apply
Room	Meeting Room Name			Apply
Language	English	_	•	Apply
			Ca	ncel
Device's Res	et			
Quick F	Reset	F	ull Reset	
restart so Device's Upo	oftware rade	re	start device	
			Upgrade	

