

CHG 1012 / PRO

Digi-Wave™ 12-Bay Charger

This multi-unit, drop-in style charger will conveniently store and charge up to 12 Williams Sound Digi-Wave™ DLT 100 transceivers over the course of a five-hour time span. Ideal for multiple transceiver applications where flexibility is key -- including tours, conferences and event production.



CHG 1012 with DLT 100's (sold separately)



CHG 1012 PRO

Digi-Wave™ 12-Bay Charger

CHG 1012, CHG 1012 PRO Multiple Battery Charger:

Dimensions:	CHG 1012 (charger only): 9"L x 7"W x 1.6"H (23 cm L x 17.8 cm W x 4 cm H) CHG 1012 PRO (case dimensions): 18"L x 14"W x 6.75"H (47.7 cm L x 35.5 cm W x 17.1 cm H)
Weight:	CHG1012: 3.3 lbs (1.5 kg), including power supply CHG1012 PRO: 9.4 lbs (4.26 kg), including power supply
Enclosure:	CHG 1012: Black, ABS plastic with metal base
Power Supply Input:	TFP 047, 90-240 VAC input, 1.5 A max *
Power Supply:	Universal DC adapter, 5 VDC - 6A output, center positive
Charging Time:	5 hours nominal **
Unit Capacity:	12 Units
Indicators:	Charge status indicators on DLT 100
Warranty:	2 year (case, cables and power supply warranty for 90 days)
Approvals:	CE, FCC, WEEE, RoHS, CB

* **NOTE:** Eight separate CHG 1012s, each powered by its own TFP 047 power supply, can be connected to a 15-amp circuit.

** **NOTE:** Charging specifications are based on Williams Sound internal rechargeable Li-Po battery BAT 100.

Architectural/Engineering Specifications

CHG 1012/CHG 1012 PRO

The CHG 1012 shall be a 12-bay, drop-in charger for use with the Digi-Wave™ DLT 100. It shall be enclosed in black ABS plastic, 9" x 7" x 1.6" and weigh 2.0 lbs excluding power supply.

The CHG 1012 shall have a five-hour nominal charge cycle. Battery status and charge indication are provided on the DLT 100.

The charger shall be powered by an external universal power supply (90-240 VAC input; 5 VDC, 6A output) via a DC barrel connector.

Eight separate CHG 1012s, each powered by its own TFP 047 power supply, can be connected to a 15amp circuit.

The charger shall have CE approval and be RoHS, WEEE, Industry Canada, FCC and CB scheme compliant.

This charger shall be the Williams Sound model CHG 1012.

The CHG 1012 PRO shall be housed in a carry case.

Domestic Sales

Williams Sound
10300 Valley View Rd.
Eden Prairie, MN 55344
Ph: 800-328-6190 / 952-943-2252
FAX: 952-943-2174
Email: info@williamssound.com
Web: www.williamssound.com

International Sales

International Sales Department
Williams Sound
10300 Valley View Rd.
Eden Prairie, MN 55344 USA
Phone: +1 952 943 2252
Fax: +1 952 943 2174
Email: info@williamssound.com
Web: www.williamssound.com



WILLIAMS SOUND®
HELPING PEOPLE HEAR

800.843.3544 / info@williamssound.com / www.williamssound.com