

Botron B2000 Technical Data Sheet



Features:

Botron's B2000 Auto Feed Carousel Tape Dispenser automatically cuts the tape and places it on a rotating carousel for easy use. When you need multiple pieces of tape at your fingertips this unit will do just that. Hold's up to 10 pre-cut pieces on the carousel.

Product Notes and Features

- Easy Length Adjustment
- Steel Blades
- Top Touch Start Button
- Photocell Control

PROPERTIES

SPECIFICATIONS

Cutting Length:	11mm - 58mm
Tape Width:	3mm - 22mm
Core & Roll Size	
Internal Diameter :	1", 1.25" & 3"
Outside Diameter:	Up to 6"
Max Outside Diameter:	6.7"
Optional:	Extension Stand
Power Repurement	
V:	AC 100V, 120V, 220-240V
Hz:	50/60Hz
W:	160W
Dimensions:	11.8" x 6.5" x 6.7"
Weight:	6.4lbs

PART NUMBERS

B2000 Automatic Carousel Tape Dispenser



BEFORE YOU START

1. When loading the tape, make sure the ON/OFF switch is in the OFF position.
2. While operating the B2000 make sure the safety guard is down. The blades are very sharp, do not attempt to work on the machine without the guard in place.
3. When there are finger marks, oils and/or dirt on the carousel, the tape will not stick properly. Use a dry cloth to clean.
Note: For more thorough cleaning, wipe the carousel with alcohol. (Never clean with thinner.)
4. To avoid shortening the life of the motor, run the B2000 without tape as little as possible.
5. This is an industrial tape dispenser. It is not for home use. Do not use around children.
6. The B2000 can be used efficiently by one or two operators. Allow the motor to rest from time to time.

OPERATION

1. Turn power switch to "ON" position.
2. Load preferred tape onto spool.
3. Close safety guard.
4. Adjust width and length.
5. Press button on top of carousel to start.
6. Remove all tape before pushing button again.
7. If desired width and length are off, readjust and press button again.

Botron Company Inc. | 325 W. Melinda Ln Phoenix AZ 85027 | Ph# 623-582-6700 | Fax# 623-582-6776

Disclaimer. All statements of technical information are believed to be true and are based upon tests we believe to be reliable. The proper use and application for this product must be the responsibility of the user.

The statements herein shall have no force or effect.