

# Keysight E9304A Option H20

## Product Note

The Keysight E9304A Option H20 modifies the standard E9304A power sensor by extending the upper frequency range to 18 GHz. This product note documents the signal characteristic for this option.

### NOTE

For information concerning the operation and connections, refer to the E9304A Power Sensors Operating and Service Guide.

---

# Specifications

## NOTE

- Specifications describe the performance of parameters covered by the product warranty (temperature: 0°C to 55°C, unless otherwise noted.)
- Typical describes additional product performance information that is not covered by the product warranty. It is performance beyond specification that 80% of the units exhibit with a 95% confidence level over the temperature range 20°C to 30 °C. Typical performance does not include measurement uncertainty.
- Nominal values indicate expected performance or describe product performance that is useful in the application of the product, but is not covered by the product warranty.

All specifications for the E9304A Option H20 are identical to E9304A with the following exceptions:

**Table 1-1** Frequency Range and Connector Type

Frequency Range	Connector	Power Range
9 kHz to 18 GHz	3.5 mm (male)	10 nW to 1 W (-60 dBm to +20 dBm)

**Table 1-2** Maximum SWR (25°C ± 10°C)

Frequency	SWR
9 kHz to < 2 GHz	1.13
2 GHz to < 14 GHz	1.19
14 GHz to < 16 GHz	1.22
16 GHz to 18 GHz	1.26

**Table 1-3** Maximum SWR (0°C to +55°C)

Frequency	SWR
9 kHz to < 2 GHz	1.15
2 GHz to < 14 GHz	1.20
14 GHz to < 16 GHz	1.23
16 GHz to 18 GHz	1.27

Max DC Volts: 10 Volts

**NOTE**

Maximum Calibration Factor uncertainties are shown in the following tables. The calibration report that is shipped with each power sensor indicates the Cal Factor uncertainty data for that specific sensor as measured at the factory. Refer to the E9304A Power Sensors Operating and Service Guide for more information about Calibration Factor and Reflection Coefficient data.

**Table 1-4** Cal Factor Uncertainty (Low Power Path, -60 dBm to -10 dBm)

Frequency	Uncertainty (25°C ±10°C)	Uncertainty (0°C to +55°C)
9 kHz to < 6 GHz	1.7%	2.0%
6 GHz to < 14 GHz	1.8%	2.0%
14 GHz to 18 GHz	2.3%	2.5%

**Table 1-5** Cal Factor Uncertainty (High Power Path, -10 dBm to +20 dBm)

Frequency	Uncertainty (25°C ±10°C)	Uncertainty (0°C to +55°C)
9 kHz to < 500 MHz	2.0%	3.4%
500 MHz to < 1.2 GHz	2.2%	3.4%
1.2 GHz to < 6 GHz	1.8%	2.1%
6 GHz to < 14 GHz	1.9%	2.3%
14 GHz to 18 GHz	2.5%	3.5%

The Keysight E9304A Option H20 has no field serviceable parts. If you need service or calibration for your power sensor, you must return it to Keysight Technologies.

Inspect the shipping container. If the container or packing material is damaged, it should be kept until the contents of the shipment have been checked mechanically and electrically. If there is mechanical damage or if the instrument does not pass the performance tests, notify the nearest Keysight Technologies office. Keep the damaged shipping materials (if any) for inspection by the carrier and a Keysight Technologies representative.

To contact Keysight for sales and technical support, refer to Keysight worldwide website at: [www.keysight.com/find/assist](http://www.keysight.com/find/assist).



This information is subject to change without notice.

© Keysight Technologies 2007-2020  
Edition 2, November 25, 2020

Printed in Malaysia



E9304-90003

[www.keysight.com](http://www.keysight.com)