

## Spesifikasjoner for Parasound Zonemaster 2350

- Power Output
- RMS, Both Channels Driven (20 Hz – 20 kHz)
- 350 watts x 2 @ 8  $\Omega$
- 600 watts x 2 @ 4  $\Omega$  or 2  $\Omega$
- Minimum Speaker Impedance (Output A+B)
- Stereo or Mono Mode: 2  $\Omega$
- Subwoofer Mode: 4  $\Omega$
- Note: Operation at these minimum impedances might require additional ventilation.
- Frequency Response
- 10 Hz – 70 kHz, +0/-3 dB
- 20 Hz – 20 kHz, +0/-0.8 dB
- Total Harmonic Distortion
- < 0.05 % at typical listening levels
- < 0.9 % at full power Inter-channel Crosstalk 70 dB at 20 kHz Input Sensitivity: 2 Volts = Full output (350 Watts @ 8  $\Omega$ ) Total gain = 29 dB (Level controls set to Maximum) S/N Ratio > 100 dB, input shorted, unweighted
- > 114 dB, input shorted, IHF A-weighted
- High and Low Pass Crossovers
- Sub Mode and Sub out jack: 80 Hz, 24 dB per octave
- High Pass Filter: 30 Hz or 80 Hz, 12 dB per octave
- DC Trigger Requirements
- +9 Vdc to +12 Vdc, 5 mA
- Audio Trigger Requirements
- 2 mV audio signal (8-15 minutes turn off delay)
- AC Power Requirement
- 1500 Watts maximum
- 100 Watts typical (music playing, typical listening level)
- 30 Watts idle (no music playing)
- 0.5 Watts in standby
- 110-240 VAC 50/60 Hz
- Dimensions
- Width: 17.25" (438 mm)
- Depth: 14.5" (368 mm)

- Depth: 16.25" (412 mm) with cables connected
- Height, with feet: 4.25" (108 mm)
- Height, without feet: 3.5" (89 mm), 2U
- Weight
- Net: 15 lbs. (6.8 kg)
- Shipping: 22.25 lbs. (10.1 kg)