




Shunt release for NZM2/3, configurable relays, 2NO, 110-130AC, Push-in terminals

Part no. NZM2/3-XA2A110-130AC
Catalog No. 189742

Similar to illustration

Delivery program

| | | |
|--------------------|--|---|
| Product range | | Accessories |
| Accessories | | Shunt release |
| Accessories | | Shunt release with two relays |
| Standard/Approval | | UL/CSA, IEC |
| Construction size | | NZM2/3 |
| Description | | <p>The breakers are actuated by a voltage pulse or by applying a no-break current. For signaling commands or different states of the circuit-breaker. Two relays per unit.</p> <p>The activation criteria can be configured in the trip unit. Configuration via communication or circuit breaker display or front USB port and Eaton Power Xpert Protection Manager.</p> <p>If the shunt trip is live, contact with the circuit breaker's primary contacts is prevented when switched on.</p> <p>Only for use in combination with circuit-breakers with electronic trips. Shunt trip relay modules cannot be installed simultaneously with make-before-break auxiliary contact NZM...-XHIV, under-voltage trip NZM...-XU... or shunt trip NZM...-XA.</p> <p>Relay coil is controlled by trip unit.</p> <p>Relay contacts for control wiring.</p> <p>Relays can be used for controlling remote operator with $U_s=208-204$ V AC. Control wiring on push-in clamps.</p> <p>Cannot be used with the PXR10 NZM-AX electronic trip.</p> |
| Connection type | | with push in terminal |
| Auxiliary contacts | | without auxiliary contact |
| For use with | | PXR20(25) NZM2(-4)-.X... PXR20(25) NZM3(-4)-.X... |
| Number of relays | | 2 |
| Contact sequence | |  |

Technical data

Shunt release

| Rated control voltage | U_s | V | |
|--|---------|-----------------|-------------------|
| AC | U_s | V AC | 110 - 130 |
| Operating range | | | |
| AC | $x U_s$ | | 0.7 - 1.1 |
| DC | $x U_s$ | | 0.7 - 1.1 |
| Power consumption | | | |
| Pick-up AC/DC | | VA/W | 2.5 |
| Power consumption Pick-up = Sealing | | VA/W | 2.5 |
| Maximum opening delay (response time until opening of the main contacts) | | ms | Approx. 20 |
| Maximum duty factor | | ms | ∞ |
| Minimum command time | | ms | Approx. 10 ... 15 |
| Terminal capacity | | | |
| Solid | | mm ² | 1 x (0.2 – 1.5) |

| | | | |
|---|------------------|-------------------|-------------------|
| Stranded | | mm ² | 1 x (0.25 – 1.5) |
| | | AWG | 1 x (24 - 16) |
| with insulated end sleeve in accordance with DIN46224 / 4 | | mm ² | 1 x (0,25 - 1,5) |
| with uninsulated end sleeve in accordance with DIN46228 / 1 | | mm ² | 1 x (0,25 - 0,75) |
| Relay contacts | | | |
| Rated control voltage | U _s | V | |
| AC | U _s | V AC | 24 - 240 |
| DC | U _s | V DC | 24 - 24 |
| Contacts | | | |
| Rated impulse withstand voltage | U _{imp} | V AC | 4000 |
| Rated insulation voltage | U _i | V | 250 |
| Overvoltage category/pollution degree | | | II/2 |
| Switching capacity | | | |
| Rated operational current | | kA _{rms} | |
| AC-1 | | | |
| 24 V | I _e | A | 1 |
| 110 V | I _e | A | 1 |
| 230 V | I _e | A | 1 |
| DC-1 | | | |
| 24 V | I _e | A | 1 |
| Min. switching capacity (reference value) | | | 0.1 mA / 0.1 VDC |
| Connection | | | |
| Stripping length | | mm | 8 |
| Terminal capacity | | | |
| Solid | | mm ² | 1 x (0.2 – 1.5) |
| Stranded | | mm ² | 1 x (0.25 – 1.5) |
| | | AWG | 1 x (24 - 16) |
| with insulated end sleeve in accordance with DIN46224 / 4 | | mm ² | 1 x (0,25 - 1,5) |
| with uninsulated end sleeve in accordance with DIN46228 / 1 | | mm ² | 1 x (0,25 - 0,75) |

Design verification as per IEC/EN 61439

| | | |
|--|--|--|
| IEC/EN 61439 design verification | | |
| 10.2 Strength of materials and parts | | |
| 10.2.2 Corrosion resistance | | Meets the product standard's requirements. |
| 10.2.3.1 Verification of thermal stability of enclosures | | Meets the product standard's requirements. |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat | | Meets the product standard's requirements. |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects | | Meets the product standard's requirements. |
| 10.2.4 Resistance to ultra-violet (UV) radiation | | Meets the product standard's requirements. |
| 10.2.5 Lifting | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 Mechanical impact | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 Inscriptions | | Meets the product standard's requirements. |
| 10.3 Degree of protection of ASSEMBLIES | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 Clearances and creepage distances | | Meets the product standard's requirements. |
| 10.5 Protection against electric shock | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 Incorporation of switching devices and components | | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 Internal electrical circuits and connections | | Is the panel builder's responsibility. |
| 10.8 Connections for external conductors | | Is the panel builder's responsibility. |
| 10.9 Insulation properties | | |
| 10.9.2 Power-frequency electric strength | | Is the panel builder's responsibility. |
| 10.9.3 Impulse withstand voltage | | Is the panel builder's responsibility. |
| 10.9.4 Testing of enclosures made of insulating material | | Is the panel builder's responsibility. |
| 10.10 Temperature rise | | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |

| | | | |
|-------------------------------------|--|--|--|
| 10.11 Short-circuit rating | | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.12 Electromagnetic compatibility | | | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 Mechanical function | | | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |

Technical data ETIM 7.0

| | | | |
|---|--|---|-------------------------|
| Low-voltage industrial components (EG000017) / Shunt release (for power circuit breaker) (EC001023) | | | |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Full load current trip (ecl@ss10.0.1-27-37-04-18 [AKF016013]) | | | |
| Rated control supply voltage Us at AC 50HZ | | V | 110 - 130 |
| Rated control supply voltage Us at AC 60HZ | | V | 110 - 130 |
| Rated control supply voltage Us at DC | | V | 0 - 0 |
| Voltage type for actuating | | | AC |
| Initial value of the undelayed short-circuit release - setting range | | A | 0 |
| End value adjustment range undelayed short-circuit release | | A | 0 |
| Type of electric connection | | | Spring clamp connection |
| Number of contacts as normally open contact | | | 2 |
| Number of contacts as normally closed contact | | | 0 |
| Number of contacts as change-over contact | | | 0 |
| Suitable for power circuit breaker | | | Yes |
| Suitable for off-load switch | | | Yes |
| Suitable for motor safety switch | | | Yes |
| Suitable for overload relay | | | No |

Approvals

| | | | |
|-----------------------------|--|--|---|
| Product Standards | | | UL489; CSA-C22.2 No. 5-09; IEC60947, CE marking |
| UL File No. | | | E140305 |
| UL Category Control No. | | | DIHS |
| CSA File No. | | | 022086 |
| CSA Class No. | | | 1437-01 |
| North America Certification | | | UL listed, CSA certified |