

PRODUCT-DETAILS

PSTX470-600-70

PSTX470-600-70 Softstarter - 470 A - 208 ... 600 V AC



Informations générales

Alias commercial mondial	PSTX470-600-70
Extension du type de produit	PSTX470-600-70
Code de produit	1SFA898116R7000
ABB désignation de type	PSTX470-600-70
EAN	7320500508954
Description courte	PSTX470-600-70 Softstarter - 470 A - 208 ... 600 V AC

Description longue	<p>The softstarter PSTX470-600-70 has a rated maximum operational current of 470 A with an operating voltage span from 208...600 V AC. The rated control voltage is between 100...250 V AC at 50/60 Hz. PSTX features a three-phase control soft start and stop through a voltage or a torque ramp. It has built-in bypass for easy installation and energy saving. A RUN, TOR and Event signal is available from relay outputs in NO (normally open state). The PSTX has functions such as current limit, kickstart, analog output, EOL, motor heating and pump cleaning. PSTX also features features jog, braking, stand-still brake, diagnostics, sequence start and emergency/fire pump mode as standard. To interact with PSTX, it has a detachable full graphic display with IP66 and 4x outdoor rating. There are four ways to communicate with PSTX. It can be done by hardwire inputs Start/Stop/Reset of fault, and by three programmable digital inputs. Another popular option is the built-in Fieldbus communication Modbus RTU and incl optional ANYBUS modules with every major protocol such as for example Profinet, Profibus, Modbus TCP, Ethernet IP and others. Another way to communicate with PSTX is to use an external adaptor and a Fieldbus plug. PSTX is the complete alternative for any motor starting application. It's suitable for medium to large-sized three-phase motors with nominal currents from 30...1250 A inline connection or 52...2160 A inside delta connection. Typical applications are, for example, pumps, fans, compressors, and conveyors.</p>
--------------------	--

Commande

Quantité minimum	1 pièce
Code douanier	85371091

Downloads Préférés

Fiche produit, informations techniques	1SFC132012C0201
Instructions et manuels	1SFC132081M0201
CAD Dimensional Drawing	2CDC001079B0201
Wiring Diagram	N/A

Dimensions

Produit Largeur Net	361 mm
Produit Hauteur Net	493 mm
Produit Longueur Net	282 mm
Poids net	25 kg

Technique

Tension	208 ... 600 V AC
Rated Control Supply Voltage (U_s)	100 ... 250 V AC
Rated Control Circuit Voltage (U_c)	24 V DC
Fréquence assignée (f)	50/60 Hz Circuit principal 50 / 60 Hz
Rated Operational Power - In-Line Connection (P_e)	(230 V) 132 kW (400 V) 250 kW (500 V) 315 kW
Courant nominal de fonctionnement-- Raccordement en ligne (I_e)	470 A
Rated Operational Power - Inside Delta Connection	at 230 V 250 kW at 400 V 450 kW at 500 V 600 kW
Rated Operational Current - Inside Delta Connection	814 A
Pourcentage Facteur de service	100 %
Overload Protection	Built-in electronic overload protection
Integrated Electronic Overload	Yes
Adjustable Rated Motor Current I_e	30 ... 100 %
Starting Capacity at Maximum Rated Current I_e	4x I_e for 10s
Ramp Time	1 ... 120 second [unit of time]
Initial Voltage During Start	10 ... 99 %
Step Down Voltage Special Ramp	100 ... 10 %
Switch for Inside Delta Connection	Oui
Run Signal Relay	Oui
By-pass Signal Relay	Yes

Fault Signal Relay	Yes
Overload Signal Relay	Oui
Signal Indication Ready to Start/Standby ON (LED)	Green
Voyant de signal indiquant R (LED)	Green
Signal Indication Protection (LED)	Yellow
Signal Indication Fault (LED)	Red
Communication	Modbus-RTU; Modbus-TCP; Ethernet-IP; EtherCAT; DeviceNet; CANopen; Profibus; Profinet; BACnet-IP; BACnet-MSTP
Indice de protection	IP00
Type de borne	Main Circuit: Bars
Connecting Capacity Main Circuit	Hole Diameter 8.5 mm
Connecting Capacity Control Circuit	Rigid 1 x 2.5 mm ²
Connecting Capacity Supply Circuit	Rigid 1 x 2.5 mm ²
Couple de serrage	Main Circuit 35 N·m
Groupe de produit	PSTX470
Fonction	<ul style="list-style-type: none"> Auto phase sequence detection Automatic restart Current limit Current limit ramp Dual current limit Dynamic brake Electricity metering Electronic overload Time-to-cool Emergency mode Event log Full voltage start Jog with slow speed, forward and reverse Keypad password Kick start Limp mode with two-phase motor control if one set of thyristors is shorted Motor heating Pre-start function Pump cleaning Real time clock Sequence start Soft start with torque control Soft start with voltage ramp Soft stop with torque control Soft stop with voltage ramp Stand still brake Start reverse (external contactors) Thyristor runtime measurement Torque limit Voltage sags detection
Protection Function	<ul style="list-style-type: none"> Bypass open protection; Current imbalance protection; Current underload protection; Dual overload (separate overload for start and run); Earth fault protection / ground fault protection; Electronic overload protection, EOL; Extension IO failure protection; Fieldbus failure protection; HMI failure protection; Locked rotor protection; Max number of starts/hour; Over voltage protection; Phase reversal protection; Power factor underload protection; PT-100 connection; PTC connection; Too long current limit protection; Too long start time protection; Under voltage protection; User defined protection; Voltage imbalance protection
Warning Details	<ul style="list-style-type: none"> Current imbalance warning; Current underload warning; Electronic overload Time-to-trip; EOL warning; Faulty fan warning; Locked rotor warning; Motor runtime limit warning; Over voltage warning; Phase loss warning (for standby); Power factor underload warning; Short circuit warning (for Limp mode); THD(U) - Total Harmonic Distortion warning; Thyristor overload warning (SCR); Under voltage warning; Voltage imbalance warning

Technique UL/CSA

Maximum Operating

Circuit principal 600 V

Voltage UL/CSA

Tightening Torque
UL/CSA

Main Circuit 309.8

Environnement

Température de l'air
ambiantOperation -25 ... +60 °C
Storage -40 ... +70 °C

Indice de protection

IP00

Informations RoHS

2CMT005210

Statut RoHS

Following EU Directive 2002/95/EC August 18, 2005 and amendment

Certificats et Déclarations (Numéro de document)

CQC Certificate

CN: CQC2015010304806588 / SE: CQC2015010304797766

Declaration of Conformity
- CCC

CN: 2020980304001094 / SE: 2020980304001859

Déclaration de Conformité
- CE

2CMT005209

Emballage

Emballage Niveau 1
Largeur

470 mm

Emballage Niveau 1
Longueur

381 mm

Emballage Niveau 1
Hauteur

650 mm

Emballage Niveau 1 Poids

29 kg

Emballage Niveau 1 EAN

7320500508954

Emballage Niveau 1
Unités

box 1 pièce

Classifications

Code de classification
d'objet

Q

ETIM 7

EC000640 - Soft starter

ETIM 8

EC000640 - Soft starter

ETIM 9

EC000640 - Soft starter

eClass

V11.0 : 27370907

UNSPSC

39121521

Code de catégorie
granulaire IDEA (IGCC)

4740 >> Soft starter

Accessories

Identifier	Description	Type	Quantity	Unit Of Measure
1SDA013922R1	KIT FC CuAl 2x240mm2 T6 630-S6 630 6pcs	KIT FC CuAl 2x240mm2 T6 630-S6 630 6pcs	1	piece
1SDA013956R1	KIT FC CuAl 3x185mm2 T6 800-S6 800 6pcs	KIT FC CuAl 3x185mm2 T6 800-S6 800 6pcs	1	piece
1SDA054988R1	KIT FC CuAl 1x185mm2 T4 3pcs	KIT FC CuAl 1x185mm2 T4 3pcs	1	piece
1SDA055020R1	KIT FC CuAl 1x240mm2 T5 400 3pcs	KIT FC CuAl 1x240mm2 T5 400 3pcs	1	piece
1SDA023380R1	KIT FC CuAl 2x240mm2 T6 630-S6 630 3pcs	KIT FC CuAl 2x240mm2 T6 630-S6 630 3pcs	1	piece
1SFN074810R1000	LX205 Terminal Extension	LX205	1	piece
1SFN075410R1000	LX370 Terminal Extension	LX370	1	piece
1SFN075710R1000	LX460 Terminal Extension	LX460	1	piece
1SFN074307R1000	LW110 Terminal Enlargement	LW110	1	piece
1SFN074807R1000	LW205 Terminal Enlargement	LW205	1	piece
1SFN075407R1000	LW370 Terminal Extension	LW370	1	piece
1SFN075707R1000	LW460 Terminal Enlargement	LW460	1	piece
1SFN076107R1000	LW750 Terminal Enlargement	LW750	1	piece
1SFN124801R1000	LT205-30C Terminal Shroud	LT205-30C	1	piece
1SFN124803R1000	LT205-30L Terminal Shroud	LT205-30L	1	piece
1SFN125401R1000	LT370-30C Terminal Shroud	LT370-30C	1	piece
1SFN125403R1000	LT370-30L Terminal Shroud	LT370-30L	1	piece
1SFN125406R1000	LT370-30D Terminal Shroud	LT370-30D	1	piece
1SFN125701R1000	LT460-AC Terminal shroud	LT460-AC	1	piece
1SFN125703R1000	LT460-AL Terminal shroud	LT460-AL	1	piece
1SFN126101R1000	LT750-AC Terminal shroud	LT750-AC	1	piece
1SFN126103R1000	LT750-AL Terminal shroud	LT750-AL	1	piece
1SFA899314R1001	PSCA-1 USB cable	PSCA-1	1	piece
1SFA899300R1001	AB-PROFIBUS-1 Communication Module	AB-PROFIBUS -1	1	piece
1SFA899300R1002	AB-DEVICENET-1 Communication Module	AB- DEVICENET-1	1	piece
1SFA899300R1003	AB-MODBUS-RTU-1 Communication Module	AB-MODBUS- RTU-1	1	piece
1SFA899300R1006	AB-ETHERNET-IP-2 Communication Module	AB- ETHERNET-IP -2	1	piece
1SFA899300R1008	AB-MODBUS-TCP-2 Communication Module	AB-MODBUS- TCP-2	1	piece
1SFA899300R1010	AB-PROFINET-IO-2 Communication Module	AB-PROFINET -IO-2	1	piece
1SFA899300R1011	AB-BACNET-MSTP-1 Communication Module	AB-BACNET- MSTP-1	1	piece
1SFA899300R1012	AB-ETHERCAT-IP-2 Communication Module	AB- ETHERCAT-IP -2	1	piece
1SAJ611000R0101	DX111-FBP.0 IO-Module for UMC100 DI 24 VDC, supply 24VDC	DX111-FBP.0	1	piece
1SAJ622000R0101	DX122-FBP.0 IO-Module for UMC100 DI 110/230VAC, supply 24VDC	DX122-FBP.0	1	piece
1SFA896312R1002	PS-FBPA Fieldbus plug kit	PS-FBPA	1	piece

Catégories

Produits basse tension → Produits de Contrôle, Protection et sécurité machines → Démarreurs progressifs → Démarreurs progressifs → PSTX Softstarters → PSTX470

Variateurs de vitesse → Démarreurs progressifs → Démarreurs progressifs → PSTX Softstarters → PSTX470

