## GX1656U12



ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 16A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING

Product designation				Rotary cam switches
Product type designation	on			GX16
General characteristics				
Switching diagram				56 - Changeover switch without 0 3 poles
N° of elements				3
Mounting form				U12 - Front mounting without front plate with key operation for hole diam. 22mm fixing
Rated insulation voltage				
Rated impulse withstar		IEC/EN UL/CSA	V V kV	690 600 6
Conventional free air th	<b>°</b>		ΓV	0
		IEC/EN UL/CSA	A A	16 12
Rated operational volta	lge		V	440
Rated operational impu	Ilse voltage		kV	4
Maximum fuse size for	short-circuit protection In (gG)			
		10kA	A	16
		15kA	A	16
		25kA	A	16
Rated short time currer	nt ICW	1s	А	250
Conductivity		13	Λ	10/5 mA/V
Operational current le l	IEC/EN			
	AC1/AC21A		A	16
	AC15			
		110V	А	10
		220/230V	А	8
		380/400V	А	4
		660/690V	A	1.5
Rated operational power				
	Three-phase AC-3	000/0001/	1.147	0 5
		220/230V	kW	3.5
		380/440V 500/690V	kW kW	4.5 5.5
	Single-phase AC-3	500/690V	ĸvv	5.5
	onigie-phase AC-3	110V	kW	0.55
		220/230V	kW	1.5
		380/440V	kW	2.2
	Three-phase AC23A			
		220/230V	kW	3.7
		380/440V	kW	6.5
		500/690V	kW	7.5
	Single-phase AC23A			
		110V	kW	0.75

GX1656U12

The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding



GX1656U12 electric ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 16A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING

		220/230V	kW	1.8
		380/440V	kW	3
Rated operational cu				
	DC21A	40)/	•	10
		48V	A	16
		60V	A	16
		110V	A	4
		220V	А	0.6
		440V	A	0.25
	DC23A (poles in series)	<b>•</b> 414		
		24V	A	16 (1)
		48V	A	16 (2)
		60V	А	16 (3)
		110V	А	10 (3)
		220V	A	7 (4)
	DC13		-	
		24V	А	16
		48V	А	14
		60V	А	10
		110V	А	1
		220V	А	0.4
		440V	А	0.15
Power dissipation			W	0.6
Mechanical features				
Terminals screw				3M
Tightening torque for	terminals max		Nm	0.5
Conductor size				
	AWG - Rigid cable			
		min	AWG	20
		Max	AWG	12
	AWG - Flexible cable			
		min	AWG	20
		Max	AWG	12
	Conductor size (IEC) - Flexible cable			
		min	mm²	0.5
		Max	mm²	2.5
	Conductor size (IEC) - Rigid cable			
		min	mm²	0.5
		Max	mm²	2.5
Mechanical life			cycles	1X10 <sup>6</sup>
UL technical data			-	
Motor power for direc	t-on-line control			
	for three-phase motor			
		120V	HP	1.5
		240V	HP	3
		480V	HP	5
		600V	HP	5
	for single-phase motor			
		120V	HP	0.75
		240V	HP	1
Ambient conditions		2101		
Temperature				
	Operating temperature			
		min	°C	-25

GX1656U12

The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding



GX1656U12 ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 16A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING


	max	°C	+55	
Storage temperature				
	min	°C	-40	
	max	°C	+70	
Resistance & Protection				
Frontal IP degree			IP65	
Terminals IP degree			IP20	
Dimensions				

Dimensions 1-5 R1,6 228 22,5 E B 30

Cariaa	L				
Series	1	2	3.	8	
GX16	54	62.5	71	113.4	
GX20	54	62.5	71	113.4	

L

## Wiring diagrams



## Certifications and compliance

Compliance		
	CSA C22.2 n° 14	
	IEC/EN/BS 60947-1	
	IEC/EN/BS 60947-3	
	IEC/EN/BS 60947-5-1	
	IEC/EN/BS 61058-1	
	UL60947-4-1	
Certificates		
	cULus	
	EAC	
ETIM classification		
ETIM 8.0		EC001029 - Selector switch, complete

GX1656U12

The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding