DATASHEET - J32/B

Main switch, 32 A, surface mounting, 3 pole, STOP function, With black rotary handle and locking ring, Lockable in the 0 (Off) position



Part no. J32/B 199547

Product name	Eaton J-Range enclosed switch-disconnector
Part no.	J32/B
EAN	5027590552042
Product Length/Depth	115 millimetre
Product height	180 millimetre
Product width	100 millimetre
Product weight	0.447 kilogram
Certifications	VDE 0660 IEC/EN 60204 IEC/EN 60947 IEC/EN 60947-3
Product Tradename	J-Range
Product Type	Enclosed switch-disconnector
Product Sub Type	None
Catalog Notes	Rated Short-time Withstand Current (Icw) for a time of 1 second
Features Fitted with:	Version as main switch Version as maintenance-/service switch Push-through cable entry diaphragm Black rotary handle and locking ring Assembly sheet screen
Functions	Interlockable STOP function
Locking facility	Lockable in the 0 (Off) position
Number of poles	Three-pole
Degree of protection	NEMA 12
Degree of protection (front side)	IP65
Lifespan, mechanical	300,000 Operations
Mounting method	Surface mounting
Mounting position	As required
Operating frequency	1200 Operations/h
Overvoltage category	III
Pollution degree	3
Product Category	Main switch
Rated impulse withstand voltage (Uimp)	6000 V AC
Safe isolation	440 V AC, Between the contacts, According to EN 61140
Safety parameter (EN ISO 13849-1)	B10d values as per EN ISO 13849-1, table C.1
Shock resistance	15 g, Mechanical, According to IEC/EN 60068-2-27, Half-sinusoidal shock 20 ms
Suitable for	Ground mounting
Ambient operating temperature (enclosed) - min	-25 °C
Ambient operating temperature (enclosed) - max	40 °C
Climatic proofing	Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Terminal capacity	1 x (1.5 - 10) mm ² , solid or stranded 2 x (1 - 4) mm ² , flexible with ferrules to DIN 46228 2 x (1.5 - 6) mm ² , solid or stranded 1 x (1 - 4) mm ² , flexible with ferrules to DIN 46228
Screw size	M4, Terminal screw
Tightening torque	1.6 Nm, Screw terminals

Band insing quadry 12/2014 (hosp bin 16 (1989-3)90ABand braining quadry 24/2014 (hosp bin 16 (1989-3)90ABand braining quadry 24/2014 (hosp bin 16 (1989-3)90ABand denotation quadry 24/2014 (hosp bin 16 (1989-3)90ABand genotation quadry 16 and 21-19090ABand quadry 16 and 21-19090A <t< th=""><th></th><th></th></t<>		
Red brasing capety at 800 Vices phi b IEC 6097.3 PA Red special arrit (1) at 62.1 keb straik with a 1/r = 1 m PA Red special arrit (1) at 62.1 keb straik with a 1/r = 1 m PA Red special arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red special arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red special arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red special arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red special arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red special arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Red arrit (1) at 62.2 keb straik with a 1/r = 1 m PA Name or a walkey catacts (1 ken ge straik with a 1/r = 1 m PA Name or a walkey catacts (1 ken ge straik with a 1/r = 1 m PA Name or a walkey catacts (1 ken ge straik with a 1/r = 1 m PA Name or a walkey catacts (1 ken ge straik with a 1/r = 1 m PA Natter or a walkey catacts (1 ken ge straik with a	Rated breaking capacity at 220/230 V (cos phi to IEC 60947-3)	260 A
Anter breaking capacity at 68989 V(csp plis 1825 6897-3) PA Ried contractal current (b) at 2-1, 40-V as a witch set (b = 1 ms) PA Ried contractal current (b) at 2-1, 40-V as a witch set (b = 1 ms) PA Ried contractal current (b) at 2-1, 40-V as a witch set (b = 1 ms) PA Ried contractal current (b) at 2-1, 40-V as a witch set (b = 1 ms) PA Ried contractal vick (b) (b) (b) (b) PA Ried contractal vick (b) PA Number of alaxing vick (b) PA Ried contractal vick (b) PA Ried vick (b) PA	Rated breaking capacity at 400/415 V (cos phi to IEC 60947-3)	300 A
Rated operational current (lo) at AC-21, 440 V PA Rated operational current (lo) (Los b-back watches) (lor 1 and series of the	Rated breaking capacity at 500 V (cos phi to IEC 60947-3)	290 A
Bitsd sparsal survet (bit shD-1, hasd-beak stables (r = 1 ms) IM Ride sparsal spore r AG-23, 4000 V 50 hs IM Ride sparsal spore r AG-23, 4000 V 50 hs IM Ride sparsal spore r AG-23, 4000 V 50 hs IM Ride sparsal spore r AG-23, 4000 V 50 hs IM Ride sparsal spore r AG-23, 4000 V 50 hs IM Ride spore r AG-23, 4000 V 50 hs IM Ride spore r AG-23, 4000 V 50 hs IM Ride spore r AG-23, 4000 V 50 hs IM Ride short-invert r and	Rated breaking capacity at 660/690 V (cos phi to IEC 60947-3)	250 A
Acta operational power at AC-3, 2000 DV, 50 hr. Image: Second S	Rated operational current (Ie) at AC-21, 440 V	32 A
Rate operational volume (Ua) 42 - hax. Bit with the second of the se	Rated operational current (Ie) at DC-1, load-break switches I/r = 1 ms	32 A
Rated operational voltage (Up) at AC - max Rated miniterrupted current (Up) Rated miniterrupted current (Up) Rated operational winter-circuit current (Up) Rated miniterrupted current (Up) Rated miniterrupted current (Up) Rated admitish winter-circuit current (Up) Rated miniterrupted current (Up) Rated miniterrupted current (Up) Rated admitish winter circuit current (Up) Rated making capacity up to 800 (rosp his IEC/EN 0097-3) Rated making capacity up to 800 (rosp his IEC/EN 0097-3) Nomber of admitish winter (circuit protection ratin) Rated making capacity up to 800 (rosp his IEC/EN 0097-3) Rated making capacity up to 800 (rosp his IEC/EN 0097-3) Number of admitish contrast hommally dosed caratess) Rated making capacity up to 800 (rosp his IEC/EN 0097-3) Rated making capacity up to 800 (rosp his IEC/EN 0097-3) Number of admitish contrast hommally dosed caratess) Rated making capacity up to 800 (rosp his IEC/EN 0097-3) Rated rate	Rated operational power at AC-3, 380/400 V, 50 Hz	0 kW
Rade unitarrupted current lub SA Unitarrupted current lub Rade unitarrupted current lub sapefled for max. cross-section. Rade cenditional start-circuit current (luc) SA LA Short-circuit protection rating SA A SGM, Fusc. Contacts Short-circuit protection rating SA A SGM, Fusc. Contacts Number of auxiliary contacts (hormally closed contacts) SA A SGM, Fusc. Contacts Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of auxiliary contacts (hormally closed contacts) SA SGM Number of	Rated operational power at AC-23A, 400 V, 50 Hz	13 kW
binder upbed current Anded winterrupted current luis specified for max. cross-section. Reted sort-dictional short-circuit current (low) Bit A Contacts. 1 second Short-circuit protection rating Bit A Contacts. 1 second Number of auxiliary contacts (homap-over contacts) Bit A Contacts. 1 second Number of auxiliary contacts (homap-over contacts) Bit A Contacts. 1 second Number of auxiliary contacts (homap-over contacts) Bit A Contacts. 1 second Number of auxiliary contacts (homap-over contacts) Bit A Contacts. 1 second Number of auxiliary contacts (homap-over contacts) Bit A Contacts. 1 second Actator color Actator color Bit A Contacts. 1 second Actator color Meets the product standed's requirements. Bit A Contacts. 1 second. 12.22 Horcicuit of stantact of insulating matrinks to normal heat Meets the product standed's requirements. 12.23 Horcicuit of active and contactors Bit A Contacts. 1 second S requirements. 12.24 Horcicuit of active and contactors Bit A Contacts. 1 second S requirements. </th <th>Rated operational voltage (Ue) at AC - max</th> <th>690 V</th>	Rated operational voltage (Ue) at AC - max	690 V
Actual contract (Cov) State of a contract, 1 second Bated short-sincat current (Cov) State of a contract, 1 second Short-sincat protection rating State of a contract, 1 second Bated making capacity up to S90 V(cos ph to IEC/EN 8997-3] State of a contract, 1 second Values per contract (corrent) State of a contract (corrent) State of a contract (corrent) Number of accilianty contracts (change-over contracts) State of a contract (corrent) State of a contract (corrent) Number of accilianty contracts (corrent) (contracts) State of a contract (corrent) State of a contract (corrent) Actuator type State of a contract (corrent) State of a contract (corrent) State of a contract (corrent) 12.22 Vortication of thread stating of enclosures Meets the product standard's requirements. 12.23 Vortication of thread stating of enclosures Meets the product standard's requirements. 12.23 Vortication of totam stating of enclosures Meets the product standard's requirements. 12.23 Vortication of states of stating of stating materials to normal head Meets the product standard's requirements. 12.23 Vortication of states of stating of stating materials to normal head Meets the product standard's requirements. 12.23 Vortication of states of stating materials	Rated uninterrupted current (lu)	32 A
Refer de dort-time withstand current Town B&B & A A Social Socie Social Sociel Social Social Social Social Social Soc	Uninterrupted current	Rated uninterrupted current lu is specified for max. cross-section.
Refer de dort-time withstand current Town B&B & A A Social Socie Social Sociel Social Social Social Social Social Soc		
Bits of the second se	Rated conditional short-circuit current (Iq)	80 kA
Shet-circuit protection rating PA pB/gL/Lise, Cotacts Rated making capacity up to 600 V (cos ph to EE/EN 6007-3) PA pB/gL/Lise, Cotacts Voltage per contact pair in series SOA Number of auxilary contacts (change-over cotacts) D Actuart type D Actuart type D 102.21 Corrosion resistance Meets the product standard's requirements. 102.21 Verification of thermal stability of encleasures Meets the product standard's requirements. 102.21 Verification of resistance of insulating material sto nomal heat Meets the product standard's requirements. 102.21 Verification of resistance of insulating material sto nomal heat Meets the product standard's requirements. 102.21 Verification of resistance of insulating material sto nomal heat Meets the product standard's requirements. 102.21 Verification of ensemblies Does not apply, since the entire switchgare needs to be avaluad. 102.21 Nerrotion of assemblies Meets the product standard's requirements. 102.21 Nerrotion of assemblies Does not apply, since the entire switchgare needs to be evaluated.	Rated short-time withstand current (Icw)	
Rated making capacity up to 880 V (loss phi to IEU/EN 66047-3) 200 A Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 0 Number of auxiliary contacts (normally closed contacts) 0 Actuator type 0 Actuator type Block Actuator type Door coupling retary drive 102.22 Corosion resistance Meets the product standard's requirements. 102.32 Vorification of resistance of insulating matorials to normal heat Meets the product standard's requirements. 102.32 Usrification of resistance of insulating matorials to normal heat Meets the product standard's requirements. 102.32 Usrification of resistance of insulating matorials to normal heat Meets the product standard's requirements. 102.32 Usrification of resistance of insulating matorials to normal heat Does not apply, since the entire switchger meeds to be evaluated. 102.32 Usrification of resistance of insulating matorials to normal heat Meets the product standard's requirements. 102.32 Usrification of resistance of insulating matorials to normal heat Meets the product standard's requirements. 102.32 Isochrification of assembles Meets the produc	Chart size/it approximation	
Number of auxiliary contacts (change-over orditacts) Image of auxiliary contacts (change-over orditacts) Image of auxiliary contacts (change-over orditacts) Image of auxiliary contacts (change-over orditacts) Number of auxiliary contacts (normally open contacts) Image of auxiliary contacts (normally open contacts) Image of auxiliary contacts (normally open contacts) Actuator color Image of auxiliary contacts (normally open contacts) Image of auxiliary contacts (normally open contacts) 12.22 Corrosion resistance Image of auxiliary contacts (normally open contacts) Image of auxiliary devices (mage of auxiliary of an editary (mage of auxiliary	Short-circuit protection rating	50 A gb/gL, Fuse, Contacts
Number of auxiliary contacts (change-over orditacts) Image of auxiliary contacts (change-over orditacts) Image of auxiliary contacts (change-over orditacts) Image of auxiliary contacts (change-over orditacts) Number of auxiliary contacts (normally open contacts) Image of auxiliary contacts (normally open contacts) Image of auxiliary contacts (normally open contacts) Actuator color Image of auxiliary contacts (normally open contacts) Image of auxiliary contacts (normally open contacts) 12.22 Corrosion resistance Image of auxiliary contacts (normally open contacts) Image of auxiliary devices (mage of auxiliary of an editary (mage of auxiliary	Pated making consolity up to 600 V/ (accepting 100/7-0)	220.4
Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (normally closed contacts) 0 Number of auxiliary contacts (normally closed contacts) 0 Number of auxiliary contacts (normally open contacts) 0 Actuator color Black Actuator color Black Actuator sistance Door coupling rotary drive 10.2.2 Corresion resistance Meets the product standard's requirements. 10.2.3 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3 Verification of insulating materials to normal heat Meets the product standard's requirements. 10.2.3 Verification of insulating materials Does not apply, since the entire switchgear needs to be evaluated. 10.2.5 Uring Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and corepoped stances		
Number of auxiliary contacts (normally coded contacts) Image: Contacts (normally coded contacts) <thimage: (normally="" coded="" contacts="" contacts)<="" th=""> Image</thimage:>	voitage per contact pair in series	60 V
Number of auxiliary contacts (normally coded contacts) Image: Contacts (normally coded contacts) <thimage: (normally="" coded="" contacts="" contacts)<="" th=""> Image</thimage:>	Number of auviliary contacts (abango aver contacts)	
Number of auxiliary contacts (normally open contacts) Image: Contact (Contact) Image: Contact (Cont		
Actuator color Black Actuator type Black 10.22 Corrosion resistance Meets the product standard's requirements. 10.23.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.23.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.23.2 Verification of resistance of insulating materials to normal heat/fire by internal elect effects Meets the product standard's requirements. 10.23.2 Verification of resistance of insulating material stability of enclosures Does not apply, since the entire switchgear needs to be evaluated. 10.23.2 Verification of resistance of insulating material stability of enclosures Does not apply, since the entire switchgear needs to be evaluated. 10.23 Verification of sessenblies Does not apply, since the entire switchgear needs to be evaluated. 10.24 Nechanical inspact Does not apply, since the entire switchgear needs to be evaluated. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric shock Dees not apply, since the entire switchgear needs to be evaluated. 10.3 Internal electrical circuits and connections Is the panel builder's responsibility. 10.3.1 Mueute withstand votage Is the panel build		
Actuator type Dor coupling rotary drive 102.2 Corrosion resistance Meets the product standard's requirements. 102.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 102.3.2 Verification of resistance of insulating materials to normal head Meets the product standard's requirements. 102.3.3 Resist. of insul. mat to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 102.3 Resist. of insul. mat to abnormal heat/fire by internal elect. effects Does not apply, since the entire switchgear needs to be evaluated. 102.5 Infiting Does not apply, since the entire switchgear needs to be evaluated. 102.7 Inscriptions Does not apply, since the entire switchgear needs to be evaluated. 103.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 104.7 Internal electrical circuits and components Does not apply, since the entire switchgear needs to be evaluated. 103.3 Moules witshand voltage Is the panel builder's responsibility. 103.4 Nouters Is the panel builder's responsibility. 103.5 Moules witshand voltage Is the panel builder's responsibility. 103.6 Nourpersenture rise Is the panel builder's responsibility. 103.1 Moules witshand voltage	Number of auxiliary contacts (normally open contacts)	
Actuator type Dor coupling rotary drive 102.2 Corrosion resistance Meets the product standard's requirements. 102.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 102.3.2 Verification of resistance of insulating materials to normal head Meets the product standard's requirements. 102.3.3 Resist. of insul. mat to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 102.3 Resist. of insul. mat to abnormal heat/fire by internal elect. effects Does not apply, since the entire switchgear needs to be evaluated. 102.5 Infiting Does not apply, since the entire switchgear needs to be evaluated. 102.7 Inscriptions Does not apply, since the entire switchgear needs to be evaluated. 103.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 104.7 Internal electrical circuits and components Does not apply, since the entire switchgear needs to be evaluated. 103.3 Moules witshand voltage Is the panel builder's responsibility. 103.4 Nouters Is the panel builder's responsibility. 103.5 Moules witshand voltage Is the panel builder's responsibility. 103.6 Nourpersenture rise Is the panel builder's responsibility. 103.1 Moules witshand voltage	Actuator color	Black
10.22 Corrosion resistance Meets the product standard's requirements. 10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.1 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Does not apply, since the entire switchgear needs to be evaluated. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electric alc circuits and connections Is the panel builder's responsibility. 10.4 Clearances made of insulating material Is the panel builder's responsibility. 10.5 Protection spaint electric strength Is the panel builder's responsibility. 10.4 Clearances and components Is the panel builder's responsibility. 1		
10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric strongth Est the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Inpulse withstand voltage Is the panel builder's responsibility. 10.9.1 Thermarie in electrical circuit rating Is the panel builder's responsibility. 10.9.1 Prover-frequency electric strength Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Inpulse withstand voltage <t< td=""><td></td><td></td></t<>		
10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric strongth Est the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Inpulse withstand voltage Is the panel builder's responsibility. 10.9.1 Thermarie in electrical circuit rating Is the panel builder's responsibility. 10.9.1 Prover-frequency electric strength Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Inpulse withstand voltage <t< th=""><th>10.2.2 Corrosion resistance</th><th>Meets the product standard's requirements</th></t<>	10.2.2 Corrosion resistance	Meets the product standard's requirements
10.2.3.2 Verification of resistance of insulting materials to normal heatMeets the product standard's requirements.10.2.3.3 Resist. of insult.mat. to abnormal heat/fire by internal elect. effectsMeets the product standard's requirements.10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility.10.12 Electromagnetic compatibility.Is the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction		
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effectsMeets the product standard's requirements.10.2.5 LiftingDees not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical impactDees not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDees not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDees not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDees not apply, since the entire switchgear needs to be evaluated.10.8 Connections for external conductorsIs the panel builder's responsibility.10.8.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility.10.12 Electromagnetic compatibility.Is the panel builder's responsibility. The specifications for the switchgear must be abserved.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction		
10.2.5 LiftingDees not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical impactDees not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesDoes not apply, since the entire switchgear needs to be evaluated.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsDoes not apply, since the entire switchgear needs to be evaluated.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder is responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction		· · · ·
10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provide the information in the instruction		
10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibility.Is the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	· ·	
10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesDoes not apply, since the entire switchgear needs to be evaluated.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibility.Is the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provide the information in the instruction	· · · · · · · · · · · · · · · · · · ·	
10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction		· · · ·
10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provide the information in the instruction		
10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.		
10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	•	
10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction		
10.9.2 Power-frequency electric strengthImage: strength in the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionImage: stresponsibility. The specifications for the switchgear must be observed.		
10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise The panel builder is responsibile for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction		
10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise Is the panel builder is responsibility. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function Image: Compatibility of the temperature rise calculation in the instruction		
10.10 Temperature rise The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function Inte device meets the requirements, provided the information in the instruction		
Instruction Instruction Instruction 10.11 Short-circuit rating Instruction Instruction 10.12 Electromagnetic compatibility Instruction Instruction 10.13 Mechanical function Instruction Instruction	· · · · · · · · · · · · · · · · · · ·	
Image: state of the second st		
10.13 Mechanical function observed.	10.11 Short-circuit rating	
	10.12 Electromagnetic compatibility	
	10.13 Mechanical function	

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Switch disconnector (EC000216)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Switch disconnector (ecl@ss10.0.1-27-37-14-03 [AKF060013])

Version as main switch

Yes

Version as maintenance-/service switch		Yes
Version as safety switch		No
Version as emergency stop installation		No
Version as reversing switch		No
Number of switches		1
Max. rated operation voltage Ue AC	V	690
Rated operating voltage	V	415 - 690
Rated permanent current lu	Α	32
Rated permanent current at AC-23, 400 V	А	
Rated permanent current at AC-21, 400 V	А	32
Rated operation power at AC-3, 400 V	kW	0
Rated short-time withstand current lcw	kA	0.64
Rated operation power at AC-23, 400 V	kW	13
Switching power at 400 V	kW	
Conditioned rated short-circuit current Iq	kA	80
Number of poles		3
Number of auxiliary contacts as normally closed contact		0
Number of auxiliary contacts as normally open contact		0
Number of auxiliary contacts as change-over contact		0
Motor drive optional		No
Motor drive integrated		No
Voltage release optional		No
Device construction		Complete device in housing
Suitable for floor mounting		Yes
Suitable for front mounting 4-hole		No
Suitable for front mounting centre		No
Suitable for distribution board installation		No
Suitable for intermediate mounting		No
Colour control element		Black
Type of control element		Door coupling rotary drive
Interlockable		Yes
Type of electrical connection of main circuit		Screw connection
Degree of protection (IP), front side		IP65
Degree of protection (NEMA)		12