

## **RMH0664 BATTERY**

### **1. Scope**

**This technical specification is for the product of RMH0664 Ni-MH rechargeable battery pack.**

### **2. Cell Type**

**Cell: Sealed Nickel Hydroxide Cylindrical Cell 8pcs pack**

**Model: 2/3AA**

**Size: 2/3AA**

### **3. Rating**

**Nominal Voltage: 9.6V per pack**

**Nominal Capacity: 750mAh**

**Standard Charging: 75mA charge 16 hrs**

**Quick Charging: 375mA charge 2.4hrs**

**Discharge End Voltage: 8.0V per pack**

**Maximum Discharge: 1.5A Current**

**Weight: 133g**

**Charge Temperature: 0°C to 45°C**

**Discharge Temp: -20°C to 60°C**

**Storage Temperature: -20°C to 55°C**

### **4. Physical Specification**

**Length: 65.1mm**

**Width: 60.0mm**

**Height: 21.6mm**

**Maximum Overstep: 0.1mm**

## **5. Electrical Test**

### **5.1 Charging Characteristics**

The battery pack should be charged under the following conditions:

- At a constant current of 75mA for 16 hrs (Standard Charges)
- At a constant current of 375mA for 2.4hrs (Quick Charge)

The above tests are the ambient temperature of 20°C (+,-5°C)

### **5.2 Discharge Characteristics**

After adopt the above charge procedure as 5.1 the battery pack is stored for 1 hour at the same temperature range, this is to be discharged at various current till the end voltage reaches 8.0V

- At 150mA discharge for 5hrs (0.2C)
- At 225mA discharge for 3.3hrs (0.3C)
- At 750mA discharge for 54 minutes (1C)
- At 1.5 A discharge for 25minutes (2C)

### **5.3 Capacity Characteristics**

The battery pack should be at or more than 90% minimum capacity under the above either charging or discharging procedure.

### **5.4 Charge retention**

After stand charging procedure as per 5.1, the battery pack store for 28 days, then discharge the battery pack are 0.2C, the nominal capacity shall not be less than 60%.

- Before using, the battery pack shall be properly charged as 5.1.
- Keep the battery pack in cool and dry place.
- DO NOT throw the battery pack into fire or disassembles them.
- DO NOT short-circuit the battery pack
- DO NOT charge with more than specified current.

**WARNING:** This battery pack should be charged by proper specified charger .  
After long storage, it is desirable to cycle (charge/discharge) the battery 3 times to restore full capacity.

We reserves the right to modify product specification and data stated herein without prior notice.