




ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 3 POLES 20A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING

| Product designation | | | Rotary cam |
|--|------------------------------|-------------|---|
| Product type designation | | | switches GX20 |
| General characteristics | | | GAZU |
| Switching diagram | | | 53 - Changeover switch 3 poles - 2 speed motor starting with separate windings |
| N° of elements | | | 3 |
| Mounting form | | | U12 - Front mounting without front plate with key operation for hole diam. 22mm fixing |
| Contact characteristics | | | |
| Rated insulation voltage Ui | IEC/EN UL/CSA | V V | 690 600 |
| Rated impulse withstand voltage Uimp | | kV | 6 |
| Conventional free air thermal current Ith | IEC/EN | A | 20 |
| But I a conform to the conformation to the con | UL/CSA | A | 15 |
| Rated operational voltage | | V kV | 440 |
| Rated operational impulse voltage Maximum fuse size for short-circuit protection In (gG) | | KV | 4 |
| | 10kA 15kA 25kA | A A A | 20 20 20 |
| Rated short time current Icw | 1s | Α | 250 |
| Conductivity | | | 10/5 mA/V |
| Operational current le IEC/EN AC1/AC21A | | | |
| 1045 | | Α | 20 |
| AC15 | 110V 220/230V 380/400V | A A A | 10 8 6 |
| | 660/690V | Α | 1.5 |
| Rated operational power in AC Three-phase AC-3 | | | |
| | 220/230V 380/440V | kW kW | 3.7 5.5 |
| Single-phase AC-3 | 500/690V | kW | 5.5 |
| . | 110V | kW | 0.75 |
| | 220/230V | kW | 1.8 |
| TI 1 2000 | 380/440V | kW | 3 |
| Three-phase AC23A | 220/230V 380/440V | kW kW | 4 |
| | 300/4407 | r V V | 7.5 |





ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 3 POLES 20A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING

| | | 500/0001/ | 1.107 | 7.5 |
|--------------------------|---------------------------------------|------------|------------|-------------------|
| | Single phase AC22A | 500/690V | kW | 7.5 |
| | Single-phase AC23A | 110V | kW | 0.75 |
| | | 220/230V | kW | 2.2 |
| | | 380/440V | kW | 3.5 |
| Rated operational curr | ent in DC | | | |
| • | DC21A | | | |
| | | 48V | Α | 20 |
| | | 60V | Α | 20 |
| | | 110V | Α | 4 |
| | | 220V | Α | 0.6 |
| | | 440V | Α | 0.25 |
| | DC23A (poles in series) | | | |
| | | 24V | Α | 20 (1) |
| | | 48V | A | 20 (2) |
| | | 60V | A | 20 (3) |
| | | 110V | A | 10 (3) |
| | DC13 | 220V | Α | 8 (4) |
| | DO13 | 24V | Α | 20 |
| | | 48V | A | 16 |
| | | 60V | A | 12 |
| | | 110V | A | 1 |
| | | 220V | A | 0.4 |
| | | 440V | A | 0.15 |
| Power dissipation | | | W | 0.6 |
| Mechanical features | | | | |
| Terminals screw | | | | M3 |
| Tightening torque for to | erminals max | | Nm | 0.8 |
| Conductor size | | | | |
| | AWG - Rigid cable | | | |
| | | min | AWG | 20 |
| | | Max | AWG | 12 |
| | AWG - Flexible cable | | | |
| | | min | AWG | 20 |
| | 01 | Max | AWG | 12 |
| | Conductor size (IEC) - Flexible cable | | | 0.5 |
| | | min Mov | mm² mm² | 0.5 |
| | Conductor size (IEC) - Rigid cable | Max | 1111117 | 2.5 |
| | Conductor Size (IEC) - Rigid Cable | min | mm² | 0.5 |
| | | Max | mm² | 2.5 |
| Mechanical life | | IVICA | cycles | 1X10 ⁶ |
| UL technical data | | | 5,5.55 | |
| Motor power for direct | -on-line control | | | |
| | for three-phase motor | | | |
| | • | 120V | HP | 1.5 |
| | | 240V | HP | 3 |
| | | 480V | HP | 5 |
| | | 600V | HP | 5 |
| | for single-phase motor | | | |
| | | 120V | HP | 0.75 |
| | | 240V | HP | 1.5 |
| Ambient conditions | | | | 1.0 |



ENERGY AND AUTOMATION

ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 3 POLES 20A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING

Temperature


Operating temperature


| | min | °C | -25 | |
|---------------------|-----|----|-----|---|
| | max | °C | +55 | |
| Storage temperature | | | | , |
| | min | °C | -40 | |
| | max | °C | +70 | |

Resistance & Protection

| Frontal IP degree | IP65 |
|---------------------|------|
| Terminals IP degree | IP20 |


Dimensions





| Series | L | | | |
|--------|----|------|----|-------|
| | 1 | 2 | 3 | 8 |
| GX16 | 54 | 62.5 | 71 | 113.4 |
| GX20 | 54 | 62.5 | 71 | 113.4 |

Wiring diagrams



Certifications and compliance

Compliance

| CSA C22.2 n° 14 |
|---------------------|
| IEC/EN/BS 60947-1 |
| IEC/EN/BS 60947-3 |
| IEC/EN/BS 60947-5-1 |
| IEC/EN/BS 61058-1 |
| UL60947-4-1 |

Certificates

| cULus |
|-------|
| FΔC |

ETIM classification



GX2053U12

ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH 3 POLES 20A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING

ETIM 8.0

EC001029 -Selector switch, complete