



ROTARY CAM SWITCH GF SERIES, CHANGEOVER SWITCH 1 POLE 20A, FOR SNAP ON FRONT MOUNTING WITH BLACK HANDLE FOR HOLE Ø22MM FIXING, FRONT PLATE 48X48MM

| Product designation | | | Rotary cam |
|--|------------------|--------|---|
| - | | | switches GF20 |
| Product type designation General characteristics | | | GF20 |
| | | | 51 - Changeover |
| Switching diagram | | | switch 1 pole |
| N° of elements | | | 1 |
| Mounting form | | | U47 - Snap on fron mounting with black handle for hole diam. 22mm finxing |
| Contact characteristics | | | |
| Rated insulation voltage Ui | IEC/EN UL/CSA | V V | 480 240 |
| Rated impulse withstand voltage Uimp | | kV | 4 |
| Conventional free air thermal current Ith | | | |
| | IEC/EN | Α | 20 |
| B. I | UL/CSA | A | 15 |
| Rated operational voltage | | V | 480 |
| Rated operational impulse voltage Maximum fuse size for short-circuit protect | ion In (aC) | kV | 4 |
| Maximum ruse size for short-circuit protect | 10kA 15kA | A A | 20 20 |
| | 25kA | Α | 20 |
| Rated short time current Icw | 1s | А | 250 |
| Conductivity | | | 10/5 mA/V |
| Operational current le IEC/EN | | | |
| AC1/AC21A | | ۸ | 20 |
| AC15 | | A | 20 |
| 7.010 | 110V | Α | 10 |
| | 220/230V | A | 8 |
| Poted energtional newer in AC | 380/400V | A | 6 |
| Rated operational power in AC Three-phase AC- | | | |
| Thice phase Ac- | , 220/230V | kW | 3 |
| | 380/440V | kW | 5 |
| Single-phase AC | 3 | | |
| | 110V | kW | 0.5 |
| | 220/230V | kW | 1.5 |
| There a share A O | 380/440V | kW | 2 |
| Three-phase AC | 3A 220/230V | kW | 4 |
| | 380/440V | kW | 7.5 |
| Single-phase AC | | | |
| g pacc / | 110V | kW | 0.75 |
| | 220/230V | kW | 2 |
| | 380/440V | kW | 2.5 |

DC21A






ROTARY CAM SWITCH GF SERIES, CHANGEOVER SWITCH 1 POLE 20A, FOR SNAP ON FRONT MOUNTING WITH BLACK HANDLE FOR HOLE Ø22MM FIXING, FRONT PLATE 48X48MM

| | | 48V | Α | 20 |
|--------------------------|--|-------|--------|-------------------|
| | | 60V | Α | 20 |
| | | 110V | Α | 4 |
| | | 220V | Α | 0.7 |
| | | 440V | Α | 0.2 |
| | DC13 | | - , , | |
| | | 24V | Α | 6 |
| | | 48V | A | 6 |
| | | 60V | A | 3 |
| | | 110V | A | 1 |
| | | 220V | A | 0.4 |
| | | 440V | A | 0.15 |
| Power dissipation | | 440 V | W | 0.8 |
| Mechanical features | | | VV | 0.0 |
| | | | | MO |
| Terminals screw | and the all and an and | | Nima | M3 |
| Tightening torque for te | erminais max | | Nm | 0.5 |
| Conductor size | | | | |
| | AWG - Rigid cable | | | |
| | | min | AWG | 20 |
| | | Max | AWG | 12 |
| | AWG - Flexible cable | | | |
| | | min | AWG | 20 |
| | | Max | AWG | 12 |
| | Conductor size (IEC) - Flexible cable | | | |
| | | min | mm² | 0.5 |
| | | Max | mm² | 2.5 |
| | Conductor size (IEC) - Rigid cable | | | _ |
| | | min | mm² | 0.5 |
| | | Max | mm² | 2.5 |
| Mechanical life | | | cycles | 1x10 ⁶ |
| UL technical data | | | | |
| Motor power for direct- | on-line control | | | |
| | for three-phase motor | | | |
| | To the process make | 240V | HP | 3 |
| | for single-phase motor | 2.01 | | |
| | Tor single phase motor | 240V | HP | 1 |
| Ambient conditions | | 2101 | | • |
| Temperature | | | | |
| remperature | Operating temperature | | | |
| | Operating temperature | min | °C | 25 |
| | | min | °C | -25 |
| | 01 | max | | +55 |
| | Storage temperature | | 0.0 | 40 |
| | | min | °C | -40 |
| | | max | °C | +70 |
| Resistance & Protection | on The Control of the | | | |
| Frontal IP degree | | | | IP40 |
| Terminals IP degree | | | | IP20 |
| Dimensions | | | | |




ROTARY CAM SWITCH GF SERIES, CHANGEOVER SWITCH 1 POLE 20A, FOR SNAP ON FRONT MOUNTING WITH BLACK HANDLE FOR HOLE Ø22MM FIXING, FRONT PLATE 48X48MM



| Series | Dimensions | | L | | | |
|--------|------------|------|----|------|----|-------|
| | □A | Е | 1 | 2 | 3 | 8 |
| GF10 | 30 | 18.5 | 60 | 72 | 84 | 144 |
| GF20 | 48 | 26.5 | 56 | 69.5 | 83 | 150.5 |

Wiring diagrams



Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

UL60947-4-1

Certificates

cULus

EAC

ETIM classification

ETIM 8.0

EC001029 -Selector switch, complete