

MODBUS TABLE ORGANIZATION

Starting Address of the Group Registers (Dec)	Starting Address of the Group Registers (Hex)	System Version (Release)	System Version (Build)	Group Name (Text)	Group Code (Hex)	Group Complexity (Hex)	Group Version (Hex)	Object Code
16640	4100	01	16	Contacteur State	52 01	10	01 00	
16640	4100	01	16	Contacteur State Configuration	52 01	10	01 00	

MODBUS PROTOCOL DETAILS

Function Code (Dec)	Exception Codes (Dec)	Data Encoding
2 (Read Discrete Inputs)	1, 2, 3	"Big Endian" (most significant byte first)
1 (Read Coils)	1, 2, 3	"Big Endian" (most significant byte first)
5/15 (Write Single/Multiple Coils)	1, 2, 3	"Big Endian" (most significant byte first)
4 (Read Input Registers)	1, 2, 3	"Big Endian" (most significant byte first)
3 (Read Holding register)	1, 2, 3	"Big Endian" (most significant byte first)
6/16 (Write Single/Multiple Holding register)	1, 2, 3	"Big Endian" (most significant byte first)

MODBUS OVER SERIAL DETAILS

Physical Layer	Trasmission Modes	Device Addressing	Baud Rates (bit/s)	Data Bits	Data bits trasmission sequence	Parity	Stop Bits
standard EIA/TIA 485 (RS-485) two-wire configuration	RTU	1÷247	programmable (1200, 2400, 4800, 9600, 19200, 38400)	8	Least significant bit first	NONE	1

MASTER/SLAVE COMMUNICATION TIMING

Timer Description	Timer Value (msec)
Inter-character time-out	< 1,5 character times
Response delay (from master request)	-
Delay Time (between two master trasmissions)	-

REFER ALSO TO:

www.modbus.org

- MODBUS over serial line specification and implementation guide V1.02
 - MODBUS APPLICATION PROTOCOL SPECIFICATION V1.1b

NOTE:

File and printed copies of this document are not subject to document change control.



Register Number	Register Address (Dec)	Register Address (Hex)	Dimension [bit]	Description	Read Function Codes (Dec)	Data Storing
16641	16640	4100	2	Contactor State		
16641	16640	4100	1	State of Contact 1	2	
16642	16641	4101	1	State of Contact 2	2	
16643	16642	4102	1	State of Contact 3	2	
16644	16643	4103	1	State of Contact 4	2	

Register Number	Register Address (Dec)	Register Address (Hex)	Dimension [bit]	Description	Note	Read Function Codes (Dec)	Write Function Codes (Dec)	Data Storing
-----------------	------------------------	------------------------	-----------------	-------------	------	---------------------------	----------------------------	--------------



Register Number	Register Address (Dec)	Register Address (Hex)	Dimension [word]	Bit Position	Description	Type	Scale	Unit	Range	Note	Read Function Code (Dec)	Data Storing
-----------------	------------------------	------------------------	------------------	--------------	-------------	------	-------	------	-------	------	--------------------------	--------------



Register Number	Register Address (Dec)	Register Address (Hex)	Dimension [word]	Bit Position	Description	Type	Scale	Unit	Range	Note	Read Function Codes (Dec)	Write Function Codes (Dec)	Data Storing
16641	16640	4100	6		Contactor State Configuration								
16641	16640	4100	1		Number of associated contacts					(3)	3	6,16	
16642	16641	4101	1		Configuration of Contact 1					(7)	3	6,16	
16643	16642	4102	1		Configuration of Contact 2					(7)	3	6,16	
16644	16643	4103	1		Configuration of Contact 3					(7)	3	6,16	
16645	16644	4104	1		Configuration of Contact 4					(7)	3	6,16	

NOTE 3) BIT 0: Normally Open = 0, Normally Closed = 1
 BIT 1-2: impulsive = 00, maintained = 10, toggle = 01
 BIT 3: 0 = independent, 1 = interlocked
 BIT 4-15: not used

NOTE 7) BIT 0: Normally Open = 0, Normally Closed = 1

