

PRODUCT-DETAILS

# MS132-0.63K

## MS132-0.63K Manual Motor Starter 0.40 ... 0.63 A



### Informations générales

Extension du type de produit	MS132-0.63K
Code de produit	1SAM350010R1004
EAN	4013614400346
Description courte	MS132-0.63K Manual Motor Starter 0.40 ... 0.63 A

### Description longue

The MS132-0.63K manual motor starter (also known as motor protection circuit breaker or manual motor protector) is a compact 45 mm width device with a rated operational current of  $I_e = 0.63$  A with Push-in spring terminals. This device is used to manually switch on and off motors and to protect them reliably and without the need for a fuse from short-circuits, overload and phase failures. The MS132-K manual motor starter offers a rated service short-circuit breaking capacity  $I_{cs} = 100$  kA at 400 VAC and trip class 10. Further features are the build-in disconnect function, temperature compensation, trip-free mechanism and a rotary handle with a clear switch position indication. The MS132-K manual motor starter is suitable for three- and single-phase applications. The handle is lockable to protect against unauthorized changes. Auxiliary contacts, signaling contacts, undervoltage releases, shunt trips and terminal spacers are available as accessory.

### Commande

Quantité minimum	1 pièce
Code douanier	85362010

### Downloads Préférés

Fiche produit, informations techniques	1SBC100212C0203
--	-----------------

Instructions et manuels	2CDC131120M6801
Instructions et manuels (Partie 2)	2CDC131060M0202
Ex Operating Instructions	2CDC131063M6801
Time-Current Characteristic Curve	1SAM300505F0104
I <sup>2</sup> t Characteristic	1SAM300507F0001 1SAM300507F0003
Cut-off Current Characteristic	1SAM300508F0001 1SAM300508F0003
CAD Dimensional Drawing	2CDC001079B0201
Installation Video	9AKK108466A6074 9AKK108466A6068
Marketing Video	9AKK107991A4712 2CDC131153V0201

## Dimensions

Produit Largeur Net	45 mm
Produit Hauteur Net	112 mm
Produit Longueur Net	87 mm
Poids net	0.256 kg

## Technique

Pouvoir assigné de coupe de service en court-circuit (I <sub>CS</sub> )	(230 V AC) 100 kA (250 V DC) 3 Poles in Series 10 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (690 V AC) 100 kA
Pouvoir assigné de coupe ultime en court- circuit (I <sub>CU</sub> )	(230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (690 V AC) 100 kA
Courant assigné instantané de réglage de court-circuit (I <sub>r</sub> )	7.9 A
Setting Range	0.40 ... 0.63 A
Puissance assignée d'emploi AC-3 (P <sub>e</sub> )	(400 V) Three Phase 0.18 kW
Puissance assignée d'emploi AC-3e (P <sub>e</sub> )	(400 V) Three Phase 0.18 kW
Tension	Circuit principal 690 V AC Circuit principal 250 V DC
Courant nominal de fonctionnement (I <sub>e</sub> )	0.63 A
Courant assignée d'emploi AC-3 (I <sub>e</sub> )	0.63 A
Courant assignée d'emploi AC-3e (I <sub>e</sub> )	0.63 A
Courant assignée d'emploi DC-5 (I <sub>e</sub> )	0.63 A
Fréquence assignée (f)	Circuit principal 50 Hz Circuit principal 60 Hz
Operating Frequency (f <sub>sw</sub> )	0 ... 400 Hz
Tension assignée de tenue aux chocs (U <sub>imp</sub> )	Circuit principal 6 kV

Tension assignée d'isolement (U <sub>i</sub> )	690 V
Power Loss	at Rated Operating Conditions per Pole 0.7 ... 1.7 W
Nombre de pôles	3
Courant thermique conventionnel à l'air libre (I <sub>th</sub> )	Main Circuit 0.63 A
Indice de protection	Housing IP20 Main Circuit Terminals IP20
Degré de pollution	3
Electrical Durability	50000 cycle
Durabilite mecanique	100000 cycle
Type de borne	Push-in Spring Terminals
Connecting Capacity Main Circuit	Flexible with Ferrule 1/2x 0.5 ... 4 mm <sup>2</sup> Flexible with Insulated Ferrule 1x 0.5 ... 4 mm <sup>2</sup> Flexible with Insulated Ferrule 2x 0.5 ... 2.5 mm <sup>2</sup> Flexible 1/2x 0.75 ... 4 mm <sup>2</sup> Solid 1/2x 1 ... 2.5 mm <sup>2</sup> Stranded 1/2x 1 ... 6 mm <sup>2</sup>
Wire Stripping Length	Main Circuit 12 mm
Recommended Screw Driver	Pozidriv 2
Type d'encastrement	1 ... 6
Montage sur rail DIN	TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715
Minimum Mounting Distance	Electrical Conductive Board, Horizontal - Up to 400 V 0 mm Electrical Conductive Board, Horizontal - Up to 690 V 1.5 mm Electrical Conductive Board, Vertical 75 mm Other Device Same Type, Horizontal 0 mm Other Device Same Type, Vertical 150 mm
Actuator Type	Rotary Handle
Contact Position Indication	ON / OFF / TRIP
Normes et standards	IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 UL 60947-1 UL 60947-4-1
Remarques	UL508 Self-Protected Combination Motor Controller (Type E) in combination with terminal spacer TS1-M3-K

## Technique UL/CSA

Short-Circuit Current Rating (SCCR)	Manual Self-Protected Combination Controllers (Type E), (480Y / 277 V AC) 65 kA Manual Self-Protected Combination Controllers (Type E), (600Y / 347 V AC) 47 kA Any UL Listed Fuses or Circuit-Breakers, Group Installations (480 V AC) 65 kA Any UL Listed Fuses or Circuit-Breakers, Group Installations (600 V AC) 47 kA Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (480 V AC) 65 kA Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (600 V AC) 47 kA Any UL Listed Fuses or Circuit-Breakers, Tap Conductor Protection in Group Installations (480Y / 277 V AC) 65 kA Any UL Listed Fuses or Circuit-Breakers, Tap Conductor Protection in Group Installations (600Y / 347 V AC) 47 kA
Maximum Operating Voltage UL/CSA	Circuit principal 600 V AC
Full Load Amps Motor Use	(200 V AC) Three Phase 0.63 A (208 V AC) Three Phase 0.63 A (220 ... 240 V AC) Three Phase 0.63 A (440 ... 480 V AC) Three Phase 0.63 A (550 ... 600 V AC) Three Phase 0.63 A
Locked Rotor Amps	(200 V AC) Three Phase 3.78 A (208 V AC) Three Phase 3.78 A (220 ... 240 V AC) Three Phase 3.78 A (440 ... 480 V AC) Three Phase 3.78 A

(550 ... 600 V AC) Three Phase 3.78 A

General Use Rating UL/CSA	(600 V AC) 0.63 A
Connecting Capacity Main Circuit UL/CSA	Stranded 1/2x 18-10 AWG Stranded 1x 8 AWG

## Environnement

Température de l'air ambiant	Around the Enclosure 0 ... +40 °C Operation -25 ... +70 °C Operation Compensated -25 ... +60 °C Storage -50 ... +80 °C
Ambient Air Temperature Compensation	Oui
Altitude de fonctionnement maximale autorisée	2000 m
REACH Declaration	1SAA963005-4502
Résistance aux chocs selon CEI 60068-2-27	11 ms Pulse 25g
Resistance to Vibrations acc. to IEC 60068-2-6	5g / 3 ... 150 Hz
Informations RoHS	1SAA963006-4502
Statut RoHS	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

## Certificats et Déclarations (Numéro de document)

Certificat ABS	1SAA963001-0101
Certificat ATEX	1SAA963000-3902
CB Certificate	1SAA963002-2002
CQC Certificate	CQC2017010307034621
Cut-off Current Characteristic	1SAM300508F0001 1SAM300508F0003
Declaration of Conformity - CCC	2020980307004600
Déclaration de Conformité - CE	1SAD101100-3402
Declaration of Conformity - UKCA	1SAD201100-3402
EAC Certificate	1SAA963004-2701
I <sup>pt</sup> Characteristic	1SAM300507F0001 1SAM300507F0003
IECEx Certificate	1SAA963000-4001
KC Certificate	1SAA963002-1502
Certificat RINA	1SAA963002-0802
Certificat UL	E137861-20090225 E345003-20090225

## Emballage

Emballage Niveau 1 Unités	box 1 pièce
Emballage Niveau 1 Largeur	50 mm
Emballage Niveau 1 Longueur	117 mm
Emballage Niveau 1 Hauteur	82 mm

Emballage Niveau 1 Poids	0.282 kg
Emballage Niveau 1 EAN	4013614400346
Emballage Niveau 2 Unités	carton 28 pièce
Emballage Niveau 2 Largeur	280 mm
Emballage Niveau 2 Longueur	395 mm
Emballage Niveau 2 Hauteur	210 mm
Emballage Niveau 2 Poids	14.026 kg
Emballage Niveau 2 EAN	4013614522666

## Classifications

Code de classification d'objet	F
ETIM 5	EC000074 - Motor protective circuit-breaker
ETIM 6	EC000074 - disjoncteur/démarrreur de moteur
ETIM 7	EC000074 - Motor protection circuit-breaker
ETIM 8	EC000074 - Motor protection circuit-breaker
eClass	V11.0 : 27370401
UNSPSC	39121521
Code de catégorie granulaire IDÉA (IGCC)	4731 >> Manual Starters
E-Number (Finland)	3707834
E-Number (Sweden)	3110453

## Accessories

Identifiant	Description	Type	Quantity	Unit Of Measure
1SAM201901R1001	HKF1-11 Auxiliary Contact	HKF1-11	1	piece
1SAM201901R1201	HKF1-11K Auxiliary Contact	HKF1-11K	1	piece
1SAM201901R1002	HKF1-20 Auxiliary Contact	HKF1-20	1	piece
1SAM201901R1202	HKF1-20K Auxiliary Contact	HKF1-20K	1	piece
1SAM201901R1004	HKF1-01 Auxiliary Contact	HKF1-01	1	piece
1SAM201901R1003	HKF1-10 Auxiliary Contact	HKF1-10	1	piece
1SAM201902R1002	HK1-20 Auxiliary Contact	HK1-20	1	piece
1SAM201902R1202	HK1-20K Auxiliary Contact	HK1-20K	1	piece
1SAM201902R1001	HK1-11 Auxiliary Contact	HK1-11	1	piece
1SAM201902R1201	HK1-11K Auxiliary Contact	HK1-11K	1	piece
1SAM201902R1003	HK1-02 Auxiliary Contact	HK1-02	1	piece
1SAM201902R1203	HK1-02K Auxiliary Contact	HK1-02K	1	piece
1SAM201902R1004	HK1-20L Auxiliary Contact	HK1-20L	1	piece
1SAM201902R1204	HK1-20LK Auxiliary Contact	HK1-20LK	1	piece
1SAM201903R1002	SK1-20 Signaling Contact	SK1-20	1	piece
1SAM201903R1202	SK1-20K Signaling Contact	SK1-20K	1	piece
1SAM201903R1005	SK1-20AR Signaling Contact	SK1-20AR	1	piece
1SAM201903R1205	SK1-20ARK Signaling Contact	SK1-20ARK	1	piece
1SAM201903R1001	SK1-11 Signaling Contact	SK1-11	1	piece
1SAM201903R1201	SK1-11K Signaling Contact	SK1-11K	1	piece
1SAM201903R1004	SK1-11AR Signaling Contact	SK1-11AR	1	piece

1SAM201903R1204	SK1-11ARK Signaling Contact	SK1-11ARK	1	piece
1SAM201903R1003	SK1-02 Signaling Contact	SK1-02	1	piece
1SAM201903R1203	SK1-02K Signaling Contact	SK1-02K	1	piece
1SAM201903R1006	SK1-02AR Signaling Contact	SK1-02AR	1	piece
1SAM201903R1206	SK1-02ARK Signaling Contact	SK1-02ARK	1	piece
1SAM301901R1002	CK1-20 Short Circuit Signaling Contact	CK1-20	1	piece
1SAM301901R1001	CK1-11 Short Circuit Signaling Contact	CK1-11	1	piece
1SAM301901R1003	CK1-02 Short Circuit Signaling Contact	CK1-02	1	piece
1SAM201910R1001	AA1-24 Shunt Trip	AA1-24	1	piece
1SAM201910R1002	AA1-110 Shunt Trip	AA1-110	1	piece
1SAM201910R1003	AA1-230 Shunt Trip	AA1-230	1	piece
1SAM201910R1004	AA1-400 Shunt Trip	AA1-400	1	piece
1SAM201904R1010	UA1-20 Undervoltage Release	UA1-20	1	piece
1SAM201904R1001	UA1-24 Undervoltage Release	UA1-24	1	piece
1SAM201904R1002	UA1-48 Undervoltage Release	UA1-48	1	piece
1SAM201904R1003	UA1-60 Undervoltage Release	UA1-60	1	piece
1SAM201904R1004	UA1-110 Undervoltage Release	UA1-110	1	piece
1SAM201904R1008	UA1-208 Undervoltage Release	UA1-208	1	piece
1SAM201904R1005	UA1-230 Undervoltage Release	UA1-230	1	piece
1SAM201904R1006	UA1-400 Undervoltage Release	UA1-400	1	piece
1SAM201904R1007	UA1-415 Undervoltage Release	UA1-415	1	piece
1SAM201904R1009	UA1-575 Undervoltage Release	UA1-575	1	piece
1SAM301903R1002	PS1-2-0-65K Busbar	PS1-2-0-65K	1	piece
1SAM301903R1003	PS1-3-0-65K Busbar	PS1-3-0-65K	1	piece
1SAM301903R1004	PS1-4-0-65K Busbar	PS1-4-0-65K	1	piece
1SAM301903R1005	PS1-5-0-65K Busbar	PS1-5-0-65K	1	piece
1SAM301903R1012	PS1-2-1-65K Busbar	PS1-2-1-65K	1	piece
1SAM301903R1013	PS1-3-1-65K Busbar	PS1-3-1-65K	1	piece
1SAM301903R1014	PS1-4-1-65K Busbar	PS1-4-1-65K	1	piece
1SAM301903R1015	PS1-5-1-65K Busbar	PS1-5-1-65K	1	piece
1SAM201909R1001	FS116 Screw Fixing Kit	FS116	1	piece
1SAM301913R1001	TS1-M3-K Terminal Spacer	TS1-M3-K	1	piece
GJF1101903R0002	SA2 Terminals and Installation Material	SA2	1	piece
1SAM201911R1012	IB132-F Enclosure	IB132-F	1	piece
1SAM201911R1010	IB132-G Enclosure	IB132-G	1	piece
1SAM201911R1011	IB132-Y Enclosure	IB132-Y	1	piece
1SAM201912R1010	DMS132-G Door Mounting Kit	DMS132-G	1	piece
1SAM201912R1011	DMS132-Y Door Mounting Kit	DMS132-Y	1	piece
1SAM201909R1021	MSAH1 Shaft Supporter	MSAH1	1	piece
1SAM201920R1011	MSHD-LTB Handles	MSHD-LTB	1	piece
1SAM201920R1012	MSHD-LTY Handles	MSHD-LTY	1	piece
1SAM201920R1000	MSH-AR Shaft Alignment Ring	MSH-AR	1	piece
1SAM101923R0002	MSMN Driver	MSMN	1	piece
1SAM101923R0012	MSMNO Driver	MSMNO	1	piece
1SCA101647R1001	OXS6X85 SHAFT	OXS6X85	1	piece
1SCA108043R1001	OXS6X105 SHAFT	OXS6X105	1	piece
1SCA101655R1001	OXS6X130 SHAFT	OXS6X130	1	piece
1SCA101659R1001	OXS6X180 SHAFT	OXS6X180	1	piece

---

## Catégories

---

Produits basse tension → Disjoncteurs de puissance → Disjoncteurs-moteurs

Produits basse tension → Produits de Contrôle, Protection et sécurité machines → Disjoncteurs-moteurs → Disjoncteurs-moteurs

