


Ref. 6962 VDS VIDEO CITY KEYPAD AMPLIFIER



DESCRIPTION

VIDEO Amplifier module of spare parts for inclusion in CityLine electronic door entry panels with KEYPAD / DISPLAY.

Installed in the accesses to the building, they enable communication with homes, door opening, guard unit call , etc.

New Cityline Panel: CityLine is the "continuous profile" outdoor panel line for buildings.

This new panel model is more robust, more luxurious and higher design and functional quality. The new design, in its video entry version, includes audio and video functions in the same module.

Colour aluminium

Injected zamak chrome finish Call buttons, in line with the curved panel profile. Sealed for outdoors.

Equipped with special gold plated contacts for lasting durability.

Pressing the call button is confirmed by an acoustic signal from the amplifier.

Pushbuttons include a polycarbonate card slot (front access) to insert a label with the home owner's name and door number. Built in lighting lets you see the card slots, even in pitch dark.

It is possible to combine two or more panels, as long as they are from the same series. For a perfect fit, a set of separators should be used for every two panels installed between their flush mounted boxes.

Colour aluminium

Pressing the call button is confirmed by an acoustic signal from the amplifier.

VDS system:

Simplified installation audio and video door entry system that does not use house call wires. The call is made by transmission of a digital call code generated by the VDS amplifier.

- In new works, installation can be carried out with the following type of wiring: UTP CAT5 / 5 wire / 3 wire + Coaxial (video).

Lets you manage up to 199 homes, 2 entrance accesses and a central guard unit.

Maximum distance from first access to last home: 200 m.

- In replacement works, the change from analogue entry to video entry system can be done taking advantage of the existing wiring.



The system capacity and distance will depend on the installation wiring.

VDS amplifier comes with voice synthesizer as standard issue.

When the door release is activated a message is heard: "Door open, please close after entering".

The home terminals require simple programming done from the outdoor panel. By means of this programming a call code is assigned to each terminal (telephone or monitor).

Communication is private.

Wiring. Audio: 3-wire bus. Video: UTP CAT5 / 5 wire / 3 wire + Coaxial (video).

Maximum distance from first access to last home: 200 m.

TECHNICAL SPECIFICATIONS

Power supply: 18 Vdc

Consumption:

- Standby: 40 mA

- Active audio: 250 mA

- Lighting per lamp: 70 mA

IPK Panel-437

Audio capacity home-outdoor panel: 2W

Audio capacity outdoor panel-home: 0.15W

Two-way volume control

Operating temperature: -10 to 60 °C