

# DMS-26

B04625

## DESCRIPTION

The perfect all-in-one solution to secure your DMX-installations: MERGER + SPLITTER + BOOSTER

## FEATURES

- The perfect all-in-one solution to secure your DMX-installations: MERGER + SPLITTER + BOOSTER
- 100% electrical isolation between all in/outputs!
- 2 DMX-inputs + 6 DMX-outputs, each equipped with 3pin and 5pin XLR-connectors.
- The booster function analyses the incoming DMX-signal and builds it back up from scratch to make it perfect for further use.
- The merger function combines 2 DMX-signals in different ways:
  - **HTP:** the highest value of 2 identical channels from 2 DMX-signals will have priority.
  - **Backup:** when the DMX-signal on input A fails, the DMX-signal in input B takes over immediately.
  - **Merger:** DMX-signals from 2 different controllers can be combined and send over 1 cable, you can choose the start address of the second controller.
- The splitter function distributes the DMX-signal(s) from the input(s) over 6 identical outputs that are 100% isolated from each other: problems that occur on 1 output will not influence the other outputs!
- The timing of the DMX-outputs can be adapted from 23ms to 45ms, increasing compatibility while connecting "slow" DMX-devices to "fast" DMX-controllers.
- Output behavior can be selected when suddenly both DMX-inputs fail:
  - *Null: no DMX signal on the outputs*
  - *Hold: keep the last DMX values on the outputs.*
  - *Clear: set the DMX values on all outputs to zero.*
- Easy setup via 4digit LED display



[www.briteq-lighting.com](http://www.briteq-lighting.com) | <https://www.facebook.com/Briteq>

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2021 by BEGLEC NV. All rights reserved.



## TECHNICAL SPECIFICATIONS

<b>General : Application</b>	DJ & Club, Stage & Rental, Theatre
<b>General : Series</b>	N/A
<b>General : Dimensions (cm)</b>	48.2 x 4.4 x 15.0 cm
<b>General : Weight (kg)</b>	2.92
<b>General : Powerinput</b>	AC 240V, 50Hz
<b>General : Energy Label</b>	No
<b>General : Color</b>	black
<b>General : Display</b>	LED
<b>General : Fixation</b>	19" rack mountable
<b>General : RU</b>	No
<b>Control : programmable</b>	No
<b>Control : upgradable software</b>	No
<b>Connections : input</b>	3 pin XLR, 5 pin XLR, IEC
<b>Connections : output</b>	3 pin XLR, 5 pin XLR
<b>Brand</b>	BRITEQ
<b>EANCode</b>	5420025646253

## YOUR DEALER



[www.briteq-lighting.com](http://www.briteq-lighting.com) | <https://www.facebook.com/Briteq>

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2021 by BEGLEC NV. All rights reserved.